

StarTech.com RK4OD2 19 Inch Open Frame 2-Post Desktop Rack User Guide

Contents

- [1 RK4OD2 19 Inch Open Frame 2-Post Desktop Rack](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
 - [3.1 Documents / Resources](#)
 - [3.1.1 References](#)

RK4OD2 19 Inch Open Frame 2-Post Desktop Rack

Product Information

The 19in Open Frame 2-Post Desktop Rack is a product designed to provide a convenient and secure way to organize and mount equipment. It comes in two product IDs: RK4OD2 and RK8OD2, with varying weight capacities of 88 lb (40 kg) and 110 lb (50 kg), respectively. The product includes vertical rails, front base brackets, rubber feet holes, assembly holes, base brackets, M6 cage nuts, M6x12 mm screws, and M6 plastic washers. The rack is designed to be used on a desk or table that can support at least two times the weight of the mounted equipment.

Product Usage Instructions

1. Read the entire quick-start guide and ensure the instructions are fully understood before assembling and/or using this product.
2. Ensure that the desk or table where the rack will be placed can support at least two times the weight of the mounted equipment.
3. Assemble the rack by following these steps:
 1. Push from the top to unlatch the pins (x 4) from the center of the rubber feet (x 4).
 2. Push the rubber feet (x 4) into the rubber feet holes (x 4) on the underside of the left base bracket and right base bracket. Next, push from the bottom to latch the pins (x 4) back into the center of the rubber feet.
 3. Align the assembly holes (x 2) on the side of the left base

bracket with the assembly holes (x 2) on the side of the left vertical rail.

4. Align the front base bracket with the assembly holes on the front of the left base bracket.
5. Repeat steps 3 and 4 with the right base bracket and the right vertical rail.
6. Insert the M5x12 mm assembly screws (x 2) through the front base bracket and into the left base bracket. Tighten the assembly screws (x 2) using a Phillips head screwdriver.
7. Repeat steps 6 and 7 for the right base bracket.
4. Arrange your equipment in the rack in descending order of weight. The lightest device should be installed at the top of the rack, and the heaviest device should be on the bottom of the rack.
5. Install the M6 cage nuts onto the desired cage nut holes where the equipment will go. Use a cage nut tool if available or your preferred installation method.
6. Use a Phillips head screwdriver to install the M6x12 mm screws and secure the equipment onto the rack.
7. Caution! Do not move the rack with the equipment mounted. If relocation of the rack is required, remove the equipment from the rack and relocate the empty rack. Mount the equipment back into the rack.

[View Fullscreen](#)



Quick-Start Guide

19in Open Frame 2-Post Desktop Rack Product IDs

RK4OD2 RK8OD2

Product Diagram

1

Package Contents

· Left Base Bracket x 1 · Right Base Bracket x 1 · Left Vertical Rail x 1 · Right Vertical Rail x 1 · Front Base Bracket x 1 · M5x12 mm Assembly Screws x 8 · Rubber Feet x 4 · Quick-Start Guide x1

Product ID

M6 Cage Nuts Quantity

RK4OD2

x 16

M6x12 mm Screws

M6 Plastic

Quantity

Washers Quantity

x 16

x 16

RK8OD2

x 32

x 32

x 32

2

Component 1 Vertical Rails 2 Front Base Bracket 3 Rubber Feet Holes 4 Assembly Holes 5 Base Brackets

3

Requirements

5 4

*Product may vary from image

Function · Feature Square Cage Nut Holes to mount your equipment. · Ranges from 4U to 8U according to the model.

- Stabilizes the frame and adds rigidity.
- Insert the Rubber Feet to protect the surface.
- Used to connect the Vertical Rails, Front Base Bracket, and Base Brackets together.
- Stabilizes the frame and adds rigidity.

For the latest manuals, product information, technical specifications, and declarations of conformance, please visit:

www.startech.com/RK4OD2

www.startech.com/RK8OD2

· Phillips head screwdriver · Cage nut tool (Optional)

Warnings!

Read the entire quick-start guide and ensure the instructions are fully understood before assembling and/or using this product.

Before adding equipment to this product, ensure this product has been properly assembled.

Never operate this product if parts are missing or damaged.

Ensure the weight of the equipment does not exceed the weight capacity of this product. If the weight capacity is exceeded, personal injury or damage to the equipment are possibilities. These products can support the following weight: 88 lb (40 kg) for RK4OD2 and 110 lb (50 kg) for RK8OD2.

This product poses a tipping risk. To view manuals, FAQs, videos, drivers, downloads, technical drawings, and more, visit www.startech.com/support.

To view manuals, FAQs, videos, drivers, downloads, technical drawings, and more, visit www.startech.com/support.

Manual Revision: August 8, 2022 12:39 PM

The desk or table should be capable of supporting at least two times the weight of the mounted equipment.

Installation

Assemble the Rack

1. Push from the Top to Unlatch the Pins (x 4) from the center of the Rubber Feet (x 4).
2. Push the Rubber Feet (x 4) into the Rubber Feet Holes (x 4) on the underside of the Left Base Bracket and Right Base Bracket. Next, Push from the Bottom to Latch the Pins (x 4) back into the center of the Rubber Feet.
3. Align the Assembly Holes (x 2) on the side of the Left Base Bracket with the Assembly Holes (x 2) on the side of the Left Vertical Rail. (Figure 1)

Left Base Bracket

Left Vertical Rail Front Base Bracket

5. Repeat Steps 3 and 4 with the Right Base Bracket and the Right Vertical Rail.
6. Align the Assembly Holes (x 2) on the Front Base Bracket with the Assembly Holes on the front of the Left Base Bracket.
7. Insert the M5x12 mm Assembly Screws (x 2) through the Front Base Bracket and into the Left Base Bracket. Tighten the Assembly Screws (x 2) using a Phillips Head Screwdriver.
8. Repeat Steps 6 and 7 for the Right Base Bracket.

Operation

Arrange your equipment in the rack in descending order of weight. The lightest device is installed at the top of the rack and the heaviest device is on the bottom of the rack. 1. Install the M6 Cage Nuts onto the desired Cage Nut Holes where the Equipment

will go. Use a Cage Nut Tool if available or your preferred installation method.

2. Use a Phillips Head Screwdriver to install the M6x12 mm Screws and secure the Equipment onto the rack.

Caution! Do not move the rack with the equipment mounted. If relocation of the rack is required, remove the equipment from the rack and relocate the empty rack. Mount the equipment back into the rack.

M5x12 mm Assembly Screws

Figure 1

4. Insert the M5x12 mm Assembly Screws (x 2) through the Left Base Bracket and into the Left Vertical Rail. Tighten the Assembly Screws (x 2) using a Phillips Head Screwdriver.

Regulatory Compliance

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of thirdparty companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders. PHILLIPS® is a registered trademark of Phillips Screw Company in the United States or other countries.

Warranty Information This product is backed by a lifetime warranty. For further information on product warranty terms and conditions, please refer to www.startech.com/warranty.

Limitation of Liability In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

Safety Measures · Read the entire manual and ensure the instructions are fully understood before assembling and/or using this product.

Mesures de sécurité · Assemblez ce produit conformément aux instructions.

.

Misure di sicurezza · Assicurarsi di Assemblare il prodotto secondo le istruzioni.

Säkerhetsåtgärder · Se till att du monterar produkten i enlighet med instruktionerna.

StarTech.com Ltd.

45 Artisans Crescent London, Ontario N5V 5E9 Canada

StarTech.com LLP

4490 South Hamilton Road Groveport, Ohio 43125 U.S.A.

StarTech.com Ltd.


Unit B, Pinnacle 15 Gowerton Road Brackmills, Northampton NN4 7BW United Kingdom

StarTech.com Ltd.

Siriusdreef 17-27 2132 WT Hoofddorp The Netherlands

FR: startech.com/fr DE: startech.com/de ES: startech.com/es NL: startech.com/nl IT: startech.com/it JP: startech.com/jp

Documents / Resources

	StarTech.com RK4OD2 19 Inch Open Frame 2-Post Desktop Rack [pdf] User Guide RK4OD2 19 Inch Open Frame 2-Post Desktop Rack, RK4OD2, 19 Inch Open Frame 2-Post Desktop Rack, Open Frame 2-Post Desktop Rack, Frame 2-Post Desktop Rack, 2-Post Desktop Rack, Desktop Rack, Rack
-------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

References

- [StarTech.com | IT Pro's Trusted Source for Connectivity Accessories](#)
- [Unsere Produkte dienen IT- und A/V-Profis zum Verbinden, Konvertieren, Erweitern, Splitten und Switchen | Deutschland](#)
- [StarTech.com diseña y fabrica una variada gama de componentes para ordenadores, cables, conmutadores KVM, racks para... | España](#)
- [StarTech.com conçoit et fabrique une vaste sélection de pièces d'ordinateur, de câbles, de commutateur KVM, de racks... | France](#)
- [Pezzi per computer, cavi, switch KVM, server rack e soluzioni per reti | Italia](#)
- [IT & A / V](#)
- [StarTech.com ontwerpt en produceert een enorme selectie computeronderdelen, kabels, KVM-switches, serverracks en... | Nederland](#)
- [4U 19in Desktop Open Frame Rack 2-Post - Server-Racks | StarTech.com](#)
- [All Products | StarTech.com](#)
- [StarTech.com Support](#)
- [StarTech.com Warranty Policy](#)

