

Sunco

**SUNCO 38838
Spark Square
Ceiling Light**



SUNCO 38838 Spark Square Ceiling Light Instruction Manual


[Home](#) » [SUNCO](#) » SUNCO 38838 Spark Square Ceiling Light Instruction Manual 

Contents

- [1 SUNCO 38838 Spark Square Ceiling Light](#)
- [2 LED DESIGNER SURFACE MOUNT INSTALL INSTRUCTIONS](#)
- [3 4" J-BOX COMPATIBILITY](#)
- [4 SURFACE MOUNTED WITH 4" J-BOX](#)
- [5 SURFACE MOUNTED WITH J-BOX – SQUARE](#)
- [6 RECESSED CAN 4" or 6"](#)
- [7 Documents / Resources](#)
 - [7.1 References](#)

Sunco

SUNCO 38838 Spark Square Ceiling Light



LED DESIGNER SURFACE MOUNT INSTALL INSTRUCTIONS

PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION. Please read the instructions before you

install and use the luminaire.

GENERAL: ALL ELECTRICAL CONNECTIONS MUST BE IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRICAL CODE (N.E.C.) STANDARDS. IF YOU ARE UNFAMILIAR WITH PROPER ELECTRICAL WIRING CONNECTIONS OBTAIN THE SERVICES OF A QUALIFIED ELECTRICIAN. REMOVE THE TRIM FROM THE BOX AND MAKE SURE THAT NO PARTS ARE MISSING.

- WARNING – Risk of fire or electric shock. LED Retrofit Kit installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician.
- WARNING – Risk of fire or electric shock. Install this kit only in luminaires that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire
- Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation
- WARNING – To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects Risk of Electric Shock: Disconnect power or circuit breaker before installing or servicing.
- WARNING DISCONNECT POWER BEFORE INSTALLING OR SERVICING.

4" J-BOX COMPATIBILITY

Compatible with most standard 4" J-Boxes with a minimum height of 1.5". Not all existing J-Boxes meeting these requirements will be compatible. A test installation should be preformed.

SURFACE MOUNTED WITH 4" J-BOX

1. Make sure power is turned off.
2. Attach mounting bracket to the J-Box using the 2 provided screws. Note the flat side of the mounting bracket should be facing down once installed. (Fig 1)
3. Attach safety clip to one of the holes in the mounting bracket. (Fig 2)
4. Insert existing wire ends from the J-Box to the LED adapter. Black wire to (+) , White wire to (-). Make sure both wires are tightly secured in the LED adapter.
5. Connect the end of the LED adapter coming out of the J-Box to the fixture and wire the grounds together using the provided wire nut.
6. Push fixture up into the mounting bracket until it clicks into place. Make sure all wires are carefully tucked inside the J-Box and fixture is flush with the ceiling.
7. Installation complete, restore power.




FIG. 1





FIG. 2

SURFACE MOUNTED WITH J-BOX – SQUARE



4" and 6" HOUSING COMPATIBILITY

Compatible with most standard IC and Non-IC Housings. 4" housing aperture 3.82-4.07". 6" housing aperture 5.91-6.18". Not all existing housing meeting these requirements will be compatible. A test installation should be preformed.


- Suggested replacements:
- 6" – Surface Mount replaces 4" Cans
- 7" – Surface Mount replaces 4" and 6" Cans 9" – Surface Mount replaces 6" Cans

RECESSED CAN 4" or 6"

1. Make sure power is turned off.
2. Insert 3 mounting clips according to can size. (Fig. 3)
3. Screw the E26 adapter into the recessed socket. Attached ground wire to recessed housing using attached ground screw or use existing bolt inside housing and provided nut.
4. Make sure all wires are carefully tucked inside the housing and gently push the fixture up until it's flush with the ceiling surface.
5. Installation complete, restore power.

FIG. 3

4" Recessed Can spring spots



6" Recessed Can spring spots

Documents / Resources

	<p>SUNCO 38838 Spark Square Ceiling Light [pdf] Instruction Manual</p> <p>38838 Spark Square Ceiling Light, 38838, Spark Square Ceiling Light, Square Ceiling Light, Ceiling Light, Light</p>
---	---

References

- [User Manual](#)

Manuals+, Privacy Policy

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.