

# SUNRICHER IP65 ZHAGA-BOOK 18 BLE 0-10V Sensor Controller Owner's Manual

## SUNRICHER IP65 ZHAGA-BOOK 18 BLE 0-10V Sensor Controller

### Contents

#### 1 TAYYEB POST

- 1.1 Features
- 1.2 Parameters
- 1.3 Dimension
- 1.4 Product Info
- 1.5 Product Description
- 1.6 Operation
- 1.7 Application
- 1.8 System Overview
- 1.9 Specification
- 1.10 Profile Configuration
- 1.11 Comfort & Convenience
- 1.12 Daylight Harvesting
- 1.13 Detection Pattern
- 1.14 Detection Area
- 1.15 Wiring
- 1.16 Statement
- 1.17 Update Log
- 1.18 Documents / Resources
  - 1.18.1 References

---

## TAYYEB POST

### Features

- Bluetooth to 0-10V sensor controller , Bluetooth® mesh network
- Mesh network, which has a much longer control distance, transmits received signals to neighboring devices
- All devices on 0-10V line are broadcast controlled by mobile application
- Supporting our kinetic energy switches and EnOcean switches EWSSB and EWSDB
- Autonomos sensor-based control
- ZHAGA Book 18 socket
- Available with Magnetic reset (touch the top part of sensor for 5 seconds)
- On-board antenna
- Waterproof grade: IP65, suitable for outdoor luminaries
- 5 years warranty

## Parameters

Electrical Information	
Power Supply	12-24 VDC
0-10V Signal Output	20mA
Control	0-10V
Marking Terminals	V+,DIM+, GND(DIM-)
Status Indicators	Green(commissioning), Red(motion detection)
Sensing	
Motion Detection	PIR
Daylight Harvesting	YES
Mounting Height	Up to 14m, recommended height: 6-12m
Detection Angle/Range	360° (ceiling)/16m(Diameter)
Environment	
Operating Temperature Range	-20°C to 40°C
Operating Humidity	0-95%(non-condensing)
Safety Certification	cULus Listed, CE

## Dimension

## Product Info

### Zhaga Receptacle Accessory(optional for order)

1. Port 1 (Brown): VCC (12-24V)
2. Port 2 (Gray): GND/ Dim- 0-10V signal
3. Port 3 (Blue): No connection
4. Port 4 (Black): DIM+ 0-10V signal

## Product Description

- The IP65 motion sensor combines motion sensor and light sensor. The device performs motion detection and measures illuminance level. With standard ZHAGA Book 18 interface socket, the sensor can easily fit into various luminaires with no tools required.
- The result is increased occupant comfort and significant energy savings that meet the most demanding building energy codes. The sensor is IP65 rating, which enables it to be used for outdoor luminaires.

## Operation

- Do wiring according to connection diagram.
- Kindly refer to “Silvair Commissioning User Manual” for further pairing.
- Available with Magnetic reset(Touch the top part of sensor for 5 seconds).

## Application

Indoor Low/High-bay Application

Outdoor Application

## System Overview

## Specification

### Energy Savings

- Low/High-end trimming
- Occupancy/Vacancy detection
- Auto and advanced demand response programs
- Time-of-Day dimming schedule
- Energy monitoring

### Profile Configuration

- Occupancy Profile
- Vacancy Profile
- Photocell Profile

### Comfort & Convenience

- Advanced occupancy detections
- Light-level stability
- Configurable dim-and-linger occupancy
- Personalized setting profile
- Work with kinetic switch keypad and dimmer wallstation
- Multi-scenes control
- Magnetic Reset

### Daylight Harvesting

- **Note:** Due to the light sensor being inside in component and with a semi-transparent enclosure, this component is not precise in lux measurements. Thus this component may not suitable for daylight harvesting usage.
- Please only use the daylight harvesting featured scenario if users conducted field tests and accepts the tolerance level.

## **Warning**

- DO NOT install with power applied to device.
- DO NOT expose the device to moisture.

## **Detection Pattern**

### **Coverage Side View**

### **Coverage Top View**

**The detection area for movement sensor can be roughly divided into two parts:**

Slow movement (person moving < 1.0'/s or 0.3m/s)

Quick movement (person moving > 1.3'/s or 0.4m/s)

## **Detection Area**

### **Note:**

1. Following different detection areas are based on different installation heights & patterns.
2. For all detection areas, the sensitivity is set to 0 the highest.
3. Detection Pattern is a relevant value, the performance should depends on the site conditions installation height/ temperature/ humidity/ Blind area...etc)

Detection pattern at floor level (12 height)

Detection pattern at floor level (15 height)

## **Wiring**

**Note:** please make sure the polarity of 0-10V signal of the sensor is correctly connected.

## **Statement**

### **FCC STATEMENT**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:**

- 1. This device may not cause harmful interference, and
- 2. This device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate the equipment.

**IC STATEMENT**

**This device complies with Industry Canada’s licence-exempt RSSs. Operation is subject to the following two conditions:**


- 1. This device may not cause interference.
- 2. This device must accept any interference, including interference that may cause undesired operation of the device.

**Update Log**

Date	Versio n	Update Content	Update by
2024-5-21	V1.1	Parameter Update	Romeo

Subject to change without notice. Please contact us if you have any questions.

**Documents / Resources**

	<a href="#">SUNRICHER IP65 ZHAGA-BOOK 18 BLE 0-10V Sensor Controller</a> [pdf] Owner's Manual SR-SV9033A-PIR-V, IP65 ZHAGA-BOOK 18 BLE 0-10V Sensor Controller, IP65 ZHAGA-BOOK 18 BLE 0-10V, Sensor Controller, Controller
---	---

**References**

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.