



Techage 202212 Xmeye WiFi Camera System User Manual

[Home](#) » [Techage](#) » Techage 202212 Xmeye WiFi Camera System User Manual 



WiFi NVR User Manual



Security Expert for Your Home and Business



<http://d.xmeye.net/XMEye>
XMEye Pro App


Contents

- 1 Preface
- 2 NVR Overview
- 3 NVR Installation
- 4 Function Setting
- 5 Add WiFi Camera
- 6 Remote View
- 7 Documents / Resources
- 8 Related Posts

Preface

Thanks for purchasing our WiFi Network Video Recorder Surveillance products. This user manual is for 8CH Xmeye WiFi NVR. This WiFi NVR supports Onvif protocol, so you can add WiFi cameras from other brands which also support Onvif protocol.

NVR Overview



IR: To receive infrared remote control signal.

PWR: It will be on when the NVR is plugged in power adapter (12V2.5A-12V3A).

REC: It will be on when the NVR set up recording.

ALARM: It will be on when the NVR received alarm attention.


Directions: Choose different options on NVR, left or right, up or down.

BACK: Back to previous step.

NEXT: Go to next step.

MENU: Enter main menu directly.

ESC: Leave the current option/window, cancel or back to previous option.



DC12V: For power supply DC 12V, the size of the DC plug is 5.5*2.1mm.

USB: For USB mouse to control NVR or USB disk to backup video.


WAN: Ethernet port for connecting to the router.

HD-PORT: For connecting the monitor or display with HDMI cable.

VGA: For connecting the monitor or display with VGA cable.

AUDIO OUT: For connecting speakers to play the recorded audio.

Connect your System



Step 1: Power on the cameras with power adapter.

Step 2: Power on the NVR with its power adapter (12V2.5A).

Step 3: Make sure your network is 2.4GHz and WiFi signal is good.

Step 4: Connect the NVR to your router by LAN cable (Cable length within 20 meters).

Step 5: Connect the cameras to your router by WiFi signal.

Step 6: Connect the NVR to monitor by VGA or HDMI cable.



Notice: Please make sure the cameras and the NVR are connected to the same router.

Cameras Installations

When you install the cameras, please make sure to avoid the inaccurate ways of installations.

Wrong Viewing Angles

Right Way: Adjust the directions of the camera lens and make sure the lens of the camera are away from the wall.

Close Object Reflects

Right Way: Move the objects away from the camera lens or change the camera's installation position.

Close Wire Cable Reflects

Right Way: Move the power cable or Ethernet cable away from the camera lens and fix it on the back of the camera.

NVR Installation

1.1 Hard Disk Installation

Please install the hard disk first. If not, the video recorder can only monitor normally, but cannot record or playback.



① Remove the case



② Plug in SATA cable



③ Screw HDD to the bottom



④ Install the case back

! **Notice:** Please choose a specialized monitoring hard drive disk in order to record for a longer time. The video recorder supports 3.5" or 2.5" SATA hard disk.

! **Warning:** please make sure the power is off before installation.

1.2 Boot & Preview

Make sure the power supply matches the requirements of the hard disk video recorder.

After connecting the power, the indicator on the front of the NVR will light on and you will hear a buzzer sound, then the display will boot up and the device will access to the preview image. After the recovery of the non-normal power failure, the device will automatically return to the state it was in before the power outage.

Function Setting

2.1 Login System

SYSTEM LOGIN

User Name

Password

[Modify Pwd](#)

The current factory default user password is displayed in clear text. For safety, please modify it as soon as possible!

Login

Cancel

Set Pattern

Please draw the unlock pattern.

Skip

The current factory default user password is displayed in clear text. For safety, please modify it as soon as possible.

Then please draw the unlock pattern to set up your new password.

2.2 HDD Setup

Right click the mouse→ Main Menu → Advanced → HDD Info

HDD Info

SATA 1

-

Type	Capacity	Left Capacity	Status
------	----------	---------------	--------

Format Storage

Recover

Partition

Read/Write

Redundant

Snapshot

Read only

View recording times

Cancel

Choosing the Hard Disk, clicking Format Storage, starting to format the HDD.


! **Notice:** Please confirm the hard disk is connected. The hard disk should be formatted before first use, so that it can record properly. It will automatically overwrite previous videos when the storage of hard disk is full if you set overwrite.

2.3 General

Right click the mouse → Main Menu → System → General



[Language] You can set the system language to the native language.



[Storage Full]

Choose Overwrite: Keep recording video and automatically overwrite the former video while the storage of HDD is full.

Choose Stop: Stop recording video while the storage of HDD is full.

[Auto Logout] You can set up a 0-60 min auto standby. 0 min means you haven't set up the standby time.

[Startup Wizard] Tick it to get startup wizard when reboot the system (untick it as default).

2.4 Record Setup

In the Record Configuration, you can set up the record mode for each channel to save space of the HDD and only record the important videos.

Right click the mouse→ Main Menu → Record Conf.



The 'Record Conf.' dialog box is used for configuring recording settings for a specific channel. It includes fields for Channel, Length, Mode, Week, and a table for recording periods with checkboxes for Regular, Detect, and Alarm recording. At the bottom are buttons for Advanced, OK, and Cancel.

Channel	Length	Mode	Week	Period	Regular	Detect	Alarm
1	60 min	Schedule	All	Period 1	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
				Period 2	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
				Period 3	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
				Period 4	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

[Channel] The channel which you want to do settings of record configuration.

[Length] The standard length of each video segment.


[Mode] The way you want to record videos.

- » Schedule: The selected channel will only record during the chosen time period.
- » Regular: The system will keep recording during the chosen time period.
- » Detect: The system will record a video segment when the camera detects movements during the chosen time period.
- » Alarm: The system will record a video segment when the camera alarms during the chosen time period.
- » Manual: The selected channel will record 24/7.
- » Stop: The selected channel will not record any video.

! **Notice:** If you would like to set the recording mode to “Alarm”, please make sure that you have enabled the alarm function of the corresponding channel.














2.5 Video Playback

Right click the mouse→ Main Menu → PlayBack



In the “Common Playback”, you can playback recorded video according to date, time, channel and mode.


1. Choose Play Mode
2. Choose Video Date
3. Playback Channel Option
4. Video Playback Time
5. Playback Control Key

 Start Playback	 Play Backward
 Stop Playing	 Slow Playback
  Rewind/Fast-forward	  Prev/Next Frame
  Prev/ Next File	 Repeat Playback
 Full Screen	 Start Editing

Click the “**Smart Express**”, you can choose different alarm type files for fast playback.


Click the “**Smart Search**”, all recorded videos, which detected motions or humans will be displayed.

Click the “**Face Search**”, all recorded videos, which detected human faces will be displayed.



2.6 Video Backup

Right click the mouse→ Main Menu → System → Backup




Choose Video Type → Channel → Time , clicking Add button to search video file, choosing the file in the list, clicking Start button to backup and it will automatically prompt after backup completed.

Notice: USB disk must be FAT32 format. Please choose AVI format while backup, so that the backup video could be played on PC directly.

2.7 Snapshot Configuration

Right click the mouse→ Main Menu → System → SnapShot Conf.



SnapShot Conf.

Channel

☐ Cycle capture

☐ EMAIL Sec.

☐ FTP Sec.

☐ storage Sec.

☐ Timing capture

0	Capture time	Delete	EMAIL	FTP	storage

☐ EMAIL ☐ FTP ☒ storage

Capture time

☒ Stop

[Cycle capture] The camera will take snapshots periodically when you choose Cycle capture. For example, if the default snapshot period is 64 seconds, it means the camera will automatically take snapshot every 64 seconds.

[EMAIL] Tick it and the NVR will send the snapshots captured by the cameras to your e-mail address.


[FTP] Tick it to enable this function. Buyers need to build their own ftp service by themselves.

[storage] Tick it and the NVR will store the snapshots captured by the cameras in the HDD.

[Timing capture] The camera will take snapshots at the time that you set when you choose Timing capture.

Network

Net Card	Wired NIC ▼	<input type="checkbox"/> DHCP Enable
IP Address	192 . 168 . 3 . 39	
Subnet Mask	255 . 255 . 255 . 0	
Gateway	192 . 168 . 3 . 1	
Primary DNS	192 . 168 . 3 . 1	
Secondary DNS	8 . 8 . 8 . 8	
Media Port	34567	
HTTP Port	<input checked="" type="checkbox"/>	80
HS Download	<input type="checkbox"/>	
Transfer Policy	Quality Prefe ▼	
Network encryption	No limited ▼	
NetService		
Wireless Channels		


 APP

[http://d.xmeye.net/xmeye?](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTE0MTI0YTAxNNkFP0dd77wZSgewpQuv3UP5LkGrSaeJ5J+PWqEGkeB3KQ4npzclj+7boiMgTC8aaA==)

[ctim=220711&firv=C6380243&sv=MTBmNzE2MTE0MTI0YTAxNNkFP0dd77wZSgewpQuv3UP5LkGrSaeJ5J+PWqEGkeB3KQ4npzclj+7boiMgTC8aaA==](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTE0MTI0YTAxNNkFP0dd77wZSgewpQuv3UP5LkGrSaeJ5J+PWqEGkeB3KQ4npzclj+7boiMgTC8aaA==)

[DHCP Enable] Tick it to automatically obtain the IP address assigned by the server.

[IP Address] It has to be a unique IP address on the same LAN segment to avoid conflicts with other equipment in local area.

[HTTP Port] A port number for remote visit, default value is 80.

[NetService] Here you can enable functions like RTSP, FTP, Email and other services.

[Wireless Channels] The channel number about NVR.

2.9 Check Nat Status

Right click the mouse → Main Menu → Advanced → Version

Version

System	V4.03.R11.C6380243.12201.140016.0000000
Build Date	2021-10-12 17:15:08
Original	1
MAC	0012424d22a0
Serial Number	c541676f2b254081
Record Channel	8
Status	222
Nat status	Connected
Nat status code	2:139.9.201.39/1/+111
Device Info.	
SSID	WIFINVR0012424d22a0


 APP

[http://d.xmeye.net/xmeye?](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKIsS7hEhpw4z7lcaX2207pni6l)

[ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKIsS7hEhpw4z7lcaX2207pni6l](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKIsS7hEhpw4z7lcaX2207pni6l)

[1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==](#)


[Serial Number] Device Serial Number for remote view.

[Nat Status] Check the network status, begin a remote monitoring when shows connected.

[Device Info] Edit function like playback preview, face and human detection.

2.10 Email Setup


Right click the mouse→ Main Menu → Network → NetService → EMAIL



The 'Network' window contains the following fields and controls:

- Net Card: Wired NIC (dropdown), DHCP Enable (checkbox)
- IP Address: 192 . 168 . 3 . 39
- Subnet Mask: 255 . 255 . 255 . 0
- Gateway: 192 . 168 . 3 . 1
- Primary DNS: 192 . 168 . 3 . 1
- Secondary DNS: 8 . 8 . 8 . 8
- Media Port: 34567
- HTTP Port: ☒ 80
- HS Download: ☐
- Transfer Policy: Quality Pref (dropdown)
- Network encryption: No limited (dropdown)
- Buttons: NetService, Wireless Channels
- Buttons: OK, Cancel

A QR code is displayed on the right side of the window, labeled 'APP'.




The 'NetService' window displays the following information:

NetService	Net Server Info
PPPoE	0:
NTP	0: NTP:60
EMAIL	0: Your SMTP Server:25
IP FILTER	0: :0 :0
DDNS	DDNS Set Invalid
FTP	0: FTP
ARSP	
AlarmServer	0:
UPNP	0
RTSP	1: 554
Cloud	Connected
Mobile reported	Enable

Buttons: OK, Cancel

<http://d.xmeye.net/xmeye?>

[ctim=220711&firv=C6380243&sv=MTBmNzE2MTE0MTI0YTAxNNkFP0dd77wZSgewpQuv3UP5LkGrSaeJ5J+P
WqEGkeB3KQ4npzclj+7boiMgTC8aaA==](#)



[SMTP Server] Sender's mailbox (for example: gmail / email).

[Port] Sender's mailbox SMTP port.

[Encryption] SSL.

[User Name] Username of the sender's mailbox (must support and open SMTP function).

[Receiver] Receiver's mailbox.

[Password] Password of the sender's mailbox. Go to get 16-digit app password on your email setting.


[Mail Testing] Click and it will send an email to receiver to test the Email setting.





Notice: Before testing the Email, please confirm the Network has been connected successfully.

• How To Get 16-Digit App Password

Enable IMAP access of your e-mail.



Log in your Google account. In "Security" section, find "Signing in to Google". If the "2-Step Verification" is off, please enable it.



You will get a 16 digits password that you need to use later to set up your email notice in NVR system.

← App passwords

App passwords let you sign in to your Google Account from apps on devices that don't support 2-Step Verification. You'll only need to enter it once so you don't need to remember it. [Learn more](#)

You don't have any app passwords.

Select the app and device for which you want to generate the app password.

Select app ▼ Select device ▼

GENERATE

← App passwords

App passwords let you sign in to your Google Account from apps on devices that don't support 2-Step Verification. You'll only need to enter it once so you don't need to remember it. [Learn more](#)

You don't have any app passwords.

Select the app and device for which you want to generate the app password.

Google Chrome X

GENERATE

You will get a 16 digits password that you need to use later to set up your e-mail notice in NVR system.

← App passwords

Generated app password

Your app password for your device

XXXX XXXX XXXX XXXX

How to use it

Go to the settings for your Google Account in the application or device you are trying to set up. Replace your password with the 16-character password shown above. Just like your normal password, this app password grants complete access to your Google Account. You won't need to remember it, so don't write it down or share it with anyone.

DONE


Email
abc@gmail.com

Password
••••••••••

! **Notice:** You are not able to review the password after you click "DONE" so please write it down or leave this page open.

2.11 User Management

Right click the mouse → Main Menu → System → Account




[Modify Pwd] Enter to Modify Password page, and modify password.

[Add User] Add User account and set up the User's permissions. Enter the Add User page and input the User Name and Password.

! **Notice:** Password can be setup as number+letter combination, please record your password in other ways and keep it in a safe place to avoid forgetting.

2.12 Alarm


Right click the mouse→ Main Menu → Alarm



! **Notice:** The NVR supports intelligent alerts, such as motion, human and face detection. You can set different intelligent alerts if your cameras also support these functions through the following operations.

2.12.1 Intelligent Alert Setting

Right click the mouse→ Main Menu → Alarm → Intelligent Alert



The 'Intelligent Alert' window has a title bar with the same name. It contains the following elements: a 'Channel' dropdown menu set to '1', an 'Enable' checkbox which is checked, and a 'Human Detect' checkbox which is also checked. Below these is a bordered box titled 'Human Detect' containing three sub-options: 'Record' (checked), 'Mobile reported' (checked), and 'Alarm Sound' (unchecked). At the bottom of this box is an 'Advanced' label and a 'Set' button. Outside the box, there is a 'Sensitivity' dropdown menu set to 'Middle' and a 'Rule' label with a 'Set' button. At the very bottom of the window are three buttons: 'Advanced', 'OK', and 'Cancel'.

[Channel] Choose the camera which you want to do alert settings.

[Enable] When it is unticked, the camera will not detect any movements.

[Human Detect] The camera will detect all movement like human, car, animals and other objects.


[Record] When it is ticked on, the camera will record a video segment when human/face detected.

[Mobile reported] When it is ticked on, the camera will send alert notifications to your mobile App when it detects movements or human activities.

[Alarm Sound] When it is ticked on, the camera will make a voice alarm when it detects movements or human activities.


[Sensitivity] Adjust the detection sensitivity of the camera.

[Rule]Set advanced detection rules like safe zone or line cross alarm.

 **Notice:** We recommend you to active “Human Detect” to reduce false alerts. It shows that “Human Detect” function can reduce 98%-99% of the false alerts.

2.12.2 Advanced Setting of Human Detection/Face Detection

Right click the mouse→ Main Menu → Alarm → Intelligent Alert → Human Detect / Face detection → Advanced , click Set button.



The 'Advanced' window has a title bar with the same name. It contains the following elements: a 'Period' label with a 'Set' button, a 'PostRec' dropdown menu set to '10' with 'Sec.' next to it, and an 'MD Interval' dropdown menu set to '2' with 'Sec.' next to it. Below these are four checkboxes: 'Tour' (unchecked), 'Send Email' (unchecked), 'FTP upload' (unchecked), and 'Snapshot' (checked). There is also a 'Write Log' checkbox which is unchecked. At the bottom is an 'Alarm' dropdown menu set to 'Shutdown'. At the very bottom of the window are two buttons: 'OK' and 'Cancel'.

[Period] The time period of the detection.

[MD Interval] The interval between 2 human motion movements alerts.

[PostRec] To adjust the length of the video after the camera detects abnormal movements.

[Tour] Not applicable.

[Snapshot] When it is ticked on, the camera will take snapshots when it detects abnormal movements.

[Send Email] When it is ticked on, the camera will send alerts to your e-mail address when it detects abnormal movements.

[Write Log] When it is ticked on, the NVR will mark down the alarm record. You can review the records by following this path: Right click the mouse→ Main Menu → Advanced → Log .

[FTP upload] Not applicable.

[Alarm] Shutdown: It means to turn off all alarm sounds.

Voice Prompts: You can select to turn on different alarm sounds.

If you have set the function of face detection, on screen of the monitor with live video, you can view the human faces detected by the cameras. You can easily and quickly get whether the persons detected by the camera are your friends or intruders. If he is an intruder, the face detection function can help take some actions as soon as possible to protect your safety and property.




When the cameras detect human faces, the NVR will show you these faces on the right side of the screen like the image above.


2.12.3 Advanced Settings of Safe Zone & Line Cross Alarm

You can set up a safe zone for camera. The camera will only detect or make alarm sound when there are abnormal activities in the safe zone.

Right click the mouse→ Main Menu → Alarm → Intelligent Alert → Rule Set



Choose the safe zone shape which you would like to use. In this user manual, we use rectangle as example.



Click & hold the sides of the different patterns then drag the sides to change the shape and the size of the safe zone.



You can also choose other size such as circle to protect our valuable objects.



When you choose "Tripwire" in stead of "Intrusion", there will be a line on the screen and the camera will only detect or make alarm sound when people cross this line.



2.12.4 Abnormality Settings

Right click the mouse→ Main Menu → Alarm → Abnormality , in this part, you can set the alarm for other events.

Abnormality

Event Type No Storage ▼

Enable ☒

Timed Alarm ☒ 60 Sec.

Show Message ☒

Alarm Shutdown ▼

Mobile reported ☒

Send Email ☐

OK
Cancel

In the **Event Type** , there are several options:

[No Storage] The NVR can't detect HDD.

[Storage Device Error] The NVR detects that the HDD is not working correctly.

[Storage No Space] The HDD is full.

[Net Disconnection] The NVR is disconnected to the Internet.

[IP Conflict] There are other devices in the LAN using the same IP address as this NVR.

You can also choose different notification types:

[Show Message] The error message will show on the monitor screen.

[Alarm] Shutdown: It means to turn off all alarm sounds.


Voice Prompts: You can select to turn on different alarm sounds.

[Mobile reported] The NVR will send error message to the App.

[Send Email] The NVR will send error message to your e-mail address.

2.12.5 Traditional Alarm Setting

Right click the mouse→ Main Menu → Alarm → Traditional alarm , in this part, you can adjust the settings for other alarm types.



[Video Blind] The camera is covered and blinded.



[Video Loss] The camera loses connection with the NVR.

[Alarm Input] The alarm input from the cameras.

[Intelligent] Not applicable.


Add WiFi Camera

This NVR supports Onvif protocol, it means that the recorder is compatible with all the WiFi cameras which support Onvif protocol. And it supports max 5mp resolution. You can add 8 pcs WiFi camera to this NVR in total. If you want to connect more cameras to the recorder, please pair the recorder and cameras first. Right click the mouse→ Main Menu → Channel Set



Click “Search” and the cameras will be able to be chosen on the upper chart. Click “Add” then the camera will be paired with the NVR.

Quick Pair: This way only work with WiFi camera which belongs to same system. Long press reset button to reboot the camera in order to complete the operation mode.

 **Notice:** This system supports 2.4GHz only.

Remote View

Right click the mouse → Main Menu → Advanced → Version



[http://d.xmeye.net/xmeye?
ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKIsS7hEhpw4z7lcaX2207pni6l
1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKIsS7hEhpw4z7lcaX2207pni6l1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==)



Serial Number: Enter device Serial Number

Username: Default user name is armn.If you have changed user name before please enter the one you set.

Password: Enter the password you have changed on login system.

4.1 Remote View via PC

Open the Google Browser, enter website: <https://www.xmeye.net>, arrive at browsing page of remote view, choose "By Device". Then enter Serial No., User name, Password and Verify to realize remote view.



4.2 Remote View via PC Client Software

Download Center:

<https://www.securitycamera.com/Software-a640163.html>

Open VMS PC client software after installation.

VMS

UserName:

admin

Password:


●●●●●●

☒ Remember Password


SIGNIN

CANCEL

Click [Device Manager] and choose [Add devices automatically] to add the device.



Online Devices: 0					
<input type="checkbox"/>	Name	CloudID	IP/Port	Protocol	Group



4.3 Remote View Via Smart Phone

① Install the software: scan the QR code or search XMEye Pro in App store to download.

When turn on NVR for the first time → Camera Test → Time Setup Wizard → Network



[http://d.xmeye.net/xmeye?](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKlsS7hEhpw4z7lcaX2207pni6l1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==)


[ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKlsS7hEhpw4z7lcaX2207pni6l1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==](http://d.xmeye.net/xmeye?ctim=220711&firv=C6380243&sv=MTBmNzE2MTI3MTE0YTAxNL3BtCoFo9nTEKlsS7hEhpw4z7lcaX2207pni6l1C+eYlp7Q7ucgHr+K+SuJOUtWXQ==)

Serial Number: Enter device Serial Number

Username: Default user name is armn.If you have changed user name before please enter the one you set.

Password: Enter the password you have changed on login system.

②Install successfully, register user, add device and begin a remote view.



Step 1:

Tap register and input your Username, Password to create a new account.

Step 2:

Click “+” to add devices: input Serial No., username and password .



Step 3:

After device added, click it to link the sever.

Step 4:

Connect successfully and start to view video.

All rights reserved. No part of this publication may be reproduced by any means without written permission from our company. The information in this publication is believed to be accurate in all respects.


Our company will not assume responsibility for any consequences resulting from the use thereof. The information contained herein is subject to change without notice. Revisions or new editions to this publication may be issued to incorporate such changes.



RoHS CE  

V202212

Documents / Resources

	<p>Techage 202212 Xmeye WiFi Camera System [pdf] User Manual</p> <p>202212 Xmeye WiFi Camera System, 202212, Xmeye WiFi Camera System, WiFi Camera System, Camera System</p>
---	--