



TIMEGUARD IS2N-16DC DC Rotary Isolator Switch Instruction Manual

[Home](#) » [TIMEGUARD](#) » TIMEGUARD IS2N-16DC DC Rotary Isolator Switch Instruction Manual 




**Weathersafe
IP65 DC Isolator Switches
16, 25 & 32A Versions in 2 or 4 Poles**



Contents

- [1 Dimensions](#)
- [2 Installation Instructions](#)
- [3 Cleaning](#)
- [4 Specifications](#)
- [5 Documents / Resources](#)
- [5.1 References](#)

Dimensions



	H	W	D2	D1	Knockouts	A	B
152N-16DC	180	100	81	36	6x M20	84	158
152N-25DC	180	100	81	36	6x M20	84	158
IS2N-32DC	180	100	81	36	6x M20	84	158
154N-16DC	180	100	81	36	6x M20	84	158
154N-25DC	180	100	81	36	6x M20	84	158
154N-32DC	180	100	81	36	6x M20	84	158

Please note that all instructions are to be left with the customer after installation

The Weathersafe Isolator range is manufactured from tough, durable thermoplastic, and is intended for use in an outdoor environment, or one in which the protection provided by the Weathersafe Extreme range is required. The protection level is IP65.

Installation Instructions

- These products should be installed by a competent person (e.g. qualified electrician) in accordance with these instructions and in compliance with the appropriate clauses of the current edition of the IEE wiring and building regulations.
- The Weathersafe Isolator range is designed to be mounted on a vertical flat surface.
- The rear box shall be mounted on the wall using fixings and wall plugs if necessary. The fixing dimensions are marked on the back of the rear box.
- The front moulding can only be removed when the switch is in the OFF position.

- The terminals should be tightened to a torque of 1.8Nm. ☿ Acable gland of IP65 or higher should be used in order to maintain the IP rating.
- The relevant cable entry knockout should be carefully removed by scoring the groove around the required knockout with a sharp knife and then tapping it out with a small hammer onto a screwdriver in the groove.
- When re-assembling the enclosure ensure that the gasket is fully in place in order to retain the IP65 rating.
- Tighten the screws supplied to refix the front cover in place. Do not overtighten. Use of an electric screwdriver is not recommended.
- Advice should be sought before installing this product in an environment where it is likely to be subjected to chemicals, oils or solvents.

Cleaning

- Care should be taken when cleaning this product.
- Inside the lid should only be wiped with a clean dry cloth.
- The outside can be cleaned with mild detergent.
- Solvent based cleaners should not be used.

Specifications

DC-PV2 / DC-PV1/21B

IS2N-16DC			
Ue	2P/4P	4T/B/S	2H
300V	16A	16A	35A
600V	16A	16A	35A
800V	12A	16A	/
1000V	8A	16A	/

DC-PV2 / DC-PV1/21B

IS4N-16DC			
Ue	2P/4P	4T/B/S	2H
300V	16A	16A	35A
600V	16A	16A	35A
800V	12A	16A	/
1000V	8A	16A	/

DC-PV2 / DC-PV1/21B

IS2N-25DC			
Ue	4P	4T/B/S	2H
300V	25A	25A	40A
600V	25A	25A	40A
800V	15A	25A	/
1000V	9A	25A	/

DC-PV2 / DC-PV1/21B

IS4N-25DC			
Ue	4P	4T/B/S	2H
300V	25A	25A	40A
600V	25A	25A	40A
800V	15A	25A	/
1000V	9A	25A	/


DC-PV2 / DC-PV1/21B

IS2N-32DC			
Ue	2P/4P	4T/B/S	2H
300V	32A	32A	45A
600V	27A	32A	40A
800V	17A	32A	/
1000V	10A	32A	/

DC-PV2 / DC-PV1/21B

IS4N-32DC			
Ue	2P/4P	4T/B/S	2H
300V	32A	32A	45A
600V	27A	32A	40A
800V	17A	32A	/
1000V	10A	32A	/

The cable cross section areas may differ subject to the switch rating of the isolator being used and the load in the circuit.



3 Year Guarantee

In the unlikely event of this product becoming faulty due to defective material or manufacture, within 3 years of the date of purchase, please return it to your supplier in the first year with proof of purchase and it will be replaced free of charge. For years 2 to 3 or any difficulty in the first year, telephone our helpline on 020 8450 0515.

Note: a proof of purchase is required in all cases. For all eligible replacements (where agreed by Timeguard) the customer is responsible for all shipping/ postage charges outside of the UK. All shipping costs are to be paid in advance before a replacement is sent.

If you experience problems, do not immediately return the unit to the store.

Email the Timeguard Customer Helpline:

HELPLINE

helpline@timeguard.com or call the helpdesk on 020 8450 0515

Qualified Customer Support Coordinators will be online to assist in resolving your query.



Deta Electrical Co Ltd

Panattoni Park, Luton Road,
Chalton, Bedfordshire, LU4 9TT

Sales Office: 0208 452 1112

or email csc@timeguard.com

www.timeguard.com

67.058.719 (Issue 1)

Documents / Resources



[TIMEGUARD IS2N-16DC DC Rotary Isolator Switch](#) [pdf] Instruction Manual

IS2N-16DC, IS2N-25DC, IS2N-32DC, IS4N-16DC, IS4N-20DC, IS4N-25DC, IS4N-32DC, IS2N-16DC DC Rotary Isolator Switch, DC Rotary Isolator Switch, Rotary Isolator Switch, Isolator Switch, Switch

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.