



Triconex 3700 Series Analog Input Modules Instructions

[Home](#) » [Triconex](#) » Triconex 3700 Series Analog Input Modules Instructions 

Triconex 3700 Series Analog Input Modules Instructions



Contents

- [1 Ana log Input Modules](#)
- [2 Analog Input Module Specifications](#)
- [3 Documents / Resources](#)
 - [3.1 References](#)
- [4 Related Posts](#)

Ana log Input Modules

Ana log Input (AI) Modules includes three independent input channels. Each input channel receives variable voltage signals from each point, converts them to digital values, and transmits the values to the three Main Processor modules on demand. In TMR mode, one value is then selected using a mid value selection algorithm to ensure correct data for every scan.

Sensing of each input point is performed in a manner that prevents a single failure on one channel from effecting another channel. Each Ana log Input Module sustains complete, ongoing diagnostics for each channel. Failure of any diagnostic on any channel activates the Fault indicator for the module, which in turn activates the chassis alarm signal. The module's Fault indicator merely reports a channel fault, not a module failure—the module can operate properly with as many as two faulty channels.

Ana log Input Modules support hot spare capability, which allows online replacement of a faulty module.

Analog Input Modules require a separate external termination panel (ETP) with a cable interface to the Triton back plane. Each module is mechanically keyed for proper installation in a Triton chassis.

Analog Input Module Specifications

Model Number	3700/3700A	3701	3703E
Voltage	0-5V, + 6% (only 3700A)	0-10V	0-5V or 0-10V ¹ , + 6%
Type	TMR, AI	TMR, AI	TMR, AI
No. of Input Points	32, diff, DC coupled	32, diff, DC coupled	16, diff, isolated
Isolated Points	No	No	Yes
Input Update Rate	55 ms	55 ms	50 ms
Resolution	12 bits	12 bits	12 bits
Accuracy	< .15% of FSR, from 0° to 60°C	< .15% of FSR, from 0° to 60°C	< .15% of FSR, from 0° to 60°C
Input Resistance (load)	30 MW (DC), min.	30 MW (DC), min.	30 MW (DC), min.
Power-Off Resistance	30 KW (DC), typical	30 KW (DC), typical	30 MW (DC), min.
Common Mode Rejection	-80 dB (DC-100Hz), typical	-80 dB (DC-100Hz), typical	-90 dB @ 60Hz, min.-100 dB @ DC, min.
Common Mode Range	-12V to +12V peak	-12V to +12V peak	±200V peak
Leg-to-Leg Isolation	200 KW, typical	200 KW, typical	20 KW, typical
Normal Mode Rejection			
@ 8Hz	-3 dB	-3 dB	-3 dB
@ 60Hz	-17 dB	-17 dB	-17 dB
@ 120Hz	-23 dB	-23 dB	-23 dB
Input Over range	150 VDC/115 VAC	150 VDC/115 VAC	150 VDC/115 VAC
Protection	continuous	continuous	continuous
Current Range	0-20 mA,	0-20 mA,	0-20 mA,
	250 W shunt	500 W shunt	250 W shunt for 5V 500 W shunt for 10V
Diagnostic Indicators			
Module Status	Pass, Fault, Active	Pass, Fault, Active	Pass, Fault, Active
Color Code	Yellow	Light yellow	Mustard yellow

1. The voltage is selected using TriStation 1131.

Triconex®

Documents / Resources



Triconex 3700 Series Analog Input Modules [pdf] Instructions

3700-3700A, 3701, 3703E, 3700 Series Analog Input Modules, 3700 Series, Analog Input Modules, Input Modules, Modules

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.