




## hp AF809 Auto Feed Microcut Paper Shredder User Manual

[Home](#) » [HP](#) » hp AF809 Auto Feed Microcut Paper Shredder User Manual 

hp AF809 Auto Feed Microcut Paper Shredder




**Please read this manual carefully before use.**

## Contents

- [1 overview](#)
- [2 Specifications](#)
- [3 Limited warranty](#)
- [4 Important information:](#)
- [5 Setup](#)
- [6 Operation](#)
- [7 Electronic Features](#)
- [8 Sheet capacity](#)
- [9 Paper jams in auto sheet feeding](#)
- [10 Minor paper jam in manual sheet feeding](#)
- [11 Major paper jam in manual sheet feeding](#)
- [12 Documents / Resources](#)
- [13 Related Posts](#)

## overview



1	Auto feed tray in closed position
2	Ready LED display
3	Overload LED display
4	OverheatLED display
5	Bin full LED display
6	Power slide switch, Reverse po sition
7	Power slide switch, power Off position
8	Power slide switch, power On position
9	Manual paper feedentry slot for up to 9 sheets
10	Credit card entry
11	Auto feed tray open to accept up to 80 sheets of paper
12	Locking pins for upper iam access panel
13	Locking pins for lower jam access panel
14	Power cord locatedin back
15	Pull-out 3.8 gal waste bin
16	Clear window for shred inspection

#### **Limitations/Local laws**

EXCEPT AS EXPRESSLY SET FORTH IN THIS LIMITED WARRANTY, THERE ARE NO OTHER WARRANTIES, EXPRESS OR IMPLIED, FOR YOUR HP PRODUCT. ALL OTHER WARRANTIES, INCLUDING ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, ARE EXPRESSLY DISCLAIMED. ANY IMPLIED WARRANTIES IMPOSED BY LAW ARE LIMITED IN DURATION TO THE APPLICABLE WARRANTY PERIOD.

This Limited Warranty gives you specific legal rights, and it is governed by the laws of the state and country in which your HP Product was purchased. You may also have other rights that vary from state to state and country to country. You are advised to consult applicable state and country laws to determine your rights. Some states and countries do not allow any limitation on how long a limited warranty will last, or any exclusion or limitation of incidental or consequential damages. In such states and countries, some of the exclusions or limitations stated in this Limited Warranty may not apply to you.

#### **Sole remedies/No incidental or consequential damages**

To the extent allowed by local law, the remedies provided in this Limited Warranty are your sole and exclusive remedies. These terms and conditions supersede any prior agreements or representations, including statements made in sales literature or advice given in connection with your purchase.

TO THE EXTENT ALLOWED BY LOCAL LAW, AND EXCEPT AS SPECIFICALLY SET FORTH IN THIS LIMITED WARRANTY, IN NO EVENT SHALL HP, ANY HP SERVICE CENTER OR ANY HP-AUTHORIZED SERVICE PROVIDER BE LIABLE FOR ANY DAMAGES CAUSED BY THE PRODUCTOR THE FAILURE OF THE PRODUCT TO PERFORM, INCLUDING ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES, WHETHER BASED ON CONTRACT, TORT, OR ANY OTHER LEGAL THEORY, AND WHETHER OR NOT ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

#### **Locate your authorized service center**

If you need support during the warranty period, locate the Authorized Service Center for this product at:

[www.hp.com/officerequipment](http://www.hp.com/officerequipment) Or use the following contact information: USA: 833-523-0800

## Specifications

Shred type:	Microcut
Shred width:	4.3mm x 12mm
Shredding capacity:	9 Sheets (20 lb. bond paper) or 1 credit card
Paper tray capacity:	80 Sheets (20 lb. bond paper)
Duty cycle (auto feed)	10 min on/ 40 min off
Feed opening:	8 3/4 inches
Dimensions ( w x D x H ):	<b>12.99" x 8.62" x 16.73"</b>
Weight:	16.97 lbs.(7.7 Kg)
Input:	115 volt AC, 4.7 Amp, 60Hz

## Limited warranty

Your HP Product is warranted to be free from defects in materials or workmanship under normal use for one year, with an additional 2 years on the cutting blades starting on your date of purchase. Your dated sales or delivery receipt is your proof of purchase. You may be required to provide proof of purchase as a condition of receiving warranty service. During the warranty period, if a defective HP Product covered by this Limited Warranty is returned to the designated Service Center, it will be repaired or replaced or, at the option of the Service Center, its purchase price will be refunded. No repair, replacement or refund will be provided unless the defective HP Product is returned to the Service Center at your expense; for some HP Products, no return will be accepted unless the Service Center first provides you with a Return Material Authorization (RMA). If your HP Product has recurring failures, at the option of the Service Center, either you will be furnished with a different product that is equivalent in performance or you will receive a refund of your purchase price. Service Center support may be provided by an HP subcontractor or other third parties. Please see the Service Center information provided.

Where permitted by local law, HP Products and any replacement products or parts may contain new materials or used materials equivalent to new in performance and reliability. Replacement products or parts will have functionality at least equal to that of the product or part being replaced. Replacement products and parts are warranted to be free from defects in materials or workmanship for 90 days, or for the remainder of the warranty period for the HP Product which they are replacing or in which they are installed, whichever is longer.

This Limited Warranty does not include technical assistance. This Limited Warranty does not cover cosmetic damage, loss or damage in transit, or damage resulting from (a) accident, misuse, abuse or other external causes; (b) product elements not supplied by HP; (c) improper site preparation or maintenance; or (d) modification or service by anyone other than HP. an HP Service Center or another HP-authorized service provider.



### Warning

- **ALWAYS** keep out of the reach of children as serious injury could occur.
- **DO NOT** place fingers too close to feed slot as serious injury could occur.
- **AVOID** getting jewelry, hair or loose clothing too close to feed slot as serious injury could occur.
- **ALWAYS** keep shredder off and unplugged when not in use.
- **ALWAYS** unplug shredder when moving, cleaning or emptying the waste receptacle.
- **DO NOT** attempt to feed more sheets of paper than specified on the feeder.
- **DO NOT** attempt to shred materials other than paper, credit cards.
- **ALWAYS** use a power outlet or socket near the shredder so it is easily accessible.








- **ALWAYS** limit continuous shredding to the specified time as suggested in the instruction manual.
- **ALWAYS** empty the waste receptacle prior to the receptacle becoming full.
- **DO NOT** attempt to operate the shredder if it is experiencing any kind of problem.
- **DO NOT** use flammable synthetic oil, petroleum-based or aerosol products of any kind on shredder.
- **DO NOT** touch exposed cutting blades under the shredder head.
- **DO NOT** attempt to repair shredder yourself.



**Warning icons:**

The Icons, on top of the shredder, warn the user of the potential dangers if the shredder is used improperly.



	<b>Warning:</b> Certain actions may cause harmful outcomes		Read user manual completely prior to using shredder		Keep children and pets away from shredder
	Keep fingers and hands away from paper shredding opening		Keep loose clothing and dangling items away from paper shredding opening		
	Keep long hair or accessories away from paper shredding opening		Do not spray aerosol, lubricants or any other accelerant products into this unit		



### Important information:

A few pieces of shredded paper may be found inside the shredder and the wastebasket. This is normal. All HP shredders are tested at the factory to ensure quality.

### Setup

1. The AF809 shredder should be placed on a flat level surface.
2. Make sure that the wastebasket is completely inserted into the shredder cabinet and that it fits flush with the shredder cabinet.
3. Plug the power cord in to any standard 115-volt AC outlet. We recommend that you do not plug your shredder

into the same outlet as other electronic devices.

4. Move the Power slide switch into the On position ③ the Ready LED ② should light up. You are now ready to start shredding.

## Operation



With the electrical cord plugged in, the Power slide switch placed into the On position ③, the shredder wastebasket properly in place, the Ready LED ② will light up. This means that the shredder is now ready for operation. It is recommended that when the auto sheet feed is not in use, the Auto feed tray should remain in the closed position.

### Manual feed shredding:

A maximum of 9 sheets at one pass or a single credit card is recommended. Exceeding the maximum 9 sheet or multiple credit card insertions could result in unnecessary paper jams. When the paper is inserted into the feed opening, the shredding process will start automatically and stop when the paper has completed its travel through the feed opening.

### Auto sheet feed shredding:

Grasp the front edge of the Auto feed tray and open fully as in Diagram ①. Staples and paper clips should be removed prior to insertion. Place up to 80 sheets of neatly stacked paper into the paper tray as in Diagram ②. The feeding of the paper should begin immediately. The duty cycle for auto feed is 10 min on/ 40 min off.



## Electronic Features

- The Ready LED ② lets you know the shredder is working and ready to shred.
- The Overload LED ③ will light up when the shredder has exceeded the maximum sheet capacity which is 8 sheets.
- The Overheat LED ④ will light up when the motor temperature has reached its maximum allowed temperature and will shut off the power to the motor. When the motor cools down, the shredder will be ready to resume shredding.
- The Bin full LED ⑤, will light up when the waste bin is full and should be emptied.

## Sheet capacity

On manual feed, the AF809 will shred up to nine (9) sheets and will accept paper widths up to 8 3/4 inches. When shredding small material like credit cards, envelopes, or receipts, insert them through the middle of the feed opening. On auto sheet feeding, the AF809 will shred up to eighty (80) sheets of paper neatly stacked into the Auto feed tray.

## Paper jams in auto sheet feeding

If during the auto feed function you receive a paper jam, place the Power slide switch into the Reverse position ⑥ and remove the jam. If the papers have traveled further into the feed rollers and cutters, open Panel 1 by moving



both access levers inward and lifting the Panel 1.

Open as shown in Diagram ③.

If further access is required to remove the jam, open Panel 2 as shown in Diagram ④ allowing access to the cutter assembly.

Always be very careful when approaching the cutter blades. They are very sharp and could harm you if mishandled. After the jam has been removed be sure Panel 1 and 2 are back in their original secured position.




Diagram ③  
Open Panel 1.






Diagram ④  
Open Panel 2.



### Minor paper jam in manual sheet feeding

Place the Power slide switch into the Reverse position ⑥ and pull the remaining sheets of paper out of the feed opening. Remove the unshredded papers from the top and clear any excess paper shreds from the feed opening. Be careful not to place your fingers near the feed opening or serious harm could result.

### Major paper jam in manual sheet feeding

- Turn off or unplug the power cord from the AC outlet and wait at least 40 minutes for the thermal overload protection to reset.
- Plug in the AC power cord and place the Power slide switch into the Reverse position ⑥ and grasp the excess paper from the top and pull it out. Be careful not to place your fingers near the feed opening or serious harm could result.


Consumer Information Products, Inc.  
HP Warranty Processing  
50 Hilton Street  
Easton, PA 18042

[www.hp.com/officeequipment](http://www.hp.com/officeequipment)

HP is a trademark of HP Inc. or its affiliates, used by Royal  
Consumer Information Products under license from HP Inc.  
© Copyright, Royal Consumer Information Products, Inc. 2021,  
All Rights Reserved.  
HP-AF809IM0421



## Documents / Resources

 <p>HP AF809 Auto Feed Microcut Paper Shredder</p>	<p><a href="#">hp AF809 Auto Feed Microcut Paper Shredder</a> [pdf] User Manual</p> <p>AF809, Auto Feed Microcut Paper Shredder, AF809 Auto Feed Microcut Paper Shredder, Feed Microcut Paper Shredder, Microcut Paper Shredder, Paper Shredder, Shredder</p>
---	---

Manuals+.