

A4TECH^{EST. 1987®}
**FS300 Hot
Swappable
Mechanical
Keyboard**



A4TECH FS300 Hot Swappable Mechanical Keyboard User Guide

[Home](#) » [A4TECH](#) » A4TECH FS300 Hot Swappable Mechanical Keyboard User Guide 

Contents

- [1 A4TECH FS300 Hot Swappable Mechanical Keyboard](#)
- [2 Product Usage Instructions](#)
- [3 WHAT'S IN THE BOX](#)
- [4 THE FRONT](#)
- [5 OPERATING SYSTEM SWAP](#)
- [6 COMBINATION FN KEYS](#)
- [7 INSTALLATION](#)
 - [7.1 SWAPPABLE SWITCH](#)
- [8 FAQ](#)
- [9 SPECIFICATIONS](#)
- [10 More Information](#)
- [11 Documents / Resources](#)
 - [11.1 References](#)

A4TECH^{EST. 1987®}

A4TECH FS300 Hot Swappable Mechanical Keyboard



Specifications

- Switch Type: Hot-Swappable
- Actuation Point: Special tuned

Product Usage Instructions

Operating System Swap

To swap between Windows and Mac OS layouts:

- Press **Fn + Windows key** for Windows layout.
- Press **Fn + Mac key** for Mac OS layout.
- The Caps Lock indicator light will show the current layout.

Combination FN Keys

- Use the FN key in combination with other keys for various functions like multimedia controls, lighting effects, and volume adjustments.

Installation

- **Connection:** Connect the Type-C cable to the keyboard and USB plug to the computer directly. Avoid using hubs or extension cables.
- **Software Download:** Download and install the Keyboard Master Editing Software for optimal performance from the provided link. Note that the software is not compatible with Mac systems.


Hot-Swappable Switch

To swap switches:


1. Remove keycaps with the keycap puller.
2. Use the switch puller to remove switches.

3. Align switch pins with the PCB socket and place the switch securely.
4. Gently press the switch into place and test it by placing back the keycaps.

WHAT'S IN THE BOX







THE FRONT



1. FN Multimedia Hotkeys
2. Lighting Effects Switching
3. Operating System Swap
4. Windows / Mac Dual-Function Keys
5. Backlit Brightness Adjustable

OPERATING SYSTEM SWAP

| System | Shortcut | Indicator Light |
|---------|---|------------------------------|
| Windows |  +  | Caps Lock Flashing 3S Off |
| Mac OS |  +  | |

Note: Windows is default system layout.


The device will remember the last keyboard layout, please switch as needed.

COMBINATION FN KEYS

Multimedia Hotkeys



Default 10 Preset Lighting Effects



Disable “Windows” Key




- The G LED Lights Up in Solid Red

Lighting Brightness +/-



INSTALLATION


CONNECTION



- Connect the cable Type-C plug to the keyboard and the USB plug to the computer.

(**Note:** Using a USB hub or extension cable to connect is not recommended)

SOFTWARE DOWNLOAD




- For the best product performance, please download and install the Software from www.a4tech.com/download.aspx

Note: The software does not support Mac systems.

SWAPPABLE SWITCH

HOT-SWAPPABLE SWITCH

Special tuned the actuation point and actuation force to bring users an unusual typing experience!






- 1. Total Travel Distance 4mm
- 2. Double Gold Cross Contacts
- 3. High Return Torsion Spring
- 4. Hot-Swappable




| Actuation Point | Tactile Point | Initial Force | Actuation Force | Tactile Force | Bottom Out Force |
|-----------------|---------------|---------------|-----------------|---------------|------------------|
| 2.0±0.6 mm | N / A | 35 cN Min | 45±10 cN | N / A | 50 cN Max |

SWAP SWITCH STEP

Compatible with 3-Pin & 5-Pin Style Mechanical Switches.



1. Remove the keycaps with the keycap puller.
2. Remove the Switches with the switch puller.
3. Line up the switch pins with the PCB socket.



4. Place the switch on the PCB and integrate it closely.
5. Gently press the switch into place.
6. Put the keycaps back on to the keyboard and test it.

The switches, keycap & switch puller pictures are for reference only, and not included in the package.

FAQ

Q & A

Can the keyboard support Mac platforms?

Support. Windows.. Mac keyboard layout switching.

Does the layout can be remembered?

The layout you used last time will be remembered.

Why does the function light not indicate in Mac OS System?

Because the Mac OS system does not have this function.

How to use Keyboard Master Editing Software functions on a Mac system?

The keyboard has built-in memory and can be used on Mac systems after editing on the Windows platform.

SPECIFICATIONS

- **Switch Type:** Hot-Swappable, Linear & Light
- **Actuation Point:** 2.0 ± 0.6 mm
- **Switch Lifetime:** 50 Million Keystrokes
- **Report Rate:** 1000Hz
- **Onboard Memory:** 4 MB
- **Keycaps:** OMA Profile
- **Keyboard Layout:** Windows / Mac
- **Backlit Color:** White
- **Cable Length:** 180 cm
- **System Platform:** Windows / Mac

More Information

Scan




- www.a4tech.com

Scan for E-Manual



Documents / Resources



[A4TECH FS300 Hot Swappable Mechanical Keyboard](#) [pdf] User Guide
FS300-GD-EN-20240430-L, 705010-8189R, FS300 Hot Swappable Mechanical Keyboard, FS300, Hot Swappable Mechanical Keyboard, Mechanical Keyboard, Keyboard

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.