

algodue ELETTRONICA MFC150-UI Rogowski Coil Current Sensor User Manual

[Home](#) » [algodue ELETTRONICA](#) » algodue ELETTRONICA MFC150-UI Rogowski Coil Current Sensor User Manual 

*algodue ELETTRONICA MFC150-UI Rogowski Coil Current Sensor
User Manual*

MFC150-UI

- EN** - USER MANUAL
- DE** - BEDIENUNGSANLEITUNG
- IT** - MANUALE D'USO
- FR** - NOTICE D'EMPLOI
- ES** - MANUAL DEL USUARIO


Subject to change without prior notice

Contents


- 1 PICTURE
- 2 INTRODUCTION
- 3 AVAILABLE MODELS
- 4 SAFETY
- INSTRUCTIONS
- 5 MOUNTING
- 6 CONNECTIONS
- 7 MAINTENANCE
- 8 TECHNICAL FEATURES
- 9 Documents / Resources
 - 9.1 References

PICTURE


A



B



C



INTRODUCTION

The manual is intended only for qualified, professional and skilled technicians, authorised to act in accordance with the safety standards provided for the electrical installations. This person must have appropriate training and wear suitable Personal Protective Equipment.

⚠ WARNING! It is strictly forbidden for anyone who does not have the above-mentioned requires to install or use the coil.

It is forbidden to use the coil for purposes other than intended ones, specified in this manual. The symbols on the product are following described:



Attention! Refer to the user manual.



Protected throughout by DOUBLE INSULATION or REINFORCED INSULATION.



Do not apply around or remove from HAZARDOUS LIVE conductors without additional protective means.



Complies with the relevant European standards.



Underwriters' Laboratory Listed product.

AVAILABLE MODELS

MODEL	Built-in INTEGRATOR	INDOOR use	OUTDOOR use
MFC150-UI		●	
MFC150-UI/O			●
MFC150-UI/F	●	●	
MFC150-UI/OF	●		●

SAFETY INSTRUCTIONS

The Rogowski coil must be installed in an environment which are according to the max operation conditions of the coil itself.

⚠ WARNING! The connection and installation of the Rogowski coil must be carried out only by qualified technicians aware of the risks involved to the presence of voltage and current. Before carrying out an operation, check if:

1. bare conductor wires are not powered,
2. there are no neighbour bare powered conductors

NOTE: The Rogowski coil complies with IEC 61010-1 and IEC 61010-2-032, UL 2808 standards and following amendments. The installation must be carried out in accordance with the standards in force, the instructions of this user manual and the coil insulation value in order to avoid any danger for people.

The Rogowski coil is a sensor for accurate measurement so it must be handled with care. Before use, read the following instructions carefully.

- Do not use the product if damaged.
- Always wear protective clothing and gloves when required.
- Avoid to strongly twist, blow and to perform pulling load on the product, the measurement accuracy may be impaired.
- Do not paint the product.
- Do not put metallic labels or other objects on the product: the insulation may be impaired.
- It is forbidden any use of the product different from the manufacturer specifications.

MOUNTING

⚠ WARNING! Before installing the coil, make sure to comply with the following statements:

- Always open or disconnect circuit from power-distribution system (or service) of building before installing of servicing coils.
- The coils may not be installed in equipment where they exceed 75 percent of the wiring space of any cross-sectional area within the equipment.
- Restrict installation of coil in an area where it would block ventilation openings.
- Restrict installation of coil in area of breaker arc venting.
- “Not suitable for Class 2 wiring methods” and “Not intended for connection to Class 2 equipment”.

⚠ **WARNING!** Check if the coil is properly installed: a bad locking can affect measurement accuracy and the coil will become sensitive to adjacent conductors or other sources of electromagnetic fields.

NOTE: Coil must not fit tightly round the conductor, therefore its internal diameter must exceed that of the conductor.

To carry out the installation, proceed as follow:

1. Fit the coil round the conductor, bringing the coil ends together.
2. Lock the coil by turning the ring as indicated in picture A.

CONNECTIONS

The coil has an arrow indicating the load side.

In case of model WITHOUT integrator refer to picture B:

A = SOURCE

B = LOAD

1. WHITE wire, OUT+
2. BLACK wire, OUT-
3. SHIELD, connect to GND or OUT-

If the cable is provided with crimp pins:

- YELLOW crimp pin, OUT+
- WHITE crimp pin, OUT-

In case of model WITH integrator refer to picture C:

A = SOURCE

B = LOAD

1. WHITE wire, OUT+
2. BLACK wire, OUT-
3. RED wire, positive power, 4...26 VDC
4. BLUE wire, negative power, GND
5. SHIELD, connect to GND

The coil is protected against reverse polarity of the power supply.

MAINTENANCE

Refer to the following instructions carefully for the product maintenance.

- Keep the product clean and free of surface contamination.
- Clean the product with a soft cloth damp with a water and neutral soap. Avoid to use corrosive chemical products, solvents or aggressive detergents.
- Make sure the product is dry before further use.

- Do not use or leave the product in particularly dirty or dusty environments.

TECHNICAL FEATURES

NOTE: For any doubt on the installation procedure or on product application, please contact our technical services or our local distributor.

COIL	
Coil length	300 ... 3000 mm (11.8 ... 118.1 in)
Sensor internal diameter	70 ... 940 mm (2.7 ... 37 in)
Coil diameter	8.3 ±0.2 mm (0.33 ±0.007 in)
Jacket material	Polyphenylene and thermoplastic elastomer
Fastening	Bayonet holder
Weight	150 ... 500 g (5.3 ... 17.6 oz)

ELECTRICAL CHARACTERISTICS FOR MODEL WITHOUT INTEGRATOR

Nominal output rate	120 mV / kA @ 60 Hz (RMS values) 100 mV / kA @ 50 Hz (RMS values) Refer to the value indicated on the product label
Max measurable current	2 kA with 300 ... 420 mm (11.8 ... 16.5 in) coil length 5 kA with 430 ... 3000 mm (16.9 ... 118.1 in) coil length
Coil resistance	70 ... 900 Ω
Positioning error	Better than ±1% of reading
Frequency	50/60 Hz
Maximum primary voltage	600 V CAT IV, Service Entrance
Pollution degree	2, Controlled Environment for indoor use model 3, Uncontrolled Environment for outdoor use model
Insulation test voltage	7400 VRMS / 5 s

ELECTRICAL CHARACTERISTICS FOR MODEL WITH INTEGRATOR

Power voltage	4 ... 26 VDC
Max consumption	5 mADC
Nominal output rate	333 mV / FS (RMS values) FS changes according to the model: 1, 2, 5 kA Refer to the value indicated on the product label
Positioning error	Better than ±1% of reading
Frequency	50/60 Hz
Maximum primary voltage	600 V CAT IV, Service Entrance
Pollution degree	2, Controlled Environment for indoor use model 3, Uncontrolled Environment for outdoor use model
Insulation test voltage	7400 VRMS / 5 s

CONNECTION CABLE FOR MODEL WITHOUT INTEGRATOR

Type	3 x 24 AWG shielded
Length	3 m (9.8 ft). Other lengths on request: 5, 7, 10, 15 m (16.4, 23.0, 32.8, 49.2 ft)

CONNECTION CABLE FOR MODEL WITH INTEGRATOR

Type	5 x 24 AWG shielded
Length	3 m (9.8 ft). Other lengths on request: 5, 7, 10, 15 m (16.4, 23.0, 32.8, 49.2 ft)


ENVIRONMENTAL CONDITIONS

Protection degree	IP65 for indoor use model IP68 for outdoor use model
Altitude	Up to 2000 m over sea-level
Operating temperature	-35 ... +75°C (-31 ... +167°F) up to 2 kA -35 ... +60°C (-31 ... +140°F) from 2 to 5 kA
Storage temperature	-40 ... +90°C (-40 ... +194°F)
Relative humidity	0 ... 95%
Installation and use	Controlled Environment for indoor use model Uncontrolled Environment for outdoor use model

STANDARD COMPLIANCE

IEC, UL standards	ANSI/CAN/UL 2808, CSA C22.2 NO. 61010-1-12, IEC 61010-2-032, IEC 61010-1 Ed3, IEC 60529
-------------------	--

Documents / Resources



[algodue ELETTRONICA MFC150-UI Rogowski Coil Current Sensor](#) [pdf] User Manual MFC150-UI, MFC150-UI-O, MFC150-UI-F, MFC150-UI-OF, MFC150-UI Rogowski Coil Current Sensor, Rogowski Coil Current Sensor, Coil Current Sensor, Current Sensor, Sensor

References

- [Algodue Elettronica: sistemi di monitoraggio energia](#)