



ALTO MK2 Bluetooth Total Battery Powered Bluetooth Receiver User Guide

[Home](#) » [ALTO](#) » ALTO MK2 Bluetooth Total Battery Powered Bluetooth Receiver User Guide 

Contents

- [1 ALTO MK2 Bluetooth Total Battery Powered Bluetooth Receiver](#)
- [2 Box Contents](#)
- [3 Controls](#)
- [4 LED Activity](#)
- [5 Documents / Resources](#)
 - [5.1 References](#)
- [6 Related Posts](#)

ALTO

ALTO MK2 Bluetooth Total Battery Powered Bluetooth Receiver



Box Contents

Bluetooth® Total, Micro-USB Charging Cable, User Guide.

Charging Bluetooth Total: Use the included micro-USB cable to connect Bluetooth Total to a USB power adapter (sold separately) connected to a power outlet or your computer (powered on).

Note: Bluetooth Total may not be fully charged upon purchase. While it is safe to use it right away, charging for 3-4 hours before initial use will ensure a full charge and the best performance.

Controls

1. XLR Output
2. Stereo-Link
3. Stereo-Link LED
4. Pair
5. Pair LED
6. Power On/Off
7. Power and Battery Status LEDs
8. Micro-USB Charging Port

LED Activity

- **When ON and battery is not charging:**

- 20–100% = Green LED lit solid.
- 10–20% = Green and Amber LEDs are lit solid.
- 0–10% = Green and Red LEDs are lit solid.

Power Standby Mode = Green LED off. Red LED flashes once every 10 seconds.

- **When ON and battery is charging:**

- Power Standby Mode = Green LED off. Red LED flashes once every 10 seconds.
- 5–80% Charged = Green LED is off. Amber LED flashes slowly.
- 80–99% Charged = Green LED flashes slowly. Amber LED is off.

- 100% Charged = Green LED is lit solid. Amber LED is off.

- **When OFF and charging:**

- 5%–80% Charged = Green LED is off. Amber LED flashes slowly.
- 80%–99% Charged = Green LED flashes slowly. Amber LED is off.
- 100% Charged = Green LED lit solid. Amber LED is off.

Bluetooth Pairing a Single Bluetooth Total

1. Power on your Bluetooth device.
2. Power on Bluetooth Total.
3. Press and hold the Pair button for 3 seconds on Bluetooth Total. A pairing tone will sound when Bluetooth Total is in pairing mode. Note: Press Pair again before your device is paired, to cancel the pairing process.


Note: Before pairing, turn off Wi-Fi on your device and stop any audio playback.

4. Navigate to your Bluetooth device's setup screen, find "ALTO BT2" and connect.
5. When paired successfully, a confirmation tone will sound and the blue Pair LED will illuminate solid.
- Note:** If your Bluetooth device prompts for a pairing code, enter "0000".
6. Adjust the volume on your Bluetooth device. To erase previous pairing settings, press and hold the Pair button for 10 seconds. A confirmation tone will sound, indicating that pairing settings have been erased. You can now pair to a new device. **Note:** When wirelessly connected to a single loudspeaker, the Left/Right audio signal will be summed to mono.

Stereo-Linking 2 Bluetooth Total Units

1. Follow steps 1-6 in the Bluetooth Pairing a Single Bluetooth Total section.
2. Press and hold the Stereo-Link button for 3 seconds on the primary (left) Bluetooth Total. Press and hold the Stereo-Link button for 3 seconds on the secondary (right) Bluetooth Total.
3. Both Stereo-Link LEDs will blink and a linking tone will sound while each Bluetooth Total "searches" for the other.
4. When they are successfully linked, each Bluetooth Total will produce a confirmation tone and the Stereo-Link LEDs on both units will be lit solid. To erase linking settings on the linked unit, press and hold the Stereo-Link button for 10 seconds. A confirmation tone will sound, indicating that linking settings have been erased. To erase linking settings on both units, press and hold the Stereo-Link button on the master unit for 10 seconds. A confirmation tone will sound, indicating that linking settings have been erased.

Documents / Resources



[ALTO MK2 Bluetooth Total Battery Powered Bluetooth Receiver](#) [pdf] User Guide
TBT2, Y4O-TBT2, Y4OTBT2, MK2, Bluetooth Total Battery Powered Bluetooth Receiver, MK2
Bluetooth Total Battery Powered Bluetooth Receiver, Bluetooth Receiver

References

- [!\[\]\(effbd7993c63c039a58fd3395789cf3f_img.jpg\) **Alto Professional**](#)
- [!\[\]\(144980d038f2541d7b588a8a9132bd70_img.jpg\) **Support : Alto Professional**](#)
- [!\[\]\(c4ce2d477989700c971cf3d240ad9283_img.jpg\) **altoprofessional.com/warranty**](#)

Manuals+.