

AMD
L9 2K plus 6
Detective
QR Code
Body
Camera



AMD L9 2K plus 6 Detective QR Code Body Camera Instruction Manual

[Home](#) » [AMD](#) » AMD L9 2K plus 6 Detective QR Code Body Camera Instruction Manual 

Contents

- [1 AMD L9 2K plus 6 Detective QR Code Body Camera](#)
- [2 Product structure](#)
- [3 Button and interface function introduction](#)
- [4 Basic operating instructions](#)
- [5 Product parameters and specifications](#)
- [6 Documents / Resources](#)
 - [6.1 References](#)



AMD L9 2K plus 6 Detective QR Code Body Camera



Instruction manual

Please read the instructions carefully before using this product

The instruction manual is for reference only, the specific operation is subject to the actual

Product structure

Product description



1. Explosive flashing light

2. Camera
3. Red lights
4. Horn
5. Shoulder clip buckle
6. Display screen
7. Up/Long press to turn on or off night vision
8. Menu key
9. Press and hold down to turn on or off WIFI
10. Video mode key
11. Photo mode key
12. Recording on key
13. OK confirmation key
14. Return key/playback mode key
15. Power button
16. USB data interface
17. Reset hole
18. TF card slot

Button and interface function introduction

Press the upper key

Up selection key: Long press to turn on night vision, and long press again to exit night vision.

Menu key

Tap to enter the Settings menu and tap again to exit the menu.

Press the down button

Downward selection key: Long press to open WIFI, short press to return, after 3 seconds, the background will all return

Video Mode key

Press to enter the recording mode, and press again to record.

Photo Mode button

Press to enter the photo mode, and press again to take a picture.

Recording on/off key

Short press to open recording, long press to exit recording

In the menu state, press the "OK key";

Return key/playback mode key

Power button

1. Short press to extinguish the screen, and short press again to light up;
2. Long press to turn on/off.

Operation method of flashing light

Press and hold the photo mode button for the first time to turn on the flashing light and sound. Press and hold the photo mode for the second time, Jian, only turn on the flashing light without any sound Third long press to close

USB data port

1. Interface Type: type-c
2. It is used to connect the external power supply to charge the battery or provide the working power supply.
3. It is used to connect the PC terminal for real-time screen;
4. You can view album files in the U disk mode;

Reset the hole

When the machine appears flower screen, abnormal crash, etc., with a pinhole-like thing short poke can restart.

TF card slot

Memory card slot

Basic operating instructions

USB mode

The device uses USB data to connect to the computer. After the device starts up automatically, the screen displays three options of “memory /PC camera/video mode” :

- **Memory:** In this mode, video files or photos can be accessed and viewed;
- **PC camera:** In this mode can be used for computer camera;
- **Video mode:** Used only by the computer to power the device.

Product parameters and specifications


lens	Fixed lens, 130 degree Angle
TH disp lay	2.0 “color display (320*240)
Video resolution	3840x2160P, 2560x1440 P, 1920x1080P
Video file format	AVI
Photo and video quality	VGA-40M
Motion detection	Close and open
Picture Settings	Close and open
Photo format	J PG
Loop video	10 minutes
Exposure compensation	- 2.0 — +2.0
Recording file format	WAV
Time mark	Close and open

App download and installation:

Scan the QR code below to download and install the APP



(WIFI optional)

Long press the Right key of the product . It will open wifi interface. Then Press again to turn off WiFi


SSID: L9-Z1 switch

password: 12345678

Automatic shutdown	Off, 1 minute, 3 minutes, 5 minutes, 10 minutes
Ac frequency	50Hz, 60Hz
screen saver	Close and open
language	English, Simplified Chinese, Traditional Chinese, Japanese, Korean, Russian, French, German, Czech, Portuguese, Polish, Dutch, Turkish, Thai
Working humidity	20 °C
Operating temperature	65 °C
Power supply	USB:5V Battery :3.6V
standby	43.6 uA
Standby current	3.7 V
low current warning	3.49 V
Power consumption	USBSV: 400mA Battery 3.7V:5.2.0W
Memory card	TF card, maximum support 128G

Note: Design and specifications are subject to change without prior notice.

Documents / Resources

	AMD L9 2K plus 6 Detective QR Code Body Camera [pdf] Instruction Manual L9 2K plus 6 Detective QR Code Body Camera, L9, 2K plus 6 Detective QR Code Body Camera, 6 Detective QR Code Body Camera, QR Code Body Camera, Body Camera, Camera
---	---

References

- [User Manual](#)

Manuals+. Privacy Policy

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.