



anslut 006866 Wall Socket Instruction Manual

[Home](#) » [anslut](#) » anslut 006866 Wall Socket Instruction Manual 

•



Contents

- 1 anslut 006866 Wall Socket
- 2 SAFETY INSTRUCTIONS
- 3 ELECTRICAL SAFETY
- 4 SYMBOLS
- 5 TECHNICAL DATA
- 6 use CHARGER
- 7 ASSEMBLY
- 8 Documents / Resources
- 9 Related Posts




SAFETY INSTRUCTIONS

- Do not connect power strips to each other.
- Do not cover the power strip.

ELECTRICAL SAFETY

New installations and extensions to existing systems should always be carried out by an authorized electrician. If you have the necessary experience and knowledge (otherwise contact an electrician), you can replace power switches and wall sockets, fit plugs, extension cords and light sockets. Incorrect installation can result in fatal injury and the risk of fire.

SYMBOLS

	Read the instructions.
	Approved in accordance with the relevant directives.
	Recycle discarded product as electrical waste.

TECHNICAL DATA

- Rated voltage 230 V ~ 50 Hz
- Size 169 x 53 x 81 mm
- Protection rating IP21
- Current 16 A

use CHARGER

- Electrical input data 230 V ~ 50 Hz, 200 mA
- Electrical output data (total) 5 v, 4.8 A
- USB port USB type A

NOTE:

The USB charger connection's total output current is 4.8 A. The current is disconnected automatically if the charging current exceeds this value to protect the connected devices.


ASSEMBLY

INSTALLATION

1. Disconnect the power supply by taking out the fuse and checking that the wires are without voltage.
2. Strip about 11 mm off the ends of the wires.
3. Dismantle the product into three parts as shown in figure 1. Do not remove the screw in the middle during the installation.
4. Open the grommets and push the cable into the box.

5. Press the box into the corner so that the sides rest against the walls and screw on with screws in the four screw holes (A).
6. Connect the wires to the PowerPoint and USB connection according to color and the markings N and L ®. The crosssectional area of the wires is 2.5 mm² •
 - L, brown (live)
 - ®, green and yellow (earth)
 - N, blue (neutral)
7. Check that all the connections are correct.
8. Screw the front onto the box. Make sure not to pinch the wires. Press the frame in place.

Documents / Resources

 <p>anslut 006866</p> <p>1. Montage Screw the box into the wall at the four screw holes (A). The box must be mounted in a dry, protected location.</p> <p>2. Wire connection Strip the insulation from the wires. Connect the wires to the terminals according to the color code and the markings N and L ®. The cross-sectional area of the wires must be 2.5 mm².</p> <p>3. Safety Do not touch the wires or the terminals when the device is plugged in. The device must be unplugged before the front cover is removed.</p> <p>4. Maintenance Clean the device with a dry cloth. Do not use liquid cleaners.</p> <p>5. Disposal The device must be disposed of in accordance with the local regulations for electrical waste.</p> <p>6. Technical data Rated voltage: 230 V AC Rated current: 16 A Rated power: 3680 W Rated frequency: 50/60 Hz Rated temperature: 0 °C to 40 °C Rated humidity: 5% to 95% Rated altitude: 0 to 2000 m Rated weight: 0.1 kg</p>	<p>anslut 006866 Wall Socket [pdf] Instruction Manual 006866, Wall Socket, 006866 Wall Socket</p>
---	---