

[Manuals.plus](#) /

› [Leviton](#) /

› Leviton 20 Amp, 125/250 Volt, Narrow Body Single Receptacle, 5032-I, Ivory User Manual

Leviton 5032-I

Leviton 20 Amp, 125/250 Volt, Narrow Body Single Receptacle User Manual

Model: 5032-I | Ivory

PRODUCT OVERVIEW

The Leviton 5032-I is a heavy-duty specification grade single receptacle designed for demanding environments. This 20 Amp, 125/250 Volt device features a narrow body and is suitable for commercial applications such as hotels, schools, hospitals, and office buildings. Its robust construction ensures reliability and durability.





Image: Front view of the Leviton 5032-I single receptacle, showing the ivory color and the 20A 125/250V rating.

SAFETY INFORMATION

WARNING: To avoid fire, shock, or death; turn off power at circuit breaker or fuse box and test that power is off before wiring! This device must be installed in accordance with all national and local electrical codes.

- Always disconnect power before installation or servicing.
- Use appropriate personal protective equipment (PPE).
- Consult a qualified electrician if you are unsure about any part of the installation process.
- Do not exceed the specified electrical ratings of the device.

SETUP AND INSTALLATION

Tools Required:

- Screwdriver (Phillips and/or Flathead)
- Wire Strippers
- Electrical Tape (optional)
- Voltage Tester

Wiring Instructions:

1. **Turn Off Power:** Locate the circuit breaker or fuse that supplies power to the outlet box. Turn it OFF. Verify power is off using a voltage tester.
2. **Remove Old Receptacle (if applicable):** Unscrew the wallplate and then the mounting screws holding the old receptacle in the box. Carefully pull the receptacle out and disconnect the wires.
3. **Prepare Wires:** Strip approximately 1/2 inch (12.7 mm) of insulation from the end of each wire.
4. **Connect Wires:**
 - Connect the **hot (black)** wire to one of the brass-colored terminal screws.
 - Connect the **neutral (white)** wire to one of the silver-colored terminal screws.
 - *Note: This model is non-grounding. If a grounding wire is present in your box, cap it off or secure it away from the receptacle terminals.*
5. **Mount Receptacle:** Carefully fold the wires into the electrical box. Secure the receptacle to the box using the provided mounting screws.
6. **Install Wallplate:** Attach the wallplate over the receptacle.
7. **Restore Power:** Turn the power back ON at the circuit breaker or fuse box.
8. **Test:** Test the receptacle with a known working appliance.

OPERATING INSTRUCTIONS

The Leviton 5032-I single receptacle operates as a standard electrical outlet. Once properly installed and power is restored, it provides 20 Amp, 125/250 Volt power for compatible electrical devices. Simply insert the plug of your appliance into the receptacle slots.

- Ensure the appliance plug matches the receptacle configuration.
- Do not force plugs into the receptacle.
- Avoid overloading the circuit by connecting too many high-power devices.

MAINTENANCE

The Leviton 5032-I receptacle requires minimal maintenance. Regular inspection is recommended to ensure safe and reliable operation.

- **Cleaning:** Clean the surface of the receptacle and wallplate with a soft, damp cloth. Do not use abrasive cleaners or solvents. Ensure power is off before cleaning if possible.
- **Inspection:** Periodically check for any signs of damage, such as cracks, discoloration, or loose connections. If any damage is observed, turn off power and replace the receptacle immediately.
- **Loose Connections:** If the receptacle feels loose in the wall, turn off power and tighten the mounting screws. If the wires feel loose at the terminals, turn off power and re-tighten the terminal screws.

TROUBLESHOOTING

Problem	Possible Cause	Solution
No power at receptacle.	Circuit breaker tripped or fuse blown. Loose wiring connection. Faulty receptacle.	Reset circuit breaker or replace fuse. Turn off power, check and tighten all wire connections. Turn off power, replace receptacle.
Receptacle feels hot.	Overloaded circuit. Loose wire connection. Internal damage.	Unplug some devices. Turn off power, check and tighten all wire connections. Turn off power, replace receptacle immediately.
Plug falls out easily.	Worn out receptacle contacts.	Turn off power, replace receptacle.

If troubleshooting steps do not resolve the issue, contact a qualified electrician or Leviton customer support.

SPECIFICATIONS

Brand	Leviton
Model Number	5032-I
Amperage	20 Amp
Voltage	125/250 Volt
Receptacle Type	Single, Narrow Body, Straight Blade, Commercial Grade
Color	Ivory
Material	Plastic
Dimensions (L x W x H)	Approximately 1 x 1.4 x 4.1 inches (or 3.74"L x 1.57"W)
Item Weight	1.6 ounces
Certification	NEMA
Country of Origin	China

WARRANTY AND SUPPORT

Warranty: This Leviton product is covered by a manufacturer's warranty. Please refer to the official Leviton website or contact their customer service for specific warranty terms and conditions.

Customer Support: For technical assistance, installation questions, or warranty claims, please contact Leviton Customer Support:

- **Website:** www.leviton.com
- Refer to the product packaging or the Leviton website for phone numbers and email contacts specific to your region.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question