

[Manuals.plus](#) /

› [Lithonia Lighting](#) /

› Lithonia Lighting Ferros 11536 BN M6 Mini-Pendant Light Instruction Manual

Lithonia Lighting 11536 BN M6

Lithonia Lighting Ferros 11536 BN M6 Mini-Pendant Light Instruction Manual

Model: 11536 BN M6

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Lithonia Lighting Ferros Energy Star Indoor Mini-Pendant Light, model 11536 BN M6. This brushed nickel mini-pendant features acid-etched opal glass and includes a 13-Watt integrated GU24 spiral 2700K fluorescent lamp/ballast for energy efficiency and long life. It operates with a standard electronic ballast (120-Volt, 60Hz) to ensure flicker-free and quiet operation. Please read all instructions carefully before proceeding with installation.







Image: Front view of the Lithonia Lighting Ferros Mini-Pendant Light, showcasing its brushed nickel finish and opal glass shade.

SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the fuse or circuit breaker before installing or servicing.
- **WARNING:** Risk of fire. Use only with specified bulb type and wattage.
- Consult a qualified electrician if you are unsure about the installation process.
- Ensure all electrical connections are made in accordance with local codes and ordinances.
- This fixture is designed for indoor use only.
- For use with non-dimmable switches only.

SETUP AND INSTALLATION

All necessary mounting hardware is included with your pendant light.

1. **Prepare for Installation:** Turn off power at the circuit breaker or fuse box. Clear the work area.
2. **Unpack Contents:** Carefully remove all components from the packaging. Inspect for any damage.
3. **Mounting Bracket Installation:** Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure it is securely fastened.
4. **Wiring Connections:**
 - Connect the *green or bare copper* ground wire from the fixture to the *green or bare copper* ground wire from the junction box.
 - Connect the *white* wire from the fixture to the *white* (neutral) wire from the junction box.
 - Connect the *black* wire from the fixture to the *black* (hot) wire from the junction box.
 - Secure all connections with wire nuts and wrap with electrical tape.
5. **Fixture Attachment:** Carefully tuck all wires into the junction box. Attach the fixture canopy to the mounting bracket, securing it with the provided screws or nuts.
6. **Glass Shade Installation:** Install the acid-etched opal glass shade onto the fixture according to the specific design.
7. **Bulb Installation:** The fixture includes a 13-Watt integrated GU24 spiral 2700K fluorescent lamp. Ensure it is properly seated.
8. **Restore Power:** Turn power back on at the circuit breaker.



Image: Angled view of the Lithonia Lighting Ferros Mini-Pendant Light, highlighting the brushed nickel rod and the opal glass shade.

OPERATING INSTRUCTIONS

Once installed, the Lithonia Lighting Ferros Mini-Pendant Light operates like any standard light fixture.

- Turn the light on or off using a standard wall switch.
- This fixture is designed for use with **non-dimmable switches only**. Attempting to use it with a dimmer switch may cause damage to the ballast or bulb, and will void the warranty.
- The integrated electronic ballast ensures quiet operation and no flickering.

MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your pendant light.

- **Cleaning:** Disconnect power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners or solvents, as these may damage the finish or glass.
- **Bulb Replacement:** The fixture uses a 13-Watt integrated GU24 spiral 2700K fluorescent lamp. While designed for long life, if replacement is needed, ensure power is off. Carefully remove the old bulb and replace it with a new GU24 fluorescent bulb of the same wattage and type.

TROUBLESHOOTING

If your pendant light is not functioning correctly, refer to the following common issues and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	◦ No power to the fixture. ◦ Loose wiring connection. ◦ Faulty bulb.	◦ Check circuit breaker or fuse. ◦ Ensure wall switch is ON. ◦ Turn off power, check all wiring connections. ◦ Replace bulb with a known good GU24 fluorescent bulb.
Light flickers or hums.	◦ Incorrect bulb type or wattage. ◦ Loose wiring. ◦ Used with a dimmer switch.	◦ Ensure correct 13-Watt GU24 fluorescent bulb is used. ◦ Turn off power, check all wiring connections. ◦ This fixture is not compatible with dimmer switches. Remove dimmer and replace with a standard ON/OFF switch.

SPECIFICATIONS

Feature	Detail
Model Number	11536 BN M6
Brand	Lithonia Lighting
Color	Brushed Nickel
Material	Glass
Light Fixture Form	Pendant
Indoor/Outdoor Usage	Indoor
Power Source	Corded Electric
Light Source	Fluorescent (GU24 spiral 2700K)
Number of Light Sources	1
Voltage	120 Volts
Wattage	13 Watts

Feature	Detail
Mounting Type	Protruding
Included Components	Bulb
UPC	784231184684
Energy Star Certified	Yes

WARRANTY AND SUPPORT

The Lithonia Lighting Ferros Mini-Pendant Light comes with a **2-year warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical support, or further assistance, please contact Lithonia Lighting customer service. Refer to your purchase documentation for specific contact details.

Please retain your proof of purchase for warranty purposes.

© 2023 Lithonia Lighting. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

