

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Crystorama](#) /

› [Crystorama Maria Theresa 4-Light Mini Chandelier \(Model 4474-GD-CL-MWP\) Instruction Manual](#)

Crystorama 4474-GD-CL-MWP

Crystorama Maria Theresa 4-Light Mini Chandelier

Model: 4474-GD-CL-MWP

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Crystorama Maria Theresa 4-Light Mini Chandelier. Please read all instructions carefully before beginning installation and retain this manual for future reference.



Figure 1: Fully assembled Crystorama Maria Theresa 4-Light Mini Chandelier.

The Maria Theresa collection features a traditional design with classic elements from the 18th and 19th centuries. It includes glass paneled arms and a gold metal finish, suitable for traditional interior settings.

2. SAFETY INFORMATION

- **WARNING:** This product can expose you to chemicals including lead, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov.
- Always turn off the main power supply at the circuit breaker before installing, cleaning, or servicing the fixture.
- This fixture is authorized for use in dry interior locations only.
- Ensure all electrical connections comply with local codes and ordinances, as well as the National Electric Code (NEC). If you are unfamiliar with electrical wiring, consult a qualified electrician.
- Use only the specified bulb type and wattage to avoid fire or electrical hazard.
- Handle crystal components with care to prevent breakage.

3. WHAT'S IN THE BOX

Verify that all components are present before beginning installation. If any parts are missing or damaged, contact Crystorama customer service.

- Chandelier Fixture Body
- Mounting Hardware (Canopy, Chain, Screws, Wire Nuts)
- Crystal Components
- Instruction Manual
- **Note:** Bulbs are not included.

4. SETUP AND INSTALLATION

Professional installation is recommended for this lighting fixture.

1. **Turn Off Power:** Before starting, ensure the power to the installation area is turned off at the main circuit breaker.
2. **Prepare Mounting Location:** Securely attach the mounting bracket to the ceiling junction box. Ensure the junction box can support the weight of the chandelier (approximately 8.8 lbs).
3. **Adjust Chain Length:** Determine the desired hanging height. Adjust the chain length by removing links as needed. Thread the electrical wires through the chain and canopy.



Figure 2: Chandelier ceiling canopy and chain for mounting.

4. **Wire Connections:** Connect the fixture's wires to the house electrical wires using appropriate wire nuts. Connect the black wire (live) to the black wire, the white wire (neutral) to the white wire, and the ground wire to the ground wire.
5. **Secure Canopy:** Push the canopy up to the ceiling and secure it to the mounting bracket with the provided screws.
6. **Attach Crystal Components:** Carefully attach all crystal components to the chandelier frame according to the included diagram (if provided separately). Refer to Figure 3 for a detailed view of crystal placement.



Figure 3: Detailed view of crystal and light socket assembly.

7. **Install Bulbs:** Screw in four E12 Candelabra base bulbs (not included) into the sockets. Do not exceed 60 watts per bulb.
8. **Restore Power:** Once installation is complete and all components are secure, restore power at the circuit breaker.

5. OPERATING INSTRUCTIONS

The Maria Theresa Chandelier is designed for simple operation. Once installed and wired correctly, it can be controlled by a standard wall switch (not included) or a compatible dimmer switch.

- **Power On/Off:** Use the wall switch connected to the fixture to turn the chandelier on or off.
- **Dimming (Optional):** If connected to a compatible dimmer switch, you can adjust the light intensity. Ensure that the bulbs used are dimmable.
- **Bulb Type:** This fixture uses E12 Candelabra base bulbs. The maximum wattage per bulb is 60 watts.

6. MAINTENANCE

Regular maintenance will help preserve the beauty and functionality of your chandelier.

- **Cleaning:** To clean the metal finish, wipe with a soft, dry cloth. Do not use abrasive cleaners or polishes, as they may damage the finish.
- **Crystal Cleaning:** The crystal components can be gently wiped with a soft, damp cloth. For a deeper clean, a mild glass cleaner can be sparingly applied to a cloth, then wiped onto the crystals. Avoid spraying cleaner directly onto the fixture to prevent damage to electrical components.
- **Bulb Replacement:** Ensure the power is turned off at the circuit breaker before replacing bulbs. Allow old bulbs to cool completely before removal. Replace with new E12 Candelabra base bulbs, not exceeding 60 watts.

7. TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Light does not turn on	No power to fixture; Loose wiring; Faulty bulb	Check circuit breaker; Verify wire connections; Replace bulb(s)
Flickering lights	Loose bulb; Incompatible dimmer; Loose wiring	Tighten bulb; Ensure dimmer is compatible with bulbs; Check wiring connections
Chandelier hangs unevenly	Improper mounting; Uneven chain adjustment	Re-secure mounting bracket; Adjust chain links for balance

If the problem persists after attempting these solutions, contact a qualified electrician or Crystorama customer support.

8. SPECIFICATIONS

Detailed product specifications for the Maria Theresa 4-Light Mini Chandelier.



Figure 4: Chandelier dimensions (16.5"L x 16.5"W x 15"H).

Feature	Detail
Brand	Crystorama
Model Number	4474-GD-CL-MWP
Color	Gold

Feature	Detail
Material	Glass, Crystal
Style	Traditional
Product Dimensions	16.5"L x 16.5"W x 15"H
Indoor/Outdoor Usage	Indoor
Power Source	Hardwired
Installation Type	Semi Flush Mount (can be adapted for chain hang)
Light Source Type	E12 Candelabra
Number of Light Sources	4
Voltage	120 Volts
Wattage (Max)	60 watts per bulb
Item Weight	8.8 Pounds
Assembly Required	Yes
Safety Standard	UL Listed

9. WARRANTY AND SUPPORT

This product is covered by a manufacturer's warranty. For specific warranty details, please refer to the documentation included with your purchase or contact Crystorama directly.

For additional support, product information, or to explore other Crystorama products, please visit the official Crystorama store:

[Visit the Crystorama Store](#)

10. PRODUCT OVERVIEW VIDEO

Watch this official video for an overview of the Crystorama Maria Theresa Collection, showcasing its design and crystal details.

Video: Crystorama Maria Theresa Collection overview.

