

- Manuals.plus /
- › SentrySafe /
- › SentrySafe T6-331 Digital Coded Keypad Floor Safe User Manual

SentrySafe T6-331

# SentrySafe T6-331 Digital Coded Keypad Floor Safe User Manual

Model: T6-331  
Brand: SentrySafe

## PRODUCT OVERVIEW

The SentrySafe T6-331 XX-Large Black Floor Safe is designed to protect your most precious valuables and provide peace of mind. Featuring robust construction and advanced security features, this spacious safe is ideal for safeguarding important documents, jewelry, handguns, and other irreplaceable items. It offers reliable protection against theft and unauthorized access with its solid steel frame and reinforced door.



*Front view of the SentrySafe T6-331 Floor Safe with the door slightly ajar, showing the digital keypad and handle.*

## KEY FEATURES

- **Home Safe:** Protects valuables with a soft interior lining and removable shelving. Suitable for laptops, jewelry, and is California DOJ certified for firearm storage.
- **Digital Lock:** Features a programmable keypad, allowing for an eight-digit combination for multiple user options.
- **Security:** Equipped with four live-locking bolts, steel construction, a pry-resistant door, and included bolt-down hardware to prevent unauthorized entry or removal.
- **Interior Organization:** Includes a key rack and bungee organizational system for easy-to-misplace items.
- **Spacious Interior:** XX-large safe secures all your valuables. Interior dimensions: 22.9 inch H x 14.3 inch W x 11.5 inch D. Exterior dimensions: 24 inch H x 15.4 inch W x 16.1 inch D.
- **Battery Recommendation:** For optimal performance, use four high-quality, name-branded, alkaline AA batteries

with an expiration date 8-10 years from the current year. Generic and rechargeable batteries may not provide sufficient lifespan.



## Set your own digital combination

*Close-up view of the digital keypad on the SentrySafe T6-331, highlighting the programmable combination feature.*



# Four live-locking bolts and steel construction

*Interior view of the safe door, showing the four live-locking bolts and solid steel construction for enhanced security.*



# Home safe with carpeted interior and removable shelving

*Interior of the SentrySafe T6-331, showcasing the carpeted shelves and ample storage space for various valuables.*

## SETUP

### Battery Installation

The digital keypad requires four AA batteries. To install, slide the keypad assembly upwards to reveal the battery compartment. Insert the batteries according to the polarity indicators. Ensure the battery pack is securely reattached.

### Setting Your Digital Code

Refer to the included quick start guide for detailed instructions on programming your personal digital combination. It is recommended to choose a code that is easy for you to remember but difficult for others to guess.

### Bolting Down the Safe

For enhanced security, the safe can be bolted to the floor. Hardware for this purpose is included. Select a suitable location, mark the drilling points through the pre-drilled holes inside the safe, and follow the instructions to secure the safe firmly to the floor.

### Opening the Safe

1. Enter your programmed digital code on the keypad.
2. Once the code is accepted (indicated by a light or sound), turn the handle to open the safe door.

### Emergency Key Access

In case of battery failure or if you forget your digital code, the safe can be opened using the emergency keys provided. The keyhole is discreetly located behind the digital keypad assembly.

1. Slide the digital keypad assembly upwards to detach it from the safe door.
2. Locate the hidden keyhole.
3. Insert one of the emergency keys and turn it to unlock the safe.
4. Turn the handle to open the door.



# Set your own digital combination

*The digital keypad, which can be slid up to reveal the emergency key access point.*

## Battery Replacement

It is recommended to replace the batteries annually or when the low battery indicator appears. Always use new, high-quality alkaline AA batteries.

## Moisture Management

SentrySafe products offering fire protection have a proprietary insulation with high moisture content. The airtight seal for water resistance can also cause moisture to accumulate inside. To prevent this:

- Open your unit once every two weeks to allow for air circulation and reduce moisture accumulation.
- If storing delicate items such as jewelry with working parts, watches, stamps, or photos, place them in an air-tight container before storing them in the safe.
- Do NOT store pearls, computer disks, audio-visual cassettes, or photo negatives directly in this safe due to potential moisture damage.

## TROUBLESHOOTING

### Forgotten Code or Dead Batteries

If you forget your digital code or the batteries die, use the emergency keys provided to open the safe. The keyhole is located behind the slide-up digital keypad assembly.

### Door Not Locking Properly

If the door does not lock securely, inspect the foam seal around the door frame. In some cases, a thick seal might interfere with the locking mechanism. Adjustment or replacement with a thinner fireproof version may be necessary. Ensure no obstructions are preventing the bolts from fully extending.

### Strong Odor or High Humidity Inside

A strong odor or high humidity is common in fire-protected safes due to their insulation and airtight design. This is normal. To mitigate this, regularly air out the safe by opening it every two weeks. For sensitive items, always use airtight containers.

## SPECIFICATIONS

| Feature            | Detail                 |
|--------------------|------------------------|
| Brand              | SentrySafe             |
| Product Dimensions | 15.4"D x 16.1"W x 24"H |
| Lock Type          | Combination            |
| Color              | Black                  |
| Capacity           | 2.18 Cubic Feet        |
| Material           | Alloy Steel            |

|                        |                                  |
|------------------------|----------------------------------|
| Special Feature        | Bolt Down                        |
| Mounting Type          | Free Standing                    |
| Control Type           | Push Button Control              |
| Included Components    | Safe, Bolt Down Hardware, Manual |
| Item Weight            | 81.4 pounds                      |
| Water Resistance Level | Not Water Resistant              |
| Chamber Depth          | 11.5 Inches                      |
| Chamber Height         | 22.9 Inches                      |
| Chamber Width          | 14.3 Inches                      |
| Model Number           | T6-331                           |
| Power Source           | Battery Powered                  |



## Exterior

**A: 15.4 in.**

**B: 16.1 in.**

**C: 24 in.**

## Interior

**A: 14.3 in.**

**B: 11.5 in.**

**C: 22.9 in.**

**Weight**  
**105 lbs.**

**Door Clearance**  
**12 in.**

*Diagram showing the exterior and interior dimensions of the SentrySafe T6-331.*

## WARRANTY INFORMATION

The SentrySafe T6-331 comes with a 1 Year Manufacturer's Warranty. Please retain your proof of purchase for warranty claims.

## SUPPORT

For additional support, detailed instructions, or frequently asked questions, please refer to the official User Manual PDF available at: [SentrySafe T6-331 User Manual \(PDF\)](#).

For further assistance, please contact SentrySafe customer support through their official website or the contact information provided in your product packaging.

## ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

### Name

Anonymous

### Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

### Question

Example: How do I reset this device or fix this error?

### Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

---

Open the live page

<https://manuals.plus/asin/B0052U3E4W>

More documents and user manuals: <https://manuals.plus/>