

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Livex Lighting](#) /

› [Livex Lighting 5006-02 Williamsburgh 6 Light Polished Brass Chandelier User Manual](#)

## Livex Lighting 5006-02

# Livex Lighting 5006-02 Williamsburgh 6 Light Polished Brass Chandelier User Manual

## INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Livex Lighting 5006-02 Williamsburgh 6 Light Polished Brass Chandelier. Please read all instructions carefully before beginning installation and retain this manual for future reference.



**Figure 1:** The Livex Lighting 5006-02 Williamsburgh 6 Light Polished Brass Chandelier, showcasing its traditional design and polished brass finish.

## SAFETY INFORMATION

**WARNING:** To avoid electric shock, always shut off power at the fuse box or circuit breaker before installation, removal, or servicing. All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with installing electrical fixtures.

- Ensure the mounting surface can support the weight of the fixture.
- Do not exceed the specified wattage for bulbs.
- Handle glass components with care to prevent breakage.
- Keep flammable materials away from the light source.

## PACKAGE CONTENTS

Verify that all parts are included before beginning installation. If any parts are missing or damaged, contact Livex Lighting customer service.

- Chandelier body with pre-wired sockets
- Mounting hardware (crossbar, mounting screws, wire nuts)
- Canopy
- Chain
- Collar ring
- Threaded pipe
- Loop
- Candle sleeves (if not pre-installed)

## SETUP AND INSTALLATION

**WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.**

**Figure 2:** Detailed installation diagram and steps for the Livex Lighting Williamsburgh Chandelier.

### Assembling the Fixture (Refer to Figure 2, FIG.2)

1. Return the arms to their suitable position.
2. Attach the collar (J) onto the top coupling of the lamp body (K) by turning it clockwise until tight.
3. Attach the pipe screw (N) into the bottom coupling of the lamp body (K). Lock it securely with the hex nut. Attach the cover (O) to the bottom pipe screw of the lamp body, lock it securely with the fixture loop (P).
4. Slide the cover (M) onto the lamp holder, slide the candle sleeve (L) over the lamp holder.
5. Install the light bulbs (not included) in accordance with the fixture specifications.**NOTE: DO NOT EXCEED THE SPECIFIED WATTAGE!**

### Hanging the Fixture (Refer to Figure 2, FIG.1)

1. Shut off power at the circuit breaker and remove old fixture from ceiling, including the old single bar.
2. Carefully unpack new fixture and lay all the parts on a clean surface.

3. Thread nipple (C) into loop (F) until snug.
4. Thread other end of nipple (C) with loop attached into single bar (D) until snug.
5. Place lock washer (B) over end of nipple protruding through single bar and thread hex nut (A) onto nipple until tight.
6. Take this single bar assembly and mount to ceiling junction box with junction box screws (E). Tighten screws securely with screwdriver.
7. Using proper chain pliers to open one end link of the chain provided and connect to the fixture loop. Close the link.
8. By measuring, determine correct number of links needed for proper hanging height.
9. Using proper chain pliers disconnect and discard remaining chain.
10. Lace the fixture wires through the chain.
11. Slip loop collar (H) over the chain, then do the same with the canopy (G).
12. Open the other end link of the chain and hang the fixture on the loop at the ceiling. Close the link.
13. Feed the fixture wires through the loop (F) and nipple (C) and pull until taut.

### Connecting the Wires (Refer to Figure 2, FIG.3)

1. Take the black wire from the ceiling junction box and the smooth wire leg from the fixture and twist bare ends together. Twist wire connector onto end of wire until snug.
2. Repeat same process with white junction box wire and ribbed wire leg of fixture wire **NOTE:** Twist wires together in the same direction you twist the wire connector onto wires.
3. If your junction box has a grounding wire (green or bare copper), attach this wire and the bare copper wire from the fixture together as step 1. If junction box has no ground wire, attach the bare copper fixture wire to the green ground screw on the crossbar.
4. Tuck these wire connections neatly into the ceiling outlet box and then raise the canopy (G) all the way to the ceiling. Raise the loop (H) and thread onto ceiling loop protruding through canopy.

## OPERATING INSTRUCTIONS

---

Once installed, restore power at the circuit breaker. The chandelier is designed for use with standard wall switches and is dimmable. Ensure compatible dimmer switches and bulbs are used for dimming functionality.

- **Turning On/Off:** Use the wall switch connected to the fixture.
- **Dimming:** If a compatible dimmer switch is installed, adjust the dimmer to control the light intensity.

## MAINTENANCE

---

Regular maintenance ensures the longevity and appearance of your chandelier.

- **Cleaning:** Dust the fixture regularly with a soft, dry cloth. For more thorough cleaning, use a slightly damp cloth with mild soap, then wipe dry immediately. Avoid abrasive cleaners or solvents that may damage the finish.
- **Bulb Replacement:** Ensure power is off at the circuit breaker before replacing bulbs. Allow bulbs to cool completely before touching. Replace with E12 base, 60-watt maximum incandescent bulbs (or equivalent LED/CFL bulbs).
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

## TROUBLESHOOTING

---

If you encounter issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power to fixture, faulty bulb, loose wiring connection.	Check circuit breaker. Replace bulb. Verify wire connections are secure (with power off).
Flickering lights	Loose bulb, incompatible dimmer, faulty wiring.	Tighten bulbs. Ensure dimmer is compatible with bulbs. Check wiring (with power off).
One light socket not working	Faulty bulb, loose connection to socket, debris in socket.	Replace bulb. Check for debris in socket. If issue persists, contact customer support.

## SPECIFICATIONS


- Brand:** Livex Lighting
- Model Number:** 5006-02
- Finish:** Polished Brass
- Material:** Alloy Steel, Glass (Shade)
- Style:** Traditional
- Product Dimensions:** 24" L x 24" W x 18" H
- Number of Light Sources:** 6
- Bulb Base:** E12
- Max Wattage per Bulb:** 60 watts
- Voltage:** 120 Volts
- Dimmable:** Yes (with compatible dimmer)
- Installation Type:** Suspended
- Indoor/Outdoor Usage:** Indoor
- Item Weight:** 6.39 pounds




## WARRANTY AND SUPPORT

This Livex Lighting product comes with a **1-year limited warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or unauthorized modifications.

For warranty claims, technical support, or replacement parts, please contact Livex Lighting customer service. Keep your proof of purchase for warranty validation.

## Related Documents - 5006-02

	<p><a href="#">Livex Lighting Fixture Installation Instructions: Models 76184, 76188, 76194</a></p> <p>Step-by-step assembly and wiring instructions for Livex Lighting outdoor post top lanterns, models 76184, 76188, and 76194. Includes safety warnings and diagram descriptions.</p>
---	---

 <p><b>Declaration of PFAS Compliance</b> Statement of PFAS Compliance Livex Lighting Inc. is committed to transparency and accountability in our operations. We believe that it is important for our customers to have access to information about the presence of PFAS in our products. We are providing this declaration to help you make informed decisions about your purchases.</p>	<p><b><u>Livex Lighting PFAS Compliance Declaration</u></b></p> <p>Official declaration from Livex Lighting, Inc. confirming adherence to state and federal regulations concerning PFAS in all supplied lighting products, with a commitment to transparency regarding product composition.</p>
 <p><b>Declaration of PFAS Compliance</b> Statement of PFAS Compliance Livex Lighting Inc. declares compliance with PFAS regulations, confirming that PFAS are not intentionally added to their AVIANCE lighting products and outlining notification procedures for future changes.</p>	<p><b><u>Livex Lighting Inc. Declaration of PFAS Compliance</u></b></p> <p>Livex Lighting Inc. declares compliance with PFAS regulations, confirming that PFAS are not intentionally added to their AVIANCE lighting products and outlining notification procedures for future changes.</p>
 <p><b>CRYSTORAMA</b> ARMED VINTAGE MODEL 1139-PB-CL-MWP Assembly Instructions Model 1139-PB-CL-MWP</p> <p><b>Crystorama 1139-PB-CL-MWP Chandelier Assembly Instructions</b></p>	<p><b><u>Crystorama 1139-PB-CL-MWP Chandelier Assembly Instructions</u></b></p> <p>Detailed assembly instructions and parts list for the Crystorama 1139-PB-CL-MWP Polished Brass Chandelier. Includes safety warnings, installation steps, and component identification.</p>
 <p><b>ZEVNI A04523 Chandelier Installation Guide</b></p>	<p><b><u>ZEVNI A04523 Chandelier Installation Guide</u></b></p> <p>Installation guide for the ZEVNI A04523 Conakry 6-Light Brass/Black Modern/Contemporary Chandelier. Includes safety warnings, parts list, assembly instructions, wiring diagrams, and cleaning tips.</p>
 <p><b>JONATHAN Y JYL6109A Regina Chandelier Installation Guide</b></p>	<p><b><u>JONATHAN Y JYL6109A Regina Chandelier Installation Guide</u></b></p> <p>Detailed installation and maintenance instructions for the JONATHAN Y JYL6109A Regina 12-inch Crystal/Metal Empire LED Chandelier, including parts list, safety precautions, and assembly steps.</p>