Omron d2f-01f

OMRON D2F-01F Microswitch Instruction Manual

Model: D2F-01F

1. Introduction

This manual provides essential information for the proper installation, operation, and maintenance of the OMRON D2F-01F Microswitch. Designed for precision and durability, these subminiature SPDT switches are commonly used as replacements in various electronic devices, particularly computer mice.

2. Product Overview

The OMRON D2F-01F is a high-quality, subminiature microswitch. It features a single-pole, double-throw (SPDT) configuration, making it versatile for various switching applications. Its compact design and precise actuation make it ideal for integration into small electronic assemblies.




Figure 1: OMRON D2F-01F Microswitch. This image displays the compact black microswitch with its three metal terminals and the plunger actuator on top. The model number "D2F-01F" is clearly visible on the switch body.

Key Features:

- **Type:** Subminiature Microswitch
- **Configuration:** SPDT (Single-Pole, Double-Throw)
- **Operation Mode:** ON-NONE-ON
- **Contact Type:** Normally Open (NO)
- **Actuator Type:** Plunger
- **Terminals:** 3 pins (Common, Normally Open, Normally Closed)

3. Setup and Installation

Installation of the OMRON D2F-01F Microswitch typically involves soldering. It is recommended that this procedure be performed by individuals with experience in electronics soldering to prevent damage to the switch or the host device.

Required Tools:

- Soldering Iron
- Solder (e.g., Rosin Core Solder)
- Desoldering Pump or Braid
- Small Pliers or Tweezers
- Safety Glasses
- Appropriate Screwdrivers for the device

Installation Steps (General Guide for Mouse Replacement):

1. **Disassemble Device:** Carefully open the electronic device (e.g., computer mouse) where the switch will be replaced. Note the location and orientation of the existing switch.
2. **Desolder Old Switch:** Using a soldering iron and desoldering tool, carefully remove the old microswitch from the circuit board. Ensure all solder is removed from the through-holes.
3. **Prepare New Switch:** Align the OMRON D2F-01F Microswitch with the corresponding holes on the circuit board. Ensure the orientation matches the original switch. The common (C), normally open (NO), and normally closed (NC) terminals must be correctly aligned.
4. **Solder New Switch:** Solder each pin of the new microswitch to the circuit board. Apply heat to the pad and pin simultaneously, then feed solder until a good joint is formed. Avoid excessive heat.
5. **Inspect Joints:** Visually inspect all solder joints for proper connection, ensuring no bridges between pins.
6. **Reassemble Device:** Carefully reassemble the electronic device, ensuring all components are correctly seated and screws are tightened.

Caution: *Improper soldering can damage the switch or the circuit board. If unsure, seek professional assistance. Always disconnect power before beginning any installation.*

4. Operating Principles

The OMRON D2F-01F is a momentary action switch. When the plunger actuator is pressed, the internal contacts switch from their default state to the actuated state. Upon release of the plunger, the contacts return to their default state.

- **Normally Open (NO):** The circuit connected to the NO terminal is open (no current flow) when the switch is at rest and closes (current flows) when the plunger is pressed.
- **Normally Closed (NC):** The circuit connected to the NC terminal is closed (current flows) when the switch is at rest and opens (no current flow) when the plunger is pressed.
- **Common (C):** This is the shared terminal for both NO and NC connections.

In typical mouse applications, the Normally Open (NO) contact is used for click detection.

5. Maintenance

OMRON D2F-01F microswitches are designed for long-term reliability and generally require no routine maintenance. However, to ensure optimal performance and longevity:

- **Keep Clean:** Avoid exposing the switch to excessive dust, dirt, or liquids, which can impede plunger movement or contaminate contacts.
- **Proper Handling:** Handle switches by their body, not by the terminals or plunger, to prevent bending or damage.
- **Environmental Conditions:** Operate and store the switches within their specified temperature and humidity ranges to prevent degradation.

6. Troubleshooting

If you experience issues after installing the OMRON D2F-01F Microswitch, consider the following common problems and solutions:

Problem	Possible Cause	Solution
Switch not registering clicks / Intermittent clicks	Poor solder joint Incorrect switch orientation Damaged switch during installation Contamination	Re-solder connections, ensuring strong, clean joints. Verify switch orientation against original or device schematic. Replace switch if physical damage is apparent. Clean the area around the switch.
"Double-clicking" or multiple inputs from a single press	Software debounce issue (less common with new switches) Faulty switch (rare for new OMRON D2F-01F)	Ensure the switch is properly seated and soldered. If problem persists, consider testing with another new switch. Check device drivers or software settings for debounce options.
Switch feels stiff or unresponsive	Misalignment within the device housing Physical obstruction	Re-check the seating of the switch and any associated buttons or levers. Ensure no debris is obstructing the plunger.

7. Specifications

Detailed technical specifications for the OMRON D2F-01F Microswitch:

Attribute	Value
Model Number	D2F-01F
Operation Mode	ON-NONE-ON
Current Rating	0.1 Amps
Operating Voltage	30 Volts
Contact Type	Normally Open
Connector Type	D248-01
Terminal	SPDT
Item Dimensions (L x W x H)	3 x 2.8 x 0.2 inches
Circuit Type	1-way
Actuator Type	Plunger
Contact Material	Copper
International Protection Rating	IP40
Number of Positions	3
Control Method	Touch

Attribute	Value
Color	Black
Wattage	3 watts
Item Weight	0.32 ounces
UPC	799599174741

8. Warranty and Support

For specific warranty information and technical support regarding your OMRON D2F-01F Microswitch, please refer to the official OMRON website or contact OMRON customer service directly. Warranty terms may vary based on region and distributor.
OMRON Official Website: www.omron.com

© 2025 OMRON. All rights reserved. Information subject to change without notice.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question