

[Manuals.plus](#) /

› [Telwin](#) /

› Telwin Mototronic 6/12 Volt Battery Charger User Manual

Telwin Mototronic 6/12 Volt

Telwin Mototronic 6/12 Volt Battery Charger User Manual

Model: Mototronic 6/12 Volt | Brand: Telwin

PRODUCT OVERVIEW

The Telwin Mototronic 6/12 Volt battery charger is specifically designed for charging 6V and 12V lead-acid batteries, including sealed (Gel) and unsealed (Wet) types, commonly used in scooters and motorcycles. This single-phase charger features electronic control of the charging current, automatic charge interruption and resumption, and protection against polarity inversion. It also includes a bypass function to facilitate charging even when sulfation is present on battery terminals.



Image: Telwin Mototronic 6/12 Volt Battery Charger. This image displays the compact design of the charger with its control panel and battery clamps.

IMPORTANT SAFETY INSTRUCTIONS

Please read and understand all safety instructions before operating the battery charger. Failure to follow these instructions may result in electric shock, fire, or serious injury.

- Always read the entire instruction manual before using the charger.
- Use the charger in a well-ventilated area to prevent the accumulation of explosive gases.
- Wear appropriate eye protection and protective clothing when working with batteries.
- Keep the charger and battery out of reach of children.
- Do not expose the charger to rain, snow, or excessive moisture.
- Disconnect the charger from the power outlet before making or breaking connections to the battery.
- Never attempt to charge non-rechargeable batteries.
- Avoid creating sparks or flames near the battery during charging, as batteries can emit explosive hydrogen gas.

- Ensure the battery voltage (6V or 12V) matches the charger's selected setting or automatic detection.

SETUP

Follow these steps to properly set up your Telwin Mototronic 6/12 Volt battery charger:

1. Unpack the charger and inspect it for any signs of damage. Do not use if damaged.
2. Place the charger on a stable, dry, and non-flammable surface, ensuring adequate ventilation.
3. Verify that the battery type and voltage (6V or 12V) are compatible with the charger's specifications.
4. Connect the **red (+)** positive clamp of the charger to the **positive (+)** terminal of the battery.
5. Connect the **black (-)** negative clamp of the charger to the **negative (-)** terminal of the battery.
6. Plug the charger's power cord into a standard 230V AC, 50/60Hz electrical outlet.

OPERATING INSTRUCTIONS

Once the charger is set up, follow these steps for operation:

1. After connecting to the battery and power outlet, the charger will automatically detect the battery voltage (6V or 12V).
2. The charging process will commence automatically. An indicator light on the charger will illuminate to show the charging status.
3. The electronic control system will regulate the charging current and automatically cease charging once the battery reaches full capacity.
4. The charger is designed to automatically resume charging if the battery voltage drops below a certain level, maintaining optimal charge.
5. To disconnect the charger, first unplug the power cord from the electrical outlet.
6. Next, disconnect the **black (-)** negative clamp from the **negative (-)** battery terminal.
7. Finally, disconnect the **red (+)** positive clamp from the **positive (+)** battery terminal.

MAINTENANCE

Proper maintenance ensures the longevity and safe operation of your battery charger:

- Keep the charger clean and dry. Wipe down the exterior with a soft, dry cloth.
- Store the charger in a cool, dry place away from direct sunlight and extreme temperatures when not in use.
- Regularly inspect the power cord, charging cables, and clamps for any signs of damage, fraying, or corrosion. Replace damaged components immediately.
- Do not attempt to open or repair the charger yourself. Refer all servicing to qualified service personnel.

TROUBLESHOOTING

If you encounter issues with your Telwin Mototronic 6/12 Volt battery charger, refer to the following table for common problems and solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Problem	Possible Cause	Solution
Charger not turning on or no indicator lights.	No power supply; faulty outlet; damaged power cord.	Check if the charger is securely plugged into a live electrical outlet. Test the outlet with another device. Inspect the power cord for damage.
Battery not charging.	Loose or incorrect battery connections; severely discharged or damaged battery; incorrect voltage selection.	Ensure battery clamps are securely connected to the correct terminals (+ to +, - to -). Verify the battery is rechargeable and not beyond recovery. Confirm the charger is detecting the correct voltage (6V or 12V).
Polarity inversion indicator active.	Battery clamps connected incorrectly.	Immediately unplug the charger from the power outlet. Disconnect the clamps and reconnect them with the correct polarity (red to positive, black to negative).
Charger gets warm during operation.	Normal operation; poor ventilation.	It is normal for the charger to become warm during use. Ensure it is placed in a well-ventilated area and not covered. If it becomes excessively hot, disconnect and allow it to cool.

TECHNICAL SPECIFICATIONS

Input Voltage	230V AC, 50/60 Hz, 1-phase
Charge Voltage	6V / 12V
Nominal Charge Current	3 - 4 A
Power	50 W
Rated Capacity (6V)	6 - 30 Ah
Rated Capacity (12V)	6 - 30 Ah
Dimensions (L x W x H)	95 x 190 x 180 mm
Weight	1.6 kg
Compatible Devices	Scooters, Motorcycles
ASIN	B006K3JL9C

WARRANTY AND SUPPORT

For detailed warranty information and technical support, please refer to the documentation included with your Telwin Mototronic 6/12 Volt battery charger at the time of purchase. It is recommended to retain your proof of purchase for any warranty claims or service inquiries. You may also visit the official Telwin website or contact their customer service for further assistance.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question