

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [WAC Lighting](#) /

› [WAC Lighting DS-WD06-F35C-WT 6-Inch Double Side Tube Arch Wall Mount Instruction Manual](#)

## WAC Lighting DS-WD06-F35C-WT

# WAC Lighting DS-WD06-F35C-WT 6-Inch Double Side Tube Arch Wall Mount Instruction Manual

Model: DS-WD06-F35C-WT

## INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your WAC Lighting DS-WD06-F35C-WT 6-Inch Double Side Tube Arch Wall Mount fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference.

## SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local and National Electrical Code (NEC) standards. If you are unfamiliar with proper electrical wiring connections, consult a qualified electrician.
- This fixture is designed for 120V AC operation.
- Do not attempt to modify the fixture. Any modifications may void the warranty and create safety hazards.
- This product is ETL & CETL Listed and UL Listed, indicating compliance with safety standards.
- The fixture is IP65 rated, suitable for wet locations.

## PACKAGE CONTENTS

Carefully unpack your fixture and inspect for any damage. Ensure all components are present before discarding packaging materials.

- WAC Lighting DS-WD06-F35C-WT Wall Mount Fixture (1)
- Mounting Hardware Kit (screws, wire nuts, etc.)
- Instruction Manual




Image: The WAC Lighting DS-WD06-F35C-WT 6-inch double-sided tube arch wall mount fixture in white.

## SETUP AND INSTALLATION

Professional installation by a qualified electrician is recommended.

1. **Prepare for Installation:** Turn off power at the main circuit breaker or fuse box. Ensure the power is off before proceeding.
2. **Mounting Location:** Select a suitable wall-mounted location. The fixture is designed for vertical wall mounting.
3. **Attach Mounting Plate:** Secure the fixture's mounting plate to the junction box on the wall using the provided screws. Ensure the plate is firmly attached.
4. **Wiring Connections:** Connect the fixture's wires to the corresponding house wires:
  - Connect the black (hot) wire from the fixture to the black (hot) wire from the junction box.
  - Connect the white (neutral) wire from the fixture to the white (neutral) wire from the junction box.
  - Connect the green or bare copper (ground) wire from the fixture to the green or bare copper (ground) wire from the junction box.

Use approved wire nuts to secure all connections. Ensure no bare wires are exposed.

5. **Secure Fixture:** Carefully tuck all wires into the junction box. Align the fixture with the mounting plate and secure it using the provided screws. Ensure the fixture is flush against the wall and securely fastened.
6. **Restore Power:** Once installation is complete, restore power at the circuit breaker.

**WAC LIGHTING**  
Responsible Lighting®  
Tube Architectural - LED Wall Mount


Model	Beam	Color Temp	CRI	Light Direction	Finish	Order Number
Double DS-WD05 Double, 5", 27x2W	S Spot	927 2700K	90	S Straight up and down 	BK- Black	DS-WD05-5027S-BK
DS-WD06 Double, 6", 36x2W	N Narrow	27 2700K	85			
DS-WD08 Double, 8", 54x2W	F Flood	930 3000K	90			
		30 3000K	85			
		35 3500K	85			
40 4000K	85					
Double DS-WD05 Double, 5", 27x2W	F	927 2700K	90	A Away from the wall 	BK- Black	DS-WD05-F927A-BK
DS-WD06 Double, 6", 36x2W	Flood	27 2700K	85			
DS-WD08 Double, 8", 54x2W	Flood	930 3000K	90			
		30 3000K	85			
		35 3500K	85			
40 4000K	85					
				B Towards the wall 		
				C One side each 		

Image: Technical diagram showing dimensions for various WAC Lighting tube architectural wall mount models, including the DS-WD06.

## OPERATING INSTRUCTIONS

The WAC Lighting DS-WD06-F35C-WT is a double-sided LED wall mount fixture designed to provide both up and down light. It is compatible with standard 120V dimmers (100%-10% dimming range).

- **Power On:** Once installed and power is restored, the fixture will illuminate.
- **Dimming:** If connected to a compatible dimmer switch, adjust the dimmer to control the light output from 100% to 10%.
- **Light Distribution:** This fixture provides light from both the top and bottom openings, creating an architectural lighting effect.



Image: Diagram illustrating the 'One side each' light distribution pattern, where light is emitted from both the top and bottom of the fixture.

## MAINTENANCE

This LED fixture requires minimal maintenance. The LEDs have a rated life of 80,000 hours and are not user-replaceable.

- **Cleaning:** To clean the fixture, ensure power is off. Use a soft, damp cloth. Do not use abrasive cleaners or solvents, as these may damage the finish or electrical components.
- **Inspection:** Periodically inspect the fixture for any signs of damage or loose connections. If any issues are found, disconnect power and consult a qualified electrician.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
---------	----------------	----------

Problem	Possible Cause	Solution
Fixture does not light up	No power to the fixture Incorrect wiring Faulty switch or dimmer	Check circuit breaker and wall switch. Verify wiring connections are secure and correct (refer to Setup section). Test switch/dimmer with another device or replace if faulty.
Light flickers or dims improperly	Incompatible dimmer switch Loose wiring connection	Ensure dimmer is compatible with LED fixtures and within the 10%-100% range. Check all wiring connections for tightness.

## SPECIFICATIONS

Feature	Detail
Model Number	DS-WD06-F35C-WT
Brand	WAC Lighting
Dimensions (L x W x H)	6.25" x 2.88" x 12.5"
Item Weight	12 Pounds
Light Source Type	Integrated LED
Color Temperature	3500 Kelvin
Brightness	Up to 3685 Lumens x2 (Total 4890 Lumens listed in specs)
Color Rendering Index (CRI)	85+
Rated Life	80,000 Hours
Voltage	120 Volts
Dimming	100% - 10% (with compatible dimmer)
Ingress Protection Rating	IP65 (Wet Location Listed)
Certifications	Energy Star, ETL & CETL Listed, UL Listed
Construction Material	Aluminum
Shade Material	Glass
Mounting Type	Wall Mount
Finish	White

## WARRANTY INFORMATION

This WAC Lighting fixture is covered by a **5-year manufacturer's warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. Please retain your proof of purchase for

warranty claims. For full warranty terms and conditions, please refer to the official WAC Lighting website or contact customer support.

## SUPPORT AND CONTACT

If you have any questions regarding the installation, operation, or maintenance of your WAC Lighting DS-WD06-F35C-WT fixture, please contact WAC Lighting customer support or consult a qualified electrician.

**WAC Lighting Official Website:** [www.waclighting.com](http://www.waclighting.com)