

Nite Ize T5C-01-R7

Nite Ize Inova T5 Flashlight User Manual

Model: T5C-01-R7

PRODUCT OVERVIEW

The Nite Ize Inova T5 Flashlight is a precision-engineered lighting instrument designed for professional use. It projects a powerful beam and features a robust construction. This flashlight is powered by 3-123A lithium batteries and incorporates a patented optical system for optimal thermal management and uniform light output. Its tactical mid-body switch allows for easy activation of various lighting modes.



Figure 1: The Nite Ize Inova T5 Flashlight, showcasing its sleek black aluminum body and knurled grip.

SETUP AND BATTERY INSTALLATION

The Inova T5 Flashlight requires three (3) 123A Lithium batteries for operation. These batteries are typically included with your purchase.

Battery Installation Steps:

1. Unscrew the tail cap of the flashlight by rotating it counter-clockwise.
2. Insert three 123A Lithium batteries into the battery compartment, ensuring the positive (+) end of each battery faces towards the head of the flashlight.
3. Carefully screw the tail cap back on by rotating it clockwise until it is securely tightened. Overtightening is not necessary but ensure a snug fit to maintain water resistance.





Figure 2: Close-up view of the flashlight body, showing the mid-body switch and knurling, indicating the area for battery access via the tail cap.

OPERATING INSTRUCTIONS

The Inova T5 features a tactical mid-body switch for easy operation and mode selection.

Power On/Off and Mode Selection:

- **Momentary On:** Lightly press and hold the mid-body switch for temporary illumination. Release to turn off.
- **Constant On (High Mode):** Fully press the mid-body switch until it clicks to activate the flashlight in High mode. Press again to turn off.
- **Mode Cycling:** From the "Constant On" state, quickly press and release the switch to cycle through the available modes: High, Medium, Low, and Strobe. The flashlight will remember the last used constant mode (High, Medium, or Low) when turned off and on again.
- **Strobe Mode:** Access Strobe mode by cycling through the modes as described above.



Figure 3: The Nite Ize Inova T5 Flashlight in operation, demonstrating its powerful beam.

MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your Inova T5 Flashlight.

Cleaning:

- Wipe the exterior of the flashlight with a soft, damp cloth. Avoid abrasive cleaners or solvents.
- For the lens, use a lens cleaning cloth or a soft, lint-free cloth with a small amount of lens cleaning solution.

Battery Replacement:

- Replace batteries when the light output diminishes significantly.
- Always use fresh, high-quality 123A Lithium batteries. Do not mix old and new batteries, or different battery types.
- Remove batteries if the flashlight will not be used for an extended period to prevent potential leakage and damage.

Storage:

Store the flashlight in a cool, dry place away from direct sunlight and extreme temperatures.

TROUBLESHOOTING

If you encounter issues with your Inova T5 Flashlight, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Flashlight does not turn on.	Dead or improperly installed batteries. Corroded battery contacts.	Ensure batteries are inserted correctly with positive (+) ends facing the head. Replace with fresh batteries. Clean battery contacts with a pencil eraser or cotton swab and rubbing alcohol.
Light is dim or flickers.	Low battery power. Loose tail cap or head.	Replace batteries. Ensure tail cap and head are securely tightened.
Cannot cycle through modes.	Switch malfunction or improper operation.	Ensure you are performing quick presses for mode cycling. If the issue persists, contact customer support.

SPECIFICATIONS

Feature	Detail
Model	T5C-01-R7
Light Output (High)	672 Lumens
Light Output (Low)	27 Lumens
Run Time (High)	1 hour 40 minutes
Run Time (Low)	40 hours
Water Resistance	IPX7 (Submersible up to 1 meter for 30 minutes)
Impact Resistance	1 meter
Beam Range	234 meters (768 feet)
Battery Type	3 x 123A Lithium (included)
Material	Aerospace-Grade Aluminum with Type III Hard Coat Anodized Finish
Dimensions	9 x 1.4 x 1.4 inches
Weight	9.9 ounces (0.28 kg)



Figure 4: Dimensions of the Nite Ize Inova T5 Flashlight, showing its length and diameter.

WARRANTY AND SUPPORT

All Nite Ize products purchased from authorized resellers are backed by their worry-free guarantee. This warranty covers defects in materials and workmanship.

For warranty claims, technical support, or any product-related inquiries, please visit the official Nite Ize website or contact their customer service department. Keep your proof of purchase for warranty validation.

For more information, you can visit the [Nite Ize Store on Amazon](#).

© 2024 Nite Ize. All rights reserved.

This manual is for informational purposes only. Specifications are subject to change without notice.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B00P150UH2>

More documents and user manuals: <https://manuals.plus/>