

[Manuals.plus](#) /

› [D-Link](#) /

› D-Link DCS-934L Day & Night Wi-Fi Camera User Manual

D-Link DCS-934L

D-Link DCS-934L Day & Night Wi-Fi Camera User Manual

Model: DCS-934L

1. OVERVIEW

The D-Link DCS-934L Day & Night Wi-Fi Camera is designed to provide reliable surveillance for your home or small office. This camera offers high-quality video streaming to your mobile devices and features advanced capabilities for enhanced security and monitoring.

Key features include:

- **Day & Night Vision:** Equipped with built-in IR LEDs, the camera provides clear visibility up to 16 feet even in complete darkness.
- **Motion Detection:** Advanced motion sensing technology sends automatic push alert notifications to your device when movement is detected.
- **Remote Viewing:** Access live video feeds, control camera functions, and utilize 4x digital zoom through the free mydlink Lite app, available for iOS, Android, and Windows Phone devices.
- **Flexible Connectivity:** Supports both Wi-Fi and Ethernet connections for versatile placement options.
- **Sound Detection:** Alerts can also be triggered by detected sounds.
- **Recording Capabilities:** Capture snapshots and video clips directly to your mobile device.



Figure 1: D-Link DCS-934L Day & Night Wi-Fi Camera (Front View)

2. PACKAGE CONTENTS

Ensure all items are present in your package:

- D-Link DCS-934L Day & Night Wi-Fi Camera
- Power Adapter
- Ethernet Cable
- Mounting Kit
- Quick Install Guide

3. PRODUCT COMPONENTS

Familiarize yourself with the camera's physical components:

3.1 Front View

- **IR LEDs:** Infrared emitters for night vision.
- **Light Sensor:** Detects ambient light to automatically switch between day and night modes.
- **Microphone:** Captures audio from the camera's environment.
- **Camera Lens:** The primary optical component for video capture.

3.2 Back View

- **Power Connector:** For connecting the power adapter.
- **Ethernet Port:** For wired network connection.
- **Power/Link LED:** Indicates power status and network connectivity.
- **Reset Button:** Used to restore factory default settings.
- **WPS Button:** For easy Wi-Fi Protected Setup.



Figure 2: D-Link DCS-934L Day & Night Wi-Fi Camera (Back View with Ports)

4. SETUP

4.1 Initial Setup

Before beginning, ensure you have a working internet connection and your Wi-Fi router is powered on.

1. **Power On:** Connect the power adapter to the camera and plug it into a power outlet. Wait for the Power/Link LED to turn solid green.
2. **Network Connection:**
 - **Wi-Fi (WPS):** If your router supports WPS, press the WPS button on your router, then immediately press the WPS button on the camera. The LED will flash green during connection and turn solid green when connected.
 - **Wi-Fi (Manual):** Download the mydlink Lite app from your device's app store. Follow the in-app instructions to connect the camera to your Wi-Fi network.
 - **Ethernet:** Connect one end of the Ethernet cable to the camera's Ethernet port and the other end to an available LAN port on your router.
3. **mydlink Account:** Create a new mydlink account or log in to an existing one through the mydlink Lite app or the mydlink web portal (www.mydlink.com).
4. **Add Camera:** Follow the prompts in the app or web portal to add your DCS-934L camera to your mydlink account.



* Phone and tablet not included

Figure 3: Remote viewing via mydlink app on mobile devices.

5. OPERATING THE CAMERA

5.1 Live Viewing

Once your camera is set up and connected to your mydlink account, you can view live video from anywhere using the mydlink Lite app or the mydlink web portal. Simply open the app or log in to the portal and select your camera from the device list.

5.2 Motion and Sound Detection

The DCS-934L can alert you to activity. To configure detection settings:

1. Access your camera settings via the mydlink Lite app or web portal.
2. Navigate to the **Motion Detection** or **Sound Detection** section.

3. Enable the desired detection type.
4. Adjust sensitivity levels and define detection zones (for motion detection) as needed.
5. Configure alert actions, such as push notifications to your mobile device or email alerts with snapshots.

5.3 Night Vision

The camera automatically switches to night vision mode in low-light conditions. The built-in IR LEDs illuminate the area, allowing for clear black-and-white video up to 16 feet. This feature can be manually toggled in the camera settings if desired.

5.4 Digital Zoom

While viewing live video, you can use the pinch-to-zoom gesture on your mobile device (or corresponding controls on the web portal) to digitally zoom up to 4x into the video feed.

6. MAINTENANCE

6.1 Cleaning

To maintain optimal performance, periodically clean the camera lens with a soft, dry cloth. Avoid using harsh chemicals or abrasive materials.

6.2 Firmware Updates

D-Link regularly releases firmware updates to improve performance and add new features. Check for available updates through the mydlink Lite app or the mydlink web portal and follow the instructions to install them.

6.3 Resetting the Camera

If you encounter persistent issues or wish to reconfigure your camera, you can perform a factory reset:

1. With the camera powered on, use a paperclip or thin object to press and hold the **Reset Button** on the back of the camera for approximately 10 seconds.
2. Release the button when the Power/Link LED begins to flash red.
3. The camera will restart with factory default settings. You will need to set it up again as a new device.

7. TROUBLESHOOTING

If you experience problems with your D-Link DCS-934L camera, refer to the following common issues and solutions:

- **Camera not connecting to Wi-Fi:** Ensure the camera is within range of your Wi-Fi router. Verify your Wi-Fi password is correct. Try using the WPS button method if your router supports it.
- **No video feed:** Check the camera's power connection and ensure the Power/Link LED is solid green. Verify your internet connection is active.
- **Motion/Sound detection not triggering alerts:** Review your detection settings in the mydlink app/portal. Adjust sensitivity levels and ensure alert notifications are enabled.
- **Poor video quality:** Ensure the camera lens is clean. Check your network bandwidth; a slow internet connection can affect streaming quality.

For more detailed troubleshooting or technical support, please visit the D-Link support website or consult the full product manual.

8. SPECIFICATIONS

DCS-934L DAY & NIGHT WI-FI CAMERA

System Integration		
System Requirements for Web Interfaces	Operating system: Microsoft Windows 8/7/Vista¹ or Mac OS X (10.6 and above)	Browser: Internet Explorer 8, Firefox 12 or above, Safari 6.0 or above, Chrome 20 or higher with Java installed and enabled
Event Management	Event notification and uploading of snapshots/video clips via e-mail (SMTP)	- Motion detection - Sound level detection
Remote Access		
Remote Management	Configuration accessible via web browser	
Mobile Support	mydlink Lite app for iOS, Android and Windows	mydlink+ app for iOS and Android
General		
Weight	Camera only: 0.13 lbs	With mounting base: 0.20 lbs
Power	5 V DC 1 A, 50/60 Hz	
Power Consumption	2.84 watts	
Temperature	Operating: 32 to 104 °F (0 to 40 °C)	Storage: -4 to 158 °F (-20 to 70 °C)
Humidity	Operating: 20% to 80% non-condensing	Storage: 5% to 95% non-condensing
Certifications	- IC - CE	- FCC Class B - C-Tick
Dimensions (H x W x D)	Camera only: 3.8 x 2.4 x 1.3 inches	With mounting base: 5 x 3.1 x 3.1 inches
Package Contents	- Day & Night Wi-Fi Camera (DCS-934L) - Power Adapter - Ethernet Cable	- Mounting Kit - Quick Install Guide
Order Information		
Part Number	Description	
DCS-934L	Day & Night Wi-Fi Camera	

¹Computer must adhere to Microsoft's recommended system requirements.

For more information

U.S.A. | 17595 Mt. Herrmann Street | Fountain Valley, CA 92708 | 800.326.1688 | dlink.com

©2015 D-Link Corporation/D-Link Systems, Inc. All rights reserved. D-Link, the D-Link logo, mydlink and the D-link RoHS logo are trademarks or registered trademarks of D-Link Corporation or its subsidiaries in the United States and/or other countries. Other trademarks or registered trademarks are the property of their respective owners. iPhone and iPad are registered trademarks of Apple Inc. Android is a trademark of Google Inc. Windows is a registered trademark of Microsoft Inc.



Updated May 2015



mydlink Lite only

D-Link®

Figure 4: Technical Specifications Overview

D-Link DCS-934L Technical Specifications

Feature	Detail
Model Number	DCS-934L

Connectivity Technology	Wireless (Wi-Fi), Wired (Ethernet)
Special Features	Motion Sensor, Night Vision
Indoor/Outdoor Usage	Indoor, Outdoor (with appropriate protection)
Controller Type	Android, iOS
Mount Type	Wall Mount
Form Factor	Dome
Alert Type	Motion Only
Waterproof Rating	IP54
Night Vision Range	16 feet
Video Capture Format	MPEG-4
Item Dimensions	7 x 4 x 3 inches
Item Weight	10.4 ounces

9. WARRANTY AND SUPPORT

For warranty information, technical support, or to download the latest drivers and firmware, please visit the official D-Link website or contact D-Link customer service. Keep your purchase receipt for warranty claims.

© 2023 D-Link Systems, Inc. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B00SIM78R0>

More documents and user manuals: <https://manuals.plus/>