

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Z-Lite](#) /

› [Z-Lite 169-4V-BN 4-Light Brushed Nickel Vanity Installation and User Manual](#)

Z-Lite 169-4V-BN

Z-Lite 169-4V-BN 4-Light Brushed Nickel Vanity Installation and User Manual

Model: 169-4V-BN | Brand: Z-Lite

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Z-Lite 169-4V-BN 4-Light Brushed Nickel Vanity fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference. Proper installation is essential for your safety and the optimal performance of this product.

The Z-Lite 169-4V-BN is a modern 4-light vanity fixture featuring bent frosted glass shades and brushed nickel hardware, designed for indoor use in bathrooms and similar environments. It operates on 120 Volts and uses E12 base incandescent bulbs, with a maximum wattage of 60 watts per bulb.

2. SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.

- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- This fixture is intended for indoor use only. Do not expose to direct water spray or submersion.
- Ensure the mounting surface can support the weight of the fixture.
- Use only the specified bulb type and wattage (E12 base, max 60 watts incandescent). Exceeding the maximum wattage may cause overheating and damage to the fixture or create a fire hazard.
- Do not attempt to modify the fixture. Any modifications may void the warranty and create safety hazards.
- Handle glass components with care to prevent breakage.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation. If any parts are

missing or damaged, do not attempt to assemble or install the fixture. Contact Z-Lite customer support for assistance.

- 1x Z-Lite 169-4V-BN 4-Light Vanity Fixture (includes housing, wiring, and lamp holders)
- 4x Frosted Glass Shades
- Mounting Hardware (e.g., mounting bracket, screws, wire nuts)
- Instruction Manual



Image 1: The Z-Lite 169-4V-BN 4-Light Brushed Nickel Vanity Fixture with its four frosted glass shades.

4. INSTALLATION INSTRUCTIONS

Professional installation is recommended. If you are not confident in your ability to install this fixture, please consult a qualified electrician.

1. **Prepare for Installation:** Turn off the main power supply at the circuit breaker or fuse box to avoid electrical shock. Ensure the power is off before proceeding.
2. **Remove Old Fixture (if applicable):** Carefully remove any existing light fixture from the wall. Disconnect all wiring and remove the old mounting bracket.
3. **Install Mounting Bracket:** Attach the new mounting bracket (provided) to the electrical junction box in the wall using the screws provided. Ensure the bracket is securely fastened and level.
4. **Make Electrical Connections:** Connect the fixture's wires to the corresponding wires from the junction box.
 - Connect the **black** (hot) wire from the fixture to the **black** (hot) wire from the junction box.
 - Connect the **white** (neutral) wire from the fixture to the **white** (neutral) wire from the junction box.
 - Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and to the mounting bracket.Secure all connections with wire nuts and wrap them with electrical tape for added safety. Carefully tuck all wires into the junction box.
5. **Mount the Fixture:** Align the fixture's base with the mounting bracket and secure it in place using the provided screws. Ensure the fixture is flush against the wall and stable.
6. **Install Glass Shades:** Carefully attach each frosted glass shade to the fixture according to the design. Typically, these slide into place or are secured with small screws or clips.
7. **Install Light Bulbs:** Screw in four E12 base incandescent bulbs (not included) into the lamp holders. Do not exceed the maximum wattage of 60 watts per bulb.
8. **Restore Power:** Once installation is complete and all components are securely in place, restore power at the circuit breaker or fuse box. Test the fixture to ensure it functions correctly.



Image 2: The Z-Lite 169-4V-BN vanity light installed above a mirror in a contemporary bathroom setting.

5. OPERATING INSTRUCTIONS

The Z-Lite 169-4V-BN vanity light is operated via a standard wall switch (not included). Once installed and wired correctly, simply toggle the wall switch to turn the light fixture ON or OFF.

6. MAINTENANCE AND CARE

- Cleaning:** To clean the fixture, ensure the power is off and the fixture is cool. Wipe with a soft, dry, or slightly damp cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or glass.

- **Bulb Replacement:** Before replacing bulbs, turn off the power to the fixture at the circuit breaker. Allow bulbs to cool completely. Carefully unscrew old bulbs and replace with new E12 base incandescent bulbs, not exceeding 60 watts per bulb.
- **Glass Shade Care:** The frosted glass shades can be removed for cleaning if necessary. Wash with mild soap and water, rinse thoroughly, and dry completely before reattaching.

7. TROUBLESHOOTING

If you experience issues with your Z-Lite 169-4V-BN vanity light, refer to the table below for common problems and solutions.

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture.	Check circuit breaker or fuse. Ensure wall switch is ON.
Light does not turn on.	Loose wire connection.	Turn off power at breaker. Check all wire connections inside the junction box and fixture. Re-secure if loose.
Light does not turn on.	Defective bulb.	Replace bulb with a new one of the correct type and wattage.
Light flickers.	Loose bulb or connection.	Ensure bulbs are screwed in tightly. Turn off power and check wire connections.
Light flickers.	Incorrect dimmer switch (if applicable).	Ensure dimmer switch is compatible with incandescent bulbs.

8. PRODUCT SPECIFICATIONS

Feature	Detail
Brand	Z-Lite
Model Number	169-4V-BN
Color	Brushed Nickel
Material	Alloy Steel (Fixture), Glass (Shades)
Style	Modern
Light Fixture Form	Vanity
Room Type	Bathroom
Product Dimensions	5" L x 30.66" W x 7" H (approximate)
Indoor/Outdoor Usage	Indoor
Power Source	Corded Electric
Installation Type	Surface Mount
Light Source Type	Incandescent

Feature	Detail
Finish Type	Brushed
Shade Material	Glass
Number of Light Sources	4
Voltage	120 Volts
Bulb Base	E12
Maximum Compatible Wattage	60 Watts per bulb
Assembly Required	Yes
Item Weight	9.92 Pounds
UPC	685659050981
Certification	UL Listed


9. WARRANTY INFORMATION

This Z-Lite product is covered by a manufacturer's warranty. For specific details regarding warranty coverage, duration, and claims process, please refer to the documentation included with your purchase or contact Z-Lite customer support directly. Keep your proof of purchase for warranty validation.

10. CUSTOMER SUPPORT




If you have any questions, require technical assistance, or need to report missing/damaged parts, please contact Z-Lite customer support. Refer to the Z-Lite official website or your purchase documentation for the most current contact information.

Related Documents - 169-4V-BN



Z-Lite 522S-BK/522M-BK Outdoor Wall Sconce Assembly and Installation Instructions

Comprehensive guide for assembling and installing the Z-Lite 522S-BK and 522M-BK outdoor wall sconce. Includes safety warnings, step-by-step instructions, and parts identification.

 <p>Page: 1 / 14</p>	<p>Z-27UJRBNU-4635 Light Fixture Installation Guide - Z-Lite</p> <p>Detailed installation instructions and safety warnings for the Z-Lite Z-27UJRBNU-4635 light fixture. Includes parts list, assembly steps, wiring guide, and cleaning recommendations.</p>
	<p>Z-Lite 651P-11R Arden 11-Light Pendant Installation and Safety Instructions</p> <p>Comprehensive installation and safety guide for the Z-Lite 651P-11R Arden 11-Light Pendant. Includes step-by-step assembly, wiring instructions, safety warnings, cleaning tips, and parts ordering information.</p>
	<p>Z-Lite 495P24/495P32 Lighting Fixture Installation and Safety Instructions</p> <p>Detailed installation and safety guide for the Z-Lite 495P24 and 495P32 lighting fixtures, covering assembly, wiring, grounding, and final setup.</p>
	<p>Z-Lite Kaden Chandelier Installation and Safety Instructions</p> <p>Comprehensive guide for installing the Z-Lite Kaden Chandelier (Model 3045-12), including safety precautions, assembly steps, wiring instructions, and cleaning recommendations.</p>
	<p>Z-Lite Laurent Outdoor Pier Mounted Fixture Installation Guide</p> <p>Comprehensive installation and operation instructions for the Z-Lite Laurent outdoor pier mounted lighting fixture, including safety warnings, assembly steps, electrical connections, and maintenance tips.</p>