



Manuals.plus /

- › Arteck /
- › Arteck Bluetooth Keyboard Instruction Manual

## Arteck HB086

# Arteck Bluetooth Keyboard Instruction Manual

Brand: **Arteck** | Model: **HB086**

## INTRODUCTION

This manual provides comprehensive instructions for the setup, operation, and maintenance of your Arteck Bluetooth Keyboard. Designed for universal compatibility, this portable wireless keyboard offers a comfortable and efficient typing experience across various operating systems.



Figure 1: Artech Bluetooth Keyboard, showcasing its compact and sleek design.

## WHAT'S IN THE BOX

Please verify that all items are present in your package:

- Artech Stainless Bluetooth Keyboard
- USB charging cable
- Welcome guide

## SETUP

### 1. Charging the Keyboard

Your Arteck keyboard features a built-in rechargeable Li-polymer battery. Before initial use, it is recommended to fully charge the keyboard.

- Locate the micro-USB charging port on the side of the keyboard.
- Connect the provided USB charging cable to the keyboard and a compatible USB power source (e.g., computer USB port, USB wall adapter).
- The charging indicator light will illuminate during charging and turn off when fully charged.
- A single charge can last for approximately 6 months based on 2 hours of non-stop use per day.



## 2. Bluetooth Pairing

The Arteck keyboard supports Bluetooth connectivity with iOS, Android, Mac OS, and Windows operating systems.

1. Turn on the keyboard using the power switch located on the back. The power indicator light will turn green.
2. Press and hold the **Fn** key, then press the **C** key (which has a Bluetooth symbol) to activate Bluetooth pairing mode. The Bluetooth indicator light will start blinking.
3. On your device (tablet, smartphone, PC), go to Bluetooth settings and enable Bluetooth.
4. Search for "Arteck Bluetooth Keyboard" or "HB086" in the list of available devices and select it to pair.
5. Once successfully paired, the Bluetooth indicator light on the keyboard will stop blinking and remain solid.



## BLUETOOTH CONNECTIVITY



*Simply press **Fn + C** for quick access to the Bluetooth pairing process.*

Figure 3: Activating Bluetooth pairing mode using Fn + C keys.

### Setup Video Guide

Your browser does not support the video tag.

Video 1: A comprehensive review and setup guide for the Arteck Slim Wireless Rechargeable Keyboard. This video demonstrates the unboxing, features, and connectivity process.

## OPERATING INSTRUCTIONS

### 1. System Compatibility

The Arteck keyboard is fully functional across major operating systems. Use the dedicated function keys to optimize performance for your specific device:

- Press **Fn + Q** for iOS (iPad, iPhone)
- Press **Fn + W** for Android (Tablets, Smartphones)
- Press **Fn + E** for Windows (PC, Laptops)



Supports 3 Systems:



Win Android ios

## THREE SYSTEM COMPATIBILITY

*Perfectly compatible with WINDOWS/ANDRIOD (above 4.0)/  
IOS system (above 6.0).*

Figure 4: Keyboard layout highlighting the system compatibility keys (Fn + Q/W/E).

### 2. Comfortable Keystrokes

The keyboard features low-profile, scissor-kick keys designed for quiet and comfortable typing. The X-structure beneath each key ensures equal pressure distribution and lower keystrokes compared to traditional clickety keyboards, enhancing typing comfort and reducing fatigue.



## COMFORTABLE KEYSTROKES

*X structure, exert equal pressure and lower keystrokes in comparison with the clickety keyboard.*

Figure 5: Detailed view of the comfortable keystrokes and X-structure design.

### 3. Media and Function Keys

The top row of keys provides quick access to common functions and media controls. These functions are system-specific and may vary slightly depending on the connected operating system.

- **Home Key:** Returns to the home screen (mobile OS).
- **Search Key:** Opens the search function.
- **Select All/Copy/Paste/Cut:** Dedicated keys for text manipulation.
- **Media Controls:** Play/Pause, Previous/Next Track, Volume Up/Down.
- **Function Keys (F1-F12):** Hold the **Fn** key and press the corresponding F-key for standard F1-F12 functionality on Windows.

## MAINTENANCE

To ensure the longevity and optimal performance of your Artek keyboard, follow these maintenance

guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the keyboard surface. For stubborn dirt, a slightly damp cloth can be used, ensuring no moisture enters the keys or ports.
- **Storage:** Store the keyboard in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** Recharge the keyboard regularly, even if not in frequent use, to maintain battery health. Avoid completely draining the battery for extended periods.
- **Durability:** The keyboard features a stainless steel material, providing a heavy-duty and durable feel.



### Brushed stainless backside

Figure 6: The brushed stainless steel backside contributes to the keyboard's durability.

## TROUBLESHOOTING

If you encounter issues with your Arteck Bluetooth Keyboard, please refer to the following common solutions:

- **Keyboard not pairing:**
  - Ensure the keyboard is fully charged.
  - Make sure the keyboard's power switch is in the "ON" position.
  - Verify that Bluetooth is enabled on your device and it is discoverable.
  - Try unpairing and re-pairing the keyboard from your device's Bluetooth settings.
  - Ensure the keyboard is within the effective Bluetooth range (up to 10 meters).

- **Keys not responding or incorrect input:**

- Check if the correct operating system mode is selected (Fn + Q/W/E).
- Ensure the keyboard is properly paired and connected.
- Recharge the keyboard if the battery is low.
- Restart your device and try connecting again.

- **Multi-device switching:**

While the keyboard is broadly compatible with multiple operating systems, it is designed to connect to one device at a time. To switch between devices, you must disconnect from the current device and then pair with the new device.

## SPECIFICATIONS

Feature	Detail
Brand	Arteck
Model Number	HB086
Connectivity Technology	Bluetooth
Operating System Compatibility	Android, iOS, Mac OS, Windows
Item Weight	10.7 ounces
Product Dimensions (LxWxH)	11.02 x 5.31 x 0.16 inches
Material	Stainless Steel
Battery Life	6 months (based on 2 hours non-stop use per day)
Power Source	Battery Powered (Rechargeable Lithium Ion)
Number of Keys	82

## WARRANTY AND SUPPORT

Arteck provides a **24-month warranty** for this product, ensuring peace of mind. Our friendly customer service team is available to assist you with any questions or concerns.

For support, please refer to the contact information provided in your welcome guide or visit the official Arteck website.