Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

HoneyGuaridan S68D

HoneyGuaridan A25 Automatic Pet Feeder (Model S68D)

Instruction Manual

Introduction

Thank you for choosing the HoneyGuaridan A25 Automatic Pet Feeder. This device is designed to provide convenient and consistent feeding for your dogs, cats, and small animals, ensuring they receive appropriate portions at scheduled times. Please read this manual thoroughly before use to ensure proper operation and maintenance.

Product Overview

The HoneyGuaridan A25 Automatic Pet Feeder features a removable food container, portion control, voice recording, and a programmable timer for up to 6 meals a day. Its design prioritizes ease of use and pet well-being.



Image: HoneyGuaridan A25 Automatic Pet Feeder, showing its sleek white and blue design with a clear food reservoir and control panel.

Setup

1. Battery Installation

The feeder requires 3 D-size batteries (not included) for operation. These batteries provide power and ensure the feeder continues to function even during power outages.

1. Turn the feeder upside down to access the battery compartment at the base.
2. Open the battery compartment cover.
3. Insert three D-size batteries, ensuring correct polarity (+/-).
4. Close the battery compartment cover securely.
5. Locate the On/Off switch near the battery compartment and slide it to the 'On' position.

2. Filling the Food Container

The feeder is designed for dry pet food. Ensure the food size does not exceed 0.39" x 0.39" (1 cm x 1 cm) to prevent

blockages.

1. Twist the lid counter-clockwise to unlock and remove it from the top of the feeder.
2. Pour dry pet food into the transparent food reservoir.
3. Replace the lid and twist it clockwise to securely lock it in place. This prevents pets from accessing the food prematurely.

Operating Instructions

The control panel allows you to program feeding times, portion sizes, and record a voice message. Refer to the video below for a visual guide on programming.

Video: Official HoneyGuaridan instruction video demonstrating the setup and programming of the automatic pet feeder, including battery installation, setting the clock, programming meal times and portions, and recording a voice message.

1. Control Panel Overview

- **Settings Activation Button:** Press to activate settings mode.
- **Recording Button:** Press and hold to record a voice message for your pet.
- **Playback Button:** Press to listen to your recorded voice message.
- **Confirmation Button:** Confirms your selections in the menu.
- **Settings Navigation Button:** Used to navigate through menu options.
- **Food Amount Selection Button:** Controls the quantity of food dispensed per meal.
- **Add Quantity/Hour Button (H/+):** Increases the hour or food quantity.
- **Decrease Quantity/Minute Button (M/-):** Decreases the minute or food quantity.

2. Setting the Master Clock

1. Press and hold the 'Clock' button (Settings Activation Button) for 2 seconds until the hour display starts blinking.
2. Use the 'H/+' button to adjust the hour.
3. Use the 'M/-' button to adjust the minutes.
4. Press the 'Confirmation' button to save the time.

3. Setting the Feeding Schedule and Amount

The feeder allows you to program multiple feeding times and corresponding portion sizes.

1. Press and hold the 'Settings Activation' button for 2 seconds to enter feeding schedule programming mode. The first feeding time will start blinking.
2. Press the 'Clock' button to select the hour for the current feeding time. Use the 'H/+' and 'M/-' buttons to adjust the hour and minutes.
3. Press the 'Food Bowl' button to select the food amount. The blinking number represents the portion size. Each increment typically means a 2-3 gram increase in food dispensed. Use the 'H/+' button to increase the portion and the 'M/-' button to decrease it.
4. Press the 'Settings Activation' button again to move to the next feeding schedule (up to 6 meals). Repeat steps 2 and 3 for each desired meal.
5. Once all schedules are set, press the 'Confirmation' button to save.

4. Voice Recording

Record a personalized message to call your pet to their meal.

1. Press and hold the 'Recording' button. Speak your message into the microphone.
2. Release the 'Recording' button when finished.
3. Press the 'Playback' button to listen to your recorded message.

5. Manual Feeding

To dispense a small amount of food immediately, outside of the scheduled times:

- Press and hold the 'Confirmation' button for 2 seconds. A small portion of food will be dispensed.

Maintenance

Cleaning

Regular cleaning ensures hygiene and proper functioning. The product care instructions specify "Hand Wash Only" for the material.

1. Ensure the feeder is turned off and unplugged (if using an adapter, though it's primarily battery-powered).
2. Remove any remaining food from the reservoir.
3. Disassemble the removable food container and food bowl.
4. Hand wash these components with mild soap and water. Rinse thoroughly.
5. Wipe the main unit with a damp cloth. Do not submerge the main unit in water.
6. Allow all parts to dry completely before reassembling and refilling with food.

Troubleshooting

- **Feeder not dispensing food:**
  - Check if the feeder is turned on.
  - Ensure batteries are correctly installed and have sufficient power.
  - Verify that the food reservoir is not empty.
  - Check for food blockages in the dispenser mechanism. Ensure food kibble size is appropriate.
- **Display not working:**
  - Check battery power. Replace batteries if necessary.
  - Ensure the On/Off switch is in the 'On' position.
- **Voice recording not playing:**
  - Ensure a message has been recorded.
  - Check volume settings if available (not explicitly mentioned but good general advice).

Specifications

Brand	HoneyGuaridan
Model Number	S68D
Product Dimensions	9.84 x 7.76 x 15.55 inches
Item Weight	4.1 Pounds
Material	Polyethylene Terephthalate, Stainless Steel
Target Species	Cat, Dog
Power Source	Battery Powered (3 D-size batteries, not included)

Operation Mode	Automatic
Capacity	6.5 liters
Special Features	Portion Control, Timer, Voice Recording
Connectivity Technology	WiFi

Warranty and Support

HoneyGuaridan provides a 12-month warranty for all its products. For technical support, troubleshooting assistance, or warranty claims, please contact HoneyGuaridan customer service through their official website or the retailer where the product was purchased. Please have your model number (S68D) and proof of purchase ready when contacting support.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question