

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Targus](#) /

› [Targus Universal USB 3.0 Dual Video 4K Docking Station User Manual](#)

Targus DOCK160USZ

Targus Universal USB 3.0 Dual Video 4K Docking Station

Model: DOCK160USZ

Brand: Targus

1. INTRODUCTION

The Targus Universal USB 3.0 Dual Video 4K Docking Station (DOCK160USZ-50) is designed to expand the connectivity of your laptop or PC, providing dual Ultra-High Definition 4K video output via DisplayPort and HDMI. This compact docking station is compatible with USB 3.0 hosts and supports multiple host platforms and brands, offering broad compatibility for various peripherals and devices. It enables dual video performance up to 4096 x 2160 at 60Hz resolution, making it ideal for enhancing your workstation setup.



Image 1.1: Front-side view of the Targus DOCK160USZ-50 docking station, showcasing its compact design.

2. PACKAGE CONTENTS

Please verify that all items are present in your package:

- Targus Universal USB 3.0 Dual Video 4K Docking Station (DOCK160USZ-50)
- Power Adapter

- 3.3-foot USB- μ B to USB-A Host Cable (detachable)

3. PRODUCT FEATURES AND PORTS

The Targus DOCK160USZ-50 offers a comprehensive set of ports to enhance your productivity:

- **Video Ports:** 2 DisplayPort (DP 1.2a) and 2 HDMI 2.0 ports for dual 4K Ultra HD video monitor support.
- **Network:** 1 Gigabit Ethernet port for reliable wired network connectivity.
- **USB Ports:**
 - 1 USB-C device port (USB 3.0 data only)
 - 4 USB 3.0 ports (including 1 fast device-charging port)
- **Audio:** 1 x 3.5mm combo Audio In/Out port for microphones, speakers, or earphones.
- **Security:** Integrated lock slot accommodates industry-standard security locks.



Image 3.1: Rear view of the docking station, detailing the DisplayPort, HDMI, Ethernet, USB 3.0, and power input ports.



Image 3.2: Front view of the docking station, highlighting the USB-C and audio combo jack.

4. SETUP GUIDE

Follow these steps to set up your Targus Universal USB 3.0 Dual Video 4K Docking Station:

1. **Connect Power:** Plug the included power adapter into the DC 18V port on the back of the docking station, then connect it to a power outlet.
2. **Connect to Host Device:** Use the provided USB- μ B to USB-A host cable to connect the docking station to an available USB 3.0 port on your laptop or PC.
3. **Install Drivers (if necessary):** For optimal performance, ensure the latest DisplayLink drivers are installed on your operating system. The docking station is compatible with Windows (10/8.1/7), Mac OS X 10.8 or later, and Android (5.1/5.0). Drivers can typically be found on the Targus support website.
4. **Connect Monitors:** Connect your external monitors to the DisplayPort or HDMI ports on the back of the docking station. You can use a combination of two DisplayPort, two HDMI, or one of each for dual display setup.
5. **Connect Peripherals:**

- Connect USB devices (keyboard, mouse, external drives) to the USB 3.0 ports.
- For wired internet, connect an Ethernet cable to the Gigabit Ethernet port.
- Connect headphones, speakers, or a microphone to the 3.5mm audio combo jack on the front.

6. Configure Display Settings: Once connected, your operating system should detect the external displays. Adjust display settings (resolution, orientation, extended/duplicate mode) through your system's display preferences.

5. OPERATING INSTRUCTIONS

The Targus docking station simplifies your workspace by providing a single connection point for all your peripherals.

5.1. Dual Display Operation

The docking station supports up to two external 4K displays simultaneously. Connect your monitors to any two of the four video output ports (2x DisplayPort, 2x HDMI). Ensure your monitors and cables support 4K resolution for optimal performance. You can configure your displays for extended desktop, mirrored display, or primary display only modes via your computer's display settings.

5.2. USB Device Connectivity

Utilize the four USB 3.0 ports for connecting various USB devices. One of these ports is a fast-charging port, suitable for quickly charging smartphones or other compatible devices. The USB-C port on the front is for data transfer only.

5.3. Audio and Network

The 3.5mm combo audio jack allows for convenient connection of headsets, speakers, or microphones. The Gigabit Ethernet port provides a stable and high-speed wired network connection, ideal for environments where Wi-Fi is unreliable or unavailable.

6. MAINTENANCE

To ensure the longevity and optimal performance of your docking station, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry, lint-free cloth to clean the exterior of the docking station. Avoid using abrasive cleaners, solvents, or strong chemicals.
- **Ventilation:** Ensure the docking station is placed in a well-ventilated area to prevent overheating. Do not block any ventilation openings.
- **Storage:** When not in use for extended periods, store the docking station in a cool, dry place away from direct sunlight and extreme temperatures.
- **Cable Management:** Keep cables organized and untangled to prevent damage to the ports or cables themselves.

7. TROUBLESHOOTING

If you encounter issues with your Targus docking station, refer to the following common troubleshooting steps:

- **No Display Output:**
 - Ensure the docking station is powered on and connected securely to your host device.
 - Verify that monitor cables are firmly connected to both the docking station and the monitors.

- Check your computer's display settings to ensure external displays are detected and configured correctly.
- Update your DisplayLink drivers to the latest version from the Targus support website.
- Test with different cables or monitors if possible.

- **USB Devices Not Working:**
 - Ensure the docking station is properly connected to your host device.
 - Try connecting the USB device to a different port on the docking station or directly to your computer to isolate the issue.
 - Check your computer's Device Manager (Windows) or System Information (macOS) for any unrecognized USB devices.

- **No Network Connection:**

- Verify the Ethernet cable is securely connected to both the docking station and your network router/switch.
- Check your computer's network settings to ensure the Ethernet adapter is enabled and configured.
- Restart your router/modem and computer.

- **Audio Issues:**

- Ensure your audio device (headphones/speakers) is correctly plugged into the 3.5mm audio jack.
- Check your computer's sound settings to ensure the docking station's audio output is selected as the default playback device.
- Adjust volume levels on both your computer and the audio device.

For more detailed troubleshooting or specific driver information, please refer to the official [Targus User Manual \(PDF\)](#).

8. SPECIFICATIONS

Feature	Detail
Model Number	DOCK160USZ
Brand	Targus
Hardware Platform	PC, Tablet
Operating System Compatibility	Windows (10/8.1/7), Mac OS X 10.8 or later, Android (5.1/5.0), Chrome, Linux
Video Output	2 x DisplayPort (DP 1.2a), 2 x HDMI 2.0 (Dual 4K Ultra HD)
USB Ports	4 x USB 3.0 (1 fast-charging), 1 x USB-C (data only)
Ethernet	1 x Gigabit Ethernet
Audio	1 x 3.5mm Combo Audio In/Out
Power Input	DC 18V (45 watts)
Item Weight	6.4 ounces (0.4 lbs)

Product Dimensions (LxWxH)	3.5 x 1.5 x 6.8 inches
Color	Black

9. WARRANTY AND SUPPORT

This Targus product comes with a standard manufacturer's warranty. For specific warranty terms, registration, and technical support, please visit the official Targus website or contact their customer service.


Additional resources:


- Official Targus Store: [Targus Amazon Store](#)
- User Manual (PDF): [Download Here](#)

Note: No official product videos were found in the provided data for embedding.

© 2023 Targus. All rights reserved.

Related Documents - DOCK160USZ

	<p>Targus USB-C Single Video 4K HDMI/VGA Docking Station with 100W Power Delivery User Guide</p> <p>User guide for the Targus USB-C Single Video 4K HDMI/VGA Docking Station. Learn about its features, system requirements, connectivity options including 4K HDMI, VGA, Gigabit Ethernet, and 100W Power Delivery. Troubleshooting tips included.</p>
	<p>Targus USB-C Single Video 4K HDMI/VGA Docking Station with 100W Power Delivery User Guide</p> <p>User guide for the Targus USB-C Single Video 4K HDMI/VGA Docking Station with 100W Power Delivery. This guide provides information on setup, system requirements, features, troubleshooting, and declarations of conformity.</p>
	<p>Targus USB Multi Display Adapter Quick Start Guide</p> <p>Get started quickly with the Targus USB Multi Display Adapter. This guide provides setup instructions, specifications, and compatibility information for expanding your display capabilities.</p>
	<p>Targus Desktop USB 2.0 7-Port Hub with Audio Pass-Through User Guide</p> <p>User guide for the Targus Desktop USB 2.0 7-Port Hub with Audio Pass-Through, detailing features, setup, troubleshooting, and warranty information.</p>

	<p>Targus Remote Control Instructions and Product Guide</p> <p>Explore instructions and details for various Targus remote controls, including laser presentation remotes, wireless presenters, and multimedia presenters. Find information on models like AMP13EU, AMP16US, and AMP01.</p>
	<p>Targus Slim Bluetooth Keyboard Case for Samsung Galaxy Tab S6 Lite - User Guide</p> <p>Official user guide for the Targus Slim Bluetooth Keyboard Case (Model AKB56) for Samsung Galaxy Tab S6 Lite. Learn how to connect, charge, use hot keys, and troubleshoot.</p>

Documents - Targus – DOCK160USZ



[pdf] Quick Start Guide Specifications Guide Diagram

DOCK160USZ 50 B UG Online 092717 quick start guide cdn targus 80 web us

DUAL VIDEO 4K p60 DOCKING STATION QUICK START GUIDE 410-3557-001B /

DOCK160USZ Contents Targus Dual Video 4K p60 Docking Station USB 3.0 Cable AC Power adapter Workstation Setup 1. Connect all peripheral devices to the docking station Features and specifications are subject to change without no...

lang:en score:48 filesize: 501.86 K page_count: 2 document date: 2017-09-27



[pdf] User Manual

Microsoft Word Document1 neiledwin talapi an Targus Universal USB 3 Dual Video 4K Docking Station DOCK160USZ 50DOCK160USZ User Manual Targus 50 B01N1PCZ0Z51v jgqwsOLm media amazon images | 51v jgqwsOL |||

Overview Create a powerful dual video workstation with the Targus Universal USB 3.0 DV4K Docking Sta ... anty Yes 092636322014 *see Website:

<http://www.targus.com/us/universal-usb-3-0-dv4kdocking-station-dock160usz ...>

lang:en score:37 filesize: 61.59 K page_count: 1 document date: 2017-09-26



[pdf] Guide Accessories

ENTERPRISE SOLUTIONS Targus 3 DOCKING STATIONS Universal Compatibility Our universal docking stations work with Mac ® and PC platforms as well Chrome OS ™ Android Linux 2018 Corporate Standard Guide 5 11 18 cdn targus web us |||

ENTERPRISE SOLUTIONS TABLE OF CONTENTS Docking Stations 3 Adapters 10

Cables Accessories 1 ... Universal Docking Station with Single 2K or Dual HD Video

DOCK177USZ 269.99 DOCK171USZ 199.99 **DOCK160USZ** 199.99 DOCK130USZ

159.99 DOCK120USZ 129.99 VersaLinkTM Universal Dual Video Travel ...

lang:en score:31 filesize: 5.26 M page_count: 32 document date: 2018-05-04

[pdf] Price List

Melvin Saldonido Targus MAP US Price List 20170919 cdn targus 80 web us

Schedule A Effective Date of Revised Policy: September 10, 2017 MAP Grid for Certain Rugged Cases5-inch iPad Pro Minimum Advertised Price* 66.49 66.49 SRP 69.99 69.99 DOCK120USZ DOCK110USZ **DOCK160USZ** DOCK130USZ DOCK410USZ DOCK411USZ DOCK177USZ DOCK171USZ 2K Universal Docking Station, USB...

lang:en score:25 filesize: 351.01 K page_count: 1 document date: 2017-09-15

[pdf] Price List

Melvin Saldonido Targus Group International Schedule A Effective Date of Revised Policy July 10 2017
SafePort Rugged Case with Integrated Stand for iPad® iPad Air 2 and Pro 9.7 inch \$66.49 MAP US Price
List 20170710 cdn targus web us |||

Schedule A Effective Date of Revised Policy: July 10, 2017 MAP Grid for Certain Rugged Cases and D ... ad Air 2 and iPad Pro 9.7-inch Minimum Advertised Price*
66.49 SRP 69.99 DOCK120USZ DOCK110USZ **DOCK160USZ** DOCK130USZ
DOCK410USZ DOCK411USZ DOCK177USZ DOCK171USZ 2K Universal Docking Station, USB...

lang:en score:23 filesize: 65.16 K page_count: 1 document date: 2017-07-06



[pdf] Catalog

CATÁLOGO LATINOAMÉRICA Targus Universal USB 3.0 DV Docking Station con Alimentación de Corriente DOCK171USZ Soporte monitor dual hasta 2048 x 1152 en 60Hz video bicolor

2018CatalogoLatam tarqus mx ||

CATALOGO LATINOAMERICA Docking Stations DEFCON Candados de Seguridad
Alimentacion Accesorios par ... tion with Single 4K or Dual HD Video 2K Universal
Docking Station with Single 2K or Dual HD Video **DOCK160USZ** DOCK130USZ
DSU400US DOCK120USZ DSU300US USB 3.0 USB 3.0 USB 3.0 VersaLink™
Uni...

lang:es score:20 filesize: 2.99 M page count: 40 document date: 2018-03-26

[pdf] Specifications

Microsoft Word Document1 neiledwin talapi an Overview Create a powerful dual video workstation with the Targus Universal USB 3.0 DV4K Docking Station Connect up to two displays for crisp clear 51v jgqwsOL images na ssl amazon | Dual Displays Supports DisplayPort and HDMI Supported in Windows Chrome Mac OS X Linux Android operating systems Specifications Color Black Gray 2x Ports 1x C Port data only 4x SuperSpeed 1 powered fast device charging Audio In Out

Overview Create a powerful dual video workstation with the Targus Universal USB 3.0 DV4K Docking Station. This compact, portable docking station is designed to support two displays simultaneously, making it ideal for professionals who need to work with multiple screens. It features a built-in power adapter and includes a USB 3.0 cable for easy connectivity. The Targus Universal USB 3.0 DV4K Docking Station is perfect for users who want to extend their desktop or laptop's functionality without the need for a separate power source or additional cables. It's a great addition to any mobile workstation or travel setup.

[pdf]

docking station comparison chart Targus targus ca 2018 04 30 — USB C™ Universal DV4K Docking Station with 60W Power 100W Thunderbolt™ 3 Comparison Chart APR2018 CAN Themes

TargusCanada Content ||

DOCKING STATION COMPARISON CHART USB TYPE-C HOST CONNECTION
NAME MODEL USB-CTM Universal DV4K Dock ... ith Single 2K or Dual HD Video
VersaLinkTM Universal Dual Video Travel Dock DOCK177USZ DOCK171USZ
DOCK160USZ DOCK130USZ DOCK120USZ DSU100BT MSRP CONNECTION
TECHNOLOGY VIDEO PORTS DISPLAYPORTTM 29...