

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Fuvision](#) /
- › [Fuvision 16GB 1080P HD Spy Pen Camera Video Recorder User Manual](#)

Fuvision PNC-2KDVR-16GB-Mini Camera

Fuvision 16GB 1080P HD Spy Pen Camera Video Recorder User Manual

Model: PNC-2KDVR-16GB-Mini Camera

INTRODUCTION

Welcome to the user manual for your Fuvision 16GB 1080P HD Spy Pen Camera Video Recorder. This manual provides detailed instructions on how to set up, operate, and maintain your device. Please read it carefully to ensure proper usage and to maximize the product's functionality.



An image showing the Fuvision 16GB 1080P HD Spy Pen Camera, highlighting its discreet design as a functional writing pen.

WELL-HIDDEN DESIGN

Nobody realize this is a spy camera from the appearance
as it works as a real ball-point pen



A person holding the Fuvision Spy Pen Camera, illustrating how its design allows it to be discreetly used as a regular pen.

PACKAGE CONTENTS

Please verify that all the following items are included in your package:

- Fuvision 16GB 1080P HD Spy Pen Camera
- USB Data/Charging Cable
- 3 x Pen Refills
- User Manual (this document)

What's included:



An image displaying all items included in the package: the Fuvision Spy Pen Camera, three ink refills, a USB data/charging cable, and a printed user manual.

PRODUCT OVERVIEW AND COMPONENTS

Familiarize yourself with the various parts of your Fuvision Spy Pen Camera:



A detailed diagram of the Fuvision Spy Pen Camera, pointing out key components such as the Reset Hole, LED Indicator, USB Plug, Function Button, Lens Cover Slider, and the Camera Lens.



Another diagram illustrating the Fuvision Spy Pen Camera's features, including the ON/OFF button, USB port, HD camera location, and the functional ball-point pen tip.

- **Function Button:** Used for powering on/off, starting/stopping recording, and switching modes.
- **Camera Lens:** The hidden lens for video and photo capture.
- **LED Indicator:** Provides status feedback (power, recording, photo mode).
- **USB Plug:** Located at the top, used for charging and data transfer.
- **Reset Hole:** For resetting the device if it becomes unresponsive.
- **Ball-Point Pen:** Fully functional writing pen.

SETUP

1. Charging the Device

Before first use, fully charge the pen camera. Connect the USB plug of the pen to a computer's USB port or a 5V DC USB wall adapter using the provided USB cable. The charging time is approximately 4 hours. The LED indicator will show charging status (specific LED behavior for charging is not detailed, assume it turns off or changes color when fully charged).

2. Initial Power On

After charging, the device is ready for use. The pen has a built-in 16GB memory, so no external memory

card installation is required.

OPERATING INSTRUCTIONS

1. Powering On and Off

- **To Power On:** Press and hold the Function Button on the top for a few seconds until the LED lights up. It will flash purple a few times, then turn off. This indicates the device has started recording. The LED is off during recording to maintain discretion.
- **To Power Off:** Press and hold the Function Button for a few seconds until the LED flashes purple a few times, then turns off completely.

2. Video Recording Mode

- **Start Recording:** When the device is powered on, it automatically begins recording video. The LED will flash purple a few times and then turn off, indicating active recording.
- **Stop Recording:** Press the Function Button once quickly. The recording will stop, and a red LED will turn on, indicating the pen is in STANDBY mode.
- **Loop Recording:** The device supports loop recording, which means it will automatically overwrite the oldest files when the memory is full.

3. Photo Mode

- **Switching to Photo Mode:** From STANDBY mode (red LED on), double-click the Function Button. The red LED will change to blue, indicating the device is now in Photo Mode.
- **Taking a Photo:** In Photo Mode (blue LED on), press the Function Button once. The purple light will blink a few times to confirm a photo has been taken.
- **Exiting Photo Mode:** Double-click the Function Button again. The device will return to STANDBY mode (red LED on).

4. Connecting to a Computer

To transfer recorded videos and photos, connect the pen camera to your computer using the provided USB cable. The device will appear as a removable disk drive. It is compatible with Windows XP/2003/Windows7/8/10 and Apple Mac OS X - 10.7 operating systems.

MAINTENANCE

1. General Care

- Avoid dropping the device or subjecting it to strong impacts.
- Keep the device away from water, moisture, and extreme temperatures.
- Store the pen in a cool, dry place when not in use.

2. Cleaning

Use a soft, dry cloth to clean the exterior of the pen. Do not use liquid cleaners or solvents, as they may damage the device.

TROUBLESHOOTING

Common Issues and Solutions:

- **Device not turning on:** Ensure the battery is fully charged. Connect to a power source and charge

for 4 hours.

- **Recording not starting:** Check if the device is powered on correctly (LED flashes purple then turns off). Ensure the battery has sufficient charge.
- **Cannot connect to computer:** Try a different USB port or a different computer. Ensure the USB cable is securely connected.
- **Device unresponsive:** Locate the Reset Hole (refer to Product Overview) and gently press it with a thin object (like a paperclip) to reset the device.

SPECIFICATIONS

Detailed technical specifications for the Fuvision 16GB 1080P HD Spy Pen Camera:



An image showcasing the clear video quality produced by the Fuvision Spy Pen Camera, indicating its 1080P Full HD resolution with still shot functionality.




Video Resolution	1080P (1920x1080) @ 30fps
Photo Resolution	JPG 4032x3024
Pixel	2.0 Mega Pixel CMOS
Internal Memory	16GB





Battery Life	Approximately 120 minutes continuous recording
Record Modes	Continuous record, Loop Recording
Video Format	AVI
USB Interface	2.0
Charging Voltage	DC-5V (500mA)
Charging Time	Approximately 4 hours
View Angle	65°
Operating System Compatibility	Windows XP/2003/Windows7/8/10, Apple Mac OS X - 10.7 and above
Dimensions	155 × 14.5 × 14.5 mm (6.1 x 0.57 x 0.57 inches)
Item Weight	100 g (0.22 lbs)
Power Source	Battery Powered (1 Lithium Ion battery included)
Recommended Uses	Motion Detection (feature mentioned in product details, but not detailed in operation)

IMPORTANT SAFETY INFORMATION

- Do not attempt to disassemble or modify the device.
- Keep out of reach of children.
- Dispose of the battery according to local regulations.
- Use only the provided USB cable for charging and data transfer.

Related Documents - PNC-2KDVR-16GB-Mini Camera

 <p>FUVISION® Webcam Quick Start Guide</p> <p>100 Pages Questions? For additional assistance contact FUVISION Tech Support Email: sales@fuvision.com</p> <p>Works with your webcam: 1. Plug the webcam to the USB port of your computer. 2. Plug the power adapter to the webcam to be installed externally on your computer. 3. Plug the webcam to the computer. 4. Plug the webcam to the computer. 5. Plug the webcam to the computer. 6. Plug the webcam to the computer. 7. Plug the webcam to the computer. 8. Plug the webcam to the computer. 9. Plug the webcam to the computer. 10. Plug the webcam to the computer.</p>	<p>FUVISION Webcam Quick Start Guide - Setup and Troubleshooting</p> <p>Comprehensive quick start guide for FUVISION webcams. Learn how to set up your webcam, find helpful reminders for different operating systems, and troubleshoot common issues like device recognition and application compatibility.</p>
 <p>FUVISION® OUTDOOR WIRELESS SOLAR CAMERA USER MANUAL MODEL: S30</p> <p></p>	<p>Fuvison S30 Outdoor Wireless Solar Camera User Manual</p> <p>User manual for the Fuvison S30 Outdoor Wireless Solar Camera, providing setup instructions, app usage, troubleshooting, and special notes.</p>

	<p>Fuvision Smart Home Security Camera User Manual</p> <p>Comprehensive user manual for the Fuvision Smart Home Security Camera, detailing package contents, product structure, installation, app setup with Tuya Smart, Wi-Fi pairing, live view, app features, settings, FAQs, and safety guidelines.</p>
	<p>Sherlock Hones Spy Pen Camera: Instructions, Tips, and Features</p> <p>A comprehensive guide to operating the Sherlock Hones Spy Pen Camera, including setup, recording, photography, viewing footage, and key features of this discreet HD spy gadget.</p>
	<p>OzSpy SPY PEN VIDEO CAMERA HD 1080P 8GB Instruction Manual</p> <p>Instruction manual for the OzSpy SPY PEN VIDEO CAMERA HD 1080P 8GB. Covers charging, setting time, operation, recording modes (photo/video), playback, cautions, and important legal notices for this hidden spy pen camera.</p>
	<p>Zone Shield EZ HD DVR User Manual</p> <p>Comprehensive user manual for the SleuthGear Zone Shield EZ HD DVR, covering setup, operation, features, specifications, troubleshooting, and warranty. Ideal for discreet surveillance applications.</p>