

[manuals.plus](#) /

› [Retevis](#) /
› [Retevis RT24 Plus PMR446 Walkie Talkie User Manual](#)

Retevis RT24 Plus

Retevis RT24 Plus PMR446 Walkie Talkie User Manual

Model: RT24 Plus (EUA9123AX2)

1. PRODUCT OVERVIEW

The Retevis RT24 Plus is a license-free PMR446 walkie talkie designed for reliable and clear communication. This manual provides essential information for setting up, operating, and maintaining your device.



Figure 1: Key components of the Retevis RT24 Plus Walkie Talkie. This diagram illustrates the antenna, channel selection knob, power/volume knob, indicator light, earpiece/mic jack, PTT button, belt clip, and battery pack.

2. PACKAGE CONTENTS

Before use, please verify that all items are present in your package:

- 4 x Retevis RT24 Plus Walkie Talkies
- 4 x Headsets
- 4 x USB Charging Cradles
- 4 x Belt Clips
- 4 x Rechargeable Batteries (1100mAh Li-Ion)
- 1 x User Manual

X2



Figure 2: An illustration of the items included in the Retevis RT24 Plus package, showing two walkie-talkies, two batteries, two charging cradles, two headsets, and two belt clips.

3. SETUP INSTRUCTIONS

3.1 Battery Installation

1. Ensure the walkie talkie is powered off.
2. Locate the battery compartment on the back of the device.
3. Align the 1100mAh Li-Ion battery with the contacts and gently press it into place until it clicks securely.
4. Slide the battery cover back on until it locks.

- Einfach zu verwenden
- Dauerhaft
- Fachmann

Retevis RT27

Figure 3: A detailed view of the battery pack, showing its design and connection points for proper installation.

3.2 Charging the Battery

The RT24 Plus walkie talkies are rechargeable and come with USB charging cradles. You can charge the walkie talkie directly or the battery separately.

1. Connect the USB charging cable to the charging cradle and a compatible USB power source (e.g., wall adapter, power bank, car charger, laptop).
2. Place the walkie talkie or the battery into the charging cradle.
3. The indicator light on the cradle will show the charging status. Charging typically takes 2-3 hours.

A full charge provides approximately 8-12 hours of continuous use or up to 74 hours in standby mode.



Figure 4: Various methods for charging the Retevis RT24 Plus, including wall charging, power bank, car charging, and laptop charging, highlighting its versatile USB compatibility.

3.3 Attaching Accessories

- **Belt Clip:** Attach the belt clip to the designated slot on the back of the walkie talkie for convenient

carrying.

- **Headset:** Plug the headset into the earpiece/mic jack on the side of the walkie talkie. Ensure it is fully inserted for proper function.



Figure 5: The included headset accessory, designed for hands-free communication with the walkie talkie.

4. OPERATING INSTRUCTIONS

4.1 Power On/Off and Volume Adjustment

1. To power on the device, rotate the Power/Volume knob clockwise until you hear a click.
2. Continue rotating the knob clockwise to increase the volume, and counter-clockwise to decrease it.
3. To power off, rotate the knob counter-clockwise until you hear a click.

4.2 Channel Selection

The RT24 Plus features 16 channels. To communicate with other walkie talkies, all devices must be set to the same channel.

1. Rotate the Channel Selection knob to choose your desired channel (1-16).
2. The walkie talkie will typically announce the selected channel number.

4.3 Transmitting and Receiving

1. To transmit (speak), press and hold the Push-To-Talk (PTT) button located on the side of the walkie talkie.
2. Speak clearly into the microphone, holding the device approximately 5-10 cm from your mouth.
3. Release the PTT button to stop transmitting and listen for a response.
4. When receiving, the indicator light may illuminate, and you will hear the incoming transmission through the speaker or headset.



Figure 6: A close-up view of the Push-To-Talk (PTT) button, essential for initiating voice transmissions.

4.4 Privacy Codes (CTCSS/DCS)

The RT24 Plus supports 50 CTCSS (Continuous Tone-Coded Squelch System) and 105 DCS (Digitally Coded Squelch) codes. These codes help filter out unwanted conversations from other users on the same

channel, ensuring more private communication. These codes are typically programmed using specialized software and a programming cable (sold separately).

5. MAINTENANCE AND CARE

5.1 General Cleaning


- Wipe the device with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Ensure the earpiece/mic jack cover is securely closed when not in use to protect against dust and moisture.

5.2 Battery Care

- Avoid fully discharging the battery frequently to prolong its lifespan.
- Store the battery in a cool, dry place when not in use for extended periods.
- Do not expose the battery to extreme temperatures.

5.3 Water Resistance

The Retevis RT24 Plus is designed to be water-repellent (IPx4 rated). This means it can withstand splashes of water from any direction. It is not designed for submersion. Ensure all port covers are sealed to maintain water resistance.



Fall resistant



Water resistant



Figure 7: Icons indicating the fall-resistant and water-resistant properties of the Retevis RT24 Plus walkie talkie, highlighting its durability.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Battery is low or not installed correctly.	Charge the battery or re-install it.
Cannot transmit or receive	Incorrect channel selected; PTT button not pressed; out of range.	Ensure all devices are on the same channel; press PTT firmly; move closer to the other device.
Poor sound quality / Static	Weak signal; interference; volume too low/high.	Move to an open area; adjust volume; check for obstructions.
Headset not working	Headset not fully plugged in; faulty headset.	Ensure headset is securely connected; try another headset if available.

7. SPECIFICATIONS

- **Brand:** Retevis
- **Model Number:** EUA9123AX2
- **Color:** Black
- **Number of Channels:** 16
- **Frequency Range:** 446.0 to 446.2 MHz (PMR446)
- **Max. Talk Range:** Up to 3 Kilometers (environment dependent)
- **Battery Type:** 1100mAh Lithium-Ion (included)
- **Voltage:** 3.7 Volts
- **Water Resistance Rating:** Water-repellent (IPx4)
- **Product Dimensions:** 6.5 x 28.8 x 20.8 cm
- **Weight:** 830 Grams (total package weight, individual unit weight not specified)
- **Special Features:** Easy operation, good build quality, clear speaker, rechargeable.



Figure 8: The rear view of the walkie talkie, displaying the model number (RT24), output power (0.5W), frequency (PMR446), voltage (3.7V), and regulatory marks (CE, RoHS).

8. WARRANTY AND SUPPORT

For warranty information, technical support, or service inquiries, please contact Retevis customer service directly. Refer to the contact details provided with your purchase documentation or visit the official Retevis website.