

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [lifeholder](#) /

› [lifeholder Mini Chandelier LH-D22-US Instruction Manual](#)

lifeholder LH-D22-US

lifeholder Mini Chandelier LH-D22-US Instruction Manual

Model: LH-D22-US | Brand: lifeholder

INTRODUCTION

Thank you for choosing the lifeholder Mini Chandelier. This elegant lighting fixture is designed to enhance the ambiance of various rooms, including bedrooms, hallways, bars, kitchens, and bathrooms. This manual provides essential information for safe installation, proper operation, and effective maintenance of your chandelier. Please read these instructions thoroughly before beginning installation or use.

Key Features:

- **Compact Size:** 10.4 inches high and 8.7 inches wide, suitable for rooms sized 5-8 square meters.
- **Comfortable Glow:** Designed for 120V 40-watt G9 bulbs (bulbs not included).
- **Elegant Design:** Features sparkling acrylic crystals that mimic glass, creating a sophisticated atmosphere.
- **Easy Installation:** Assembly required, including hanging crystal strings. All mounting hardware and a detailed manual are included.

WHAT'S IN THE BOX

Carefully unpack the contents and ensure all items are present and undamaged. If any parts are missing or damaged, please contact customer support before proceeding.

- Chandelier Base
- Crystal Strings (pre-assembled)
- Mounting Hardware Kit
- Instruction Manual

SAFETY INFORMATION

- **Electrical Safety:** Always turn off power at the circuit breaker before installation, maintenance, or bulb replacement.

- **Professional Installation:** If you are unsure about electrical wiring, consult a qualified electrician.
- **Bulb Type:** Use only G9 LED bulbs, 120V, up to 40 watts. Do not exceed the maximum wattage.
- **Handling Crystals:** Handle crystals with care to avoid breakage. Wearing gloves during assembly can prevent fingerprints.
- **Secure Mounting:** Ensure the mounting hardware is securely fastened to a structurally sound ceiling.

SETUP AND INSTALLATION

Follow these steps for proper installation of your mini chandelier.

Step 1: Prepare for Installation

1. Turn off the power at the main circuit breaker.
2. Remove any existing light fixture from the ceiling.
3. Ensure the mounting surface is clean and dry.

Step 2: Install Mounting Bracket

1. Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure it is firmly secured.
2. *Note: Some installations may require additional support depending on ceiling structure.*

Step 3: Wire the Chandelier

1. Connect the chandelier's wires to your household wiring according to local electrical codes. Typically, this involves connecting:
 - Black (Live) wire from chandelier to Black (Live) wire from ceiling.
 - White (Neutral) wire from chandelier to White (Neutral) wire from ceiling.
 - Green or bare copper (Ground) wire from chandelier to Green or bare copper (Ground) wire from ceiling.
2. Secure connections with wire nuts and wrap with electrical tape for added safety.

Step 4: Attach Chandelier Base to Ceiling

1. Carefully lift the chandelier base and align it with the mounting bracket.
2. Secure the base to the bracket using the provided screws or nuts.

Step 5: Install Bulbs

1. Insert two G9 LED bulbs (not included) into the sockets. Ensure bulbs are fully seated.

Step 6: Hang Crystal Strings

The crystal strings come pre-assembled. Attach each string to the designated hooks on the chandelier base. Refer to the diagram below for guidance on crystal placement.



Image: Close-up view of the crystal strings and attachment points on the chandelier base.



Image: Chandelier dimensions, illustrating its compact size.

OPERATING INSTRUCTIONS

Once installed, restore power at the circuit breaker. The chandelier operates via a standard wall switch (not included). Ensure the correct G9 LED bulbs are installed for optimal performance and light output.



Image: The chandelier illuminated, showcasing its light distribution.

MAINTENANCE

Cleaning:

- Always turn off power before cleaning.
- Wipe the metal parts with a soft, dry cloth.
- For crystals, use a soft, lint-free cloth dampened with a mild glass cleaner or water. Avoid abrasive cleaners.
- Do not spray cleaner directly onto the fixture.

Bulb Replacement:

- Ensure power is off and bulbs have cooled before attempting replacement.
- Gently pull out the old G9 bulb and insert a new one, ensuring it is securely seated.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power, loose wiring, faulty bulb.	Check circuit breaker. Verify wire connections. Replace bulb.
Light flickers.	Loose bulb, incompatible dimmer switch, faulty wiring.	Ensure bulb is tight. Use a dimmer compatible with LED G9 bulbs. Consult an electrician for wiring issues.
Crystals appear dull.	Dust or residue buildup.	Clean crystals as per maintenance instructions.

SPECIFICATIONS

Feature	Detail
Brand	lifeholder
Model Name	Mini Chandelier
Model Number	LH-D22-US
Product Dimensions	8.7"L x 8.7"W x 10.4"H
Material	Acrylic, Glass, Plastic
Style	Modern
Light Fixture Form	Flush Mount Ceiling Light
Room Type	Bedroom, Hallway, Bar, Kitchen, Bathroom
Power Source	Corded Electric
Voltage	120 Volts
Number of Light Sources	2
Bulb Base	G9
Max Wattage	40 Watts (per bulb)
Light Output Maximum	400 Lumens
Item Weight	2.2 pounds (1 Kilogram)
Assembly Required	Yes
UPC	611517813801

WARRANTY AND SUPPORT

lifeholder provides a limited warranty for this product. Please retain your proof of purchase for any warranty claims.

Worry-Free Guarantee:

If you encounter any quality issues or are not satisfied with your purchase, please do not hesitate to contact lifeholder customer service. Contact information can typically be found on the product packaging or the retailer's website.

Optional Protection Plans:

Extended protection plans may be available for purchase separately through your retailer. These plans typically offer coverage beyond the standard manufacturer's warranty.

- 3-Year Protection Plan
- 4-Year Protection Plan
- Complete Protect (monthly billing option)

Note: Availability and terms of protection plans are subject to change and are managed by the retailer or third-party providers.