

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [VTech](#) /

› [VTech DS6151-11 DECT 6.0 2-Line Expandable Cordless Phone System User Manual](#)

### VTech DS6151-11

# VTech DS6151-11 DECT 6.0 2-Line Expandable Cordless Phone System User Manual

Model: DS6151-11, DS6101-11

## INTRODUCTION

This manual provides comprehensive instructions for the setup, operation, and maintenance of your VTech DS6151-11 DECT 6.0 2-Line Expandable Cordless Phone System, including the DS6101-11 accessory handsets. This system is designed for efficient communication with its two-line operation and integrated digital answering system.



Image: The complete VTech DS6151-11 system, showing the main base unit with one cordless handset and three additional accessory handsets in their charging cradles.

## SETUP GUIDE

Follow these steps to set up your VTech cordless phone system.

## 1. Package Contents

Ensure all components are present:

- Main base unit (DS6151-11)
- Cordless handset(s) (DS6151-11 and DS6101-11 accessory handsets)
- Handset charger(s)
- Power adapter(s)
- Telephone line cord(s)
- Rechargeable battery pack(s)

## 2. Battery Installation

Install the battery pack into each cordless handset:

1. Locate the battery compartment cover on the back of the handset.
2. Slide the cover off.
3. Connect the battery pack connector securely into the jack inside the compartment.
4. Place the battery pack into the compartment.
5. Slide the battery compartment cover back into place until it clicks.



Image: A close-up view of the VTech cordless handset's backlit LCD display, showing call information and menu options.

## 3. Base Unit and Charger Connection

Connect the base unit and accessory chargers:

1. Plug one end of the telephone line cord into the TEL LINE jack on the back of the base unit.
2. Plug the other end of the telephone line cord into a telephone wall jack.
3. Plug the small end of the power adapter into the POWER jack on the back of the base unit.
4. Plug the large end of the power adapter into an electrical outlet not controlled by a wall switch.
5. For each accessory charger, plug the power adapter into the charger and then into an electrical outlet.



Image: The VTech DS6151-11 base unit with a cordless handset docked in its charging cradle, illustrating the main components.

#### 4. Initial Charging

Place each handset in its respective base or charger. Allow at least 16 hours for the batteries to fully charge before initial use. The CHARGE light on the handset will illuminate during charging.

### OPERATING INSTRUCTIONS

This section covers the basic operation of your VTech cordless phone system.

#### Making and Receiving Calls

- **To make a call:** Press **TALK/FLASH** or **SPEAKER**, then dial the number.
- **To answer a call:** Press any dialing key (0-9, \*, #), **TALK/FLASH**, or **SPEAKER**.
- **To end a call:** Press **OFF/CLEAR** or place the handset in the charger.

## Two-Line Operation

The system supports two separate telephone lines. Use the **LINE 1** and **LINE 2** buttons on the base unit or handset to select the desired line for calls.



Image: A detailed view of the VTech DS6151-11 base unit's keypad, navigation buttons, and digital answering system controls, including the LINE 1 and LINE 2 buttons.

## Digital Answering System

The integrated digital answering system has a dedicated mailbox for each line, offering approximately 13 minutes of recording time.

- **To play messages:** Press **PLAY/STOP** on the base unit or access the Answering System menu on the handset.
- **To record an outgoing announcement:** Follow the instructions in the handset menu under Answering System settings.

## Phonebook and Caller ID

- **Phonebook:** Store up to 50 names and numbers. Access via the **DIRECTORY** button on the handset.
- **Caller ID:** The system stores up to 50 caller ID entries. Press **CID** on the handset to review.

## Expandability

The system is expandable up to 12 handsets (DS6101-11 accessory handsets). Refer to the accessory handset manual for pairing instructions.



Image: A single VTech DS6101-11 accessory cordless handset shown in its compact charging cradle.

## MAINTENANCE

Proper care ensures the longevity of your phone system.

### Cleaning

Wipe the phone and base unit with a soft, damp cloth. Do not use cleaning sprays or liquid cleaners as they may damage the finish or electrical components.

### Battery Care

- Only use the supplied rechargeable battery packs or equivalent replacements.
- Do not dispose of batteries in a fire. They may explode.
- Do not open or mutilate the batteries. Released electrolyte is corrosive and may cause burns or injury to the eyes or skin.

- Charge batteries for at least 16 hours before first use.
- If the phone will not be used for an extended period, remove the batteries to prevent leakage.

## TROUBLESHOOTING

This section addresses common issues you might encounter.

Problem	Solution
No dial tone.	<p>Ensure the telephone line cord is securely plugged into the base unit and the wall jack.</p> <p>Check if the power adapter is properly connected to the base unit and a working electrical outlet.</p> <p>Make sure the handset battery is charged.</p>
Handset displays "Out of range" or "No power at base".	<p>Move closer to the base unit.</p> <p>Ensure the base unit's power adapter is connected and the outlet is active.</p> <p>Re-register the handset to the base if necessary (refer to the full user manual for registration steps).</p>
Cannot hear messages on answering system.	<p>Adjust the volume on the base unit or handset.</p> <p>Ensure the answering system is turned on for the respective line.</p>
Caller ID does not display.	<p>Ensure you have subscribed to Caller ID service from your telephone service provider.</p> <p>The caller may have blocked their number.</p>

## SPECIFICATIONS

Key technical specifications for the VTech DS6151-11 system:

- **Technology:** DECT 6.0 (1.9GHz)
- **Lines Supported:** 2-Line Operation
- **Expandability:** Up to 12 Handsets (DS6101-11 accessory handsets)
- **Answering System:** Digital, 13 minutes recording time, dedicated mailbox per line
- **Phonebook Capacity:** 50 names and numbers
- **Caller ID Memory:** 50 entries
- **Display:** Large Backlit LCD Display
- **Keypad:** Backlit Keypad
- **Speakerphone:** Dual Speakerphone (Base & Handset)
- **Batteries:** 7 AAA batteries required.
- **Material:** Plastic

- **Color:** Black
- **Dimensions (Package):** 15.12 x 12.01 x 5.31 inches
- **Weight (Item):** 4.69 pounds
- **Compatible Devices:** PSTN, VoIP services

## WARRANTY AND SUPPORT

For detailed warranty information and technical support, please refer to the official VTech website or the warranty card included with your product. VTech provides customer service to assist with any product-related inquiries or issues.

**Online Support:** Visit [www.vtechphones.com](http://www.vtechphones.com) for FAQs, product registration, and support resources.

© 2024 VTech Communications, Inc. All rights reserved.

## Related Documents - DS6151-11

	<p><a href="#">VTech DS6101 Accessory Handset User Manual</a></p> <p>This user manual provides instructions for setting up, registering, and using the VTech DS6101 accessory handset with the DS6151/DS6151-11 telephone base. It covers battery installation and charging, belt clip and headset usage, handset registration and replacement, and important safety information.</p>
	<p><a href="#">VTech DS6151 Cordless Phone Quick Start Guide</a></p> <p>A quick start guide for the VTech DS6151 series cordless phone, covering installation, battery charging, making/answering calls, and using the answering system.</p>
	<p><a href="#">VTech DS6151 Quick Start Guide</a></p> <p>Concise guide to installing, setting up, and using the VTech DS6151 cordless phone system, including battery installation, making/answering calls, and managing the answering system.</p>
	<p><a href="#">VTech SIP Cordless Phones User Guide</a></p> <p>Comprehensive user guide for VTech's SIP Next Gen Series cordless phones, including models NG-S3111, NGC-C3416HC, NGC-C5106, and C5016. Covers safety instructions, parts lists, telephone layout, installation, setup, operation, troubleshooting, and warranty information.</p>

 <p>For more support information US CA</p> <p><b>vttech</b> User's manual</p>	<p><a href="#">VTech CS6314 / VG101 DECT 6.0 Cordless Telephone User Manual</a></p> <p>Comprehensive user manual for the VTech CS6314 and VG101 series DECT 6.0 cordless telephones. Covers setup, operation, features, safety instructions, troubleshooting, and technical specifications.</p>
 <p>For more support information US CA</p> <p><b>vttech</b> User's manual</p>	<p><a href="#">VTech CS6114 DECT 6.0 Cordless Telephone User Manual</a></p> <p>Comprehensive user manual for the VTech CS6114 DECT 6.0 cordless telephone, covering setup, features, operations, troubleshooting, and safety instructions.</p>

## Documents - VTech – DS6151-11



### [\[pdf\] User Manual Instructions Accessories Label](#)

User's manual User manual Accessory handset for use with VTech model DS6151 11 vtechphones Model DS6101 BCvtech ds6101 manualcdnimg webstaurantstore documents vtech |||

User's manual Accessory handset for use with VTech model DS6151 **DS6151-11** w w w. v t e c h p h o n e s . c o m Model: DS6101/ DS6101-11 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 9 of this manual. This manu...

lang:en score:38 filesize: 2.64 M page\_count: 25 document date: 2017-06-13



### [VTech DS6101 Accessory Handset User Manual](#)

This user manual provides instructions for setting up, registering, and using the VTech DS6101 accessory handset with the DS6151/DS6151-11 telephone base. It covers battery installation and charging, belt clip and headset usage, handset registration and replacement, and important safety information.

lang:en score:35 filesize: 2.65 M page\_count: 25 document date: 2017-06-13



### [pdf] User Manual Installation Guide Instructions Troubleshooting Guide Label

User's manual This has all the feature operations and troubleshooting necessary to install and Please review this thoroughly ensure proper installation operation of DS6151 CIB V8 CEC 20170616 cdn media vtechphones products DS on purchasing your new VTech product Before using telephone please read Important safety instructions page 80 653CC1C7 12DA 4087 8850 4A0AAB25ADC1 files bbystatic 1wFCLchBNQinYNf2PpoV2A Jun 16 2017 — operate Manual vtech factoryoutletstore content User's manual www.vtechphones.com Models: DS6151/DS6151-11/ DS6151-2 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 80 of this manual. This manual has all the feature operations and trouble...

lang:en score:33 filesize: 16.46 M page\_count: 99 document date: 2017-06-16




### [pdf] User Manual Instructions Accessories Label

User's manual vtech ds6101 webstaurantstore documents |||

User's manual Accessory handset for use with VTech model DS6101/DS6101-11 www.vtechphones.com Model: DS6101/ DS6101-11 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 9 of this manual. This manu...

lang:en score:32 filesize: 2.64 M page\_count: 25 document date: 2017-06-13




### [pdf] Quick Start Guide Installation Guide Guide Label

User Guide Amazon VTech DS6151 2 Line Cordless Phone System for Home or Small Business with Digital Answering Mailbox on Each line Black Silver Telephones Office Products A15A4UgipfL m media amazon images |||

Quick start guide DS6151/DS6151-11/DS6151-2 Install the telephone base Follow the figures below to install the telephone base as shown below: Figure One: Installation with 2-line jack Electrical outlet not controlled by a wall switch L1 L2 telephone wall jack Telephone base power adapter If you...

lang:en score:31 filesize: 1.16 M page\_count: 2 document date: 2017-10-13




### [pdf] Quick Start Guide Installation Guide Guide Label

Quick start guide Battery installation and charging Install the To turn on or off with telephone base Press ON OFF LINE 1 2 to corresponding answering system The 23 giu 2020 — DS6151 QSG V4 20200623 cdn web vtp media products DS

Quick start guide DS6151/DS6151-11/DS6151-2 Install the telephone base Follow the figures below to install the telephone base as shown below: Figure One: Installation with 2-line jack Electrical outlet not controlled by a wall switch L1 L2 telephone wall jack Telephone base power adapter If you...

lang:en score:27 filesize: 1.16 M page\_count: 2 document date: 2020-06-23




### [\[pdf\] User Manual Installation Guide Instructions Troubleshooting Guide Label](#)

User s manual 328vteds6151 webrestaurantstore documents |||

User s manual w w w.v t e c h p h o n e s . c o m Models: DS6151/**DS6151-11**/

DS6151-2 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 80 of this manual. This manual has all the feature operations and trouble...

lang:en **score:25** filesize: 16.45 M page\_count: 99 document date: 2017-06-16



### [\[pdf\] VTech DS6151 Quick Start Guide](#)

Concise guide to installing, setting up, and using the VTech DS6151 cordless phone system, including battery installation, making/answering calls, and managing the answering system.

lang:en **score:24** filesize: 1.16 M page\_count: 2 document date: 2017-08-04




### [\[pdf\] User Manual Installation Guide Instructions Troubleshooting Guide Specifications Label](#)

User s manual Webstaurant Store0 TONE \* ! @ space When entering a name in the directory VTech is registered trademark of Holdings Limited Specifications 328vteds6151 manualwebstaurantstore documents 328vteds6151 srltid AfmBOoq R1RrzsauJ5mYEb uUEFmWZA E2gG 5xR6wJs dahRdz06OW Specifications This has all feature operations and troubleshooting necessary to install operate your new telephone Please review this328vteds6151 manual328vteds6151 dahRdz06OWcdnimg webstaurantstore AfmBOoqzW8 CJGmVGy7M3zVJtEwfxyD39DRjvV3Wh8hk7UBttxWFZ2q4webstaurantstore AfmBOooID7F 8VzZzFMmtCNBDx 0WQEXbSlqIT8PD8klniewCGk7cFoO AfmBOorhT6njbCz18X1ZQhvz krkPLuV jft m5 7qXXzSleXEpxLwwebstaurantstore |||

User s manual w w w.v t e c h p h o n e s . c o m Models: DS6151/**DS6151-11**/

DS6151-2 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 80 of this manual. This manual has all the feature operations and trouble...

lang:en **score:21** filesize: 16.45 M page\_count: 99 document date: 2017-06-16



### [\[pdf\] VTech DS6151 Cordless Phone Quick Start Guide](#)

A quick start guide for the VTech DS6151 series cordless phone, covering installation, battery charging, making/answering calls, and using the answering system.

lang:en **score:16** filesize: 1.16 M page\_count: 2 document date: 2017-08-04



User's manual  
www.vtechphones.com



Models:  
DS6151/DS6151-11/  
DS6151-2



DECT 6.0

[\[pdf\]](#) User Manual Installation Guide Instructions Troubleshooting Guide Label

User's manual media amazonE1UuCD5sAQS amazon images | E1UuCD5sAQS |||

User's manual w w w.v t e c h p h o n e s . c o m Models: DS6151/**DS6151-11/**

DS6151-2 BC Congratulations on purchasing your new VTech product. Before using this telephone, please read Important safety instructions on page 80 of this manual. This manual has all the feature operations and trouble...

lang:en score:13 filesize: 16.46 M page\_count: 99 document date: 2017-06-16