Arcchio Nora 9966006

Arcchio LED Nora Floor Lamp with Motion Sensor Instruction Manual

Model: Nora 9966006

1. Introduction

Thank you for purchasing the Arcchio LED Nora Floor Lamp. This energy-efficient LED lamp is designed for various indoor environments, including offices and living spaces, and features an integrated motion sensor for automatic operation. This manual provides essential information for the safe and efficient use of your new lamp, covering installation, operation, maintenance, and troubleshooting.

2. Safety Instructions

Please read these safety instructions carefully before installation and use. Keep this manual for future reference.

- Ensure the power supply is disconnected before installation, cleaning, or maintenance.
- This product is designed for indoor use only (IP20 rating). Do not expose to moisture or extreme temperatures.
- The light source (LEDs) is integrated and not user-replaceable. Do not attempt to open or modify the lamp.
- Ensure the lamp is placed on a stable, level surface to prevent tipping.
- Do not cover the lamp with any materials, as this may cause overheating.
- Keep away from children and pets.
- If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.

3. Package Contents

Verify that all components are present and undamaged upon unpacking.

- Arcchio LED Nora Floor Lamp (main unit with integrated LED light source)
- Power Cable with Plug
- Instruction Manual (this document)

4. Product Overview

The Arcchio LED Nora is a modern floor lamp constructed from aluminum, featuring an integrated LED light panel and a motion sensor. Its design is suitable for various contemporary interiors.



Figure 4.1: The Arcchio LED Nora floor lamp positioned in an office environment, showcasing its full height and light output.

- **Lamp Head:** Contains the integrated LED light source and the motion sensor.
- **Lamp Stand:** The main vertical support column, housing the manual switch.
- **Base:** Provides stability for the lamp.
- **Motion Sensor:** Detects movement to automatically switch the light on or off.
- **Manual Switch:** Located on the lamp stand for manual control.

5. Setup and Installation

Follow these steps to set up your Arcchio LED Nora floor lamp.

1. **Unpack:** Carefully remove all components from the packaging. Retain packaging for future transport or storage.
2. **Assembly (if required):** The lamp typically comes pre-assembled or requires minimal assembly of the stand to the base. Ensure all connections are secure.
3. **Placement:**
    - Place the lamp on a firm, level surface to ensure stability.
    - Position the lamp in an area where the motion sensor has an unobstructed view of the desired detection zone. Avoid placing it near heat sources or in direct sunlight, which might interfere with sensor operation.
4. **Connect Power:** Insert the power plug into a standard 230V electrical outlet.



Figure 5.1: The power cable and plug for connecting the lamp to a mains power supply.

6. Operating Instructions

The Arcchio LED Nora lamp offers both manual and automatic operation modes.

6.1 Manual Operation

The lamp is equipped with a manual switch located on the lamp stand.

- To turn the lamp **ON**, press the switch.
- To turn the lamp **OFF**, press the switch again.



Figure 6.1: The manual push-button switch located on the lamp's vertical stand.

6.2 Motion Sensor Operation

The integrated motion sensor automatically detects movement within its range and activates the light, providing convenient and energy-efficient illumination.

- When movement is detected within the sensor's field of view, the lamp will automatically turn on.
- After a period of no detected movement, the lamp will automatically turn off to conserve energy. The exact duration before turning off may vary and is typically pre-set.
- Ensure the motion sensor is not obstructed for optimal performance.



Figure 6.2: Detail of the lamp head, highlighting the integrated motion sensor.

7. Maintenance and Care

Proper care will ensure the longevity and optimal performance of your lamp.

- **Cleaning:** Disconnect the lamp from the power supply before cleaning. Use a soft, dry, or slightly damp cloth to wipe the surfaces. Do not use abrasive cleaners, solvents, or harsh chemicals, as these can damage the finish.
- **Light Source:** The LED light source is integrated and designed for a long lifespan. It is not user-replaceable. If the light source fails, contact qualified personnel or the manufacturer for assistance.
- **General Inspection:** Periodically check the power cord for any signs of damage. If damage is found, discontinue use and contact a qualified electrician or the manufacturer.

8. Troubleshooting

If you encounter issues with your lamp, refer to the following common problems and solutions.

Problem	Possible Cause	Solution
Lamp does not turn on.	• No power supply. • Manual switch is off. • Motion sensor not detecting movement (in automatic mode).	• Check if the power plug is securely inserted into a working outlet. • Press the manual switch to turn the lamp on. • Ensure the motion sensor is unobstructed and you are within its detection range.
Motion sensor not working correctly.	• Sensor obstructed. • Interference from heat sources or direct light. • Sensor dirty.	• Clear any obstructions from the sensor's field of view. • Relocate the lamp away from interfering sources. • Gently clean the sensor lens with a soft, dry cloth.
Light flickers or dims unexpectedly.	• Unstable power supply. • Internal component issue.	• Try plugging the lamp into a different electrical outlet. • If the problem persists, discontinue use and contact the manufacturer or a qualified electrician.

If these solutions do not resolve the issue, please contact Arcchio customer support or your retailer for further assistance. Do not attempt to repair the lamp yourself.

9. Specifications

Brand	Arcchio
Model Number	9966006
Product Dimensions (L x W x H)	60 x 30 x 195 cm
Weight	15.7 kg
Material	Aluminum (Metal)
Color	Aluminum, Opal
Light Source Type	Integrated LED
Total Wattage	50 W
Luminous Flux	6200 Lumen
Operating Voltage	230 V
IP Code (Protection Class)	IP20 (Indoor use only)
Protection Class	I
Energy Label EU	A+

Special Features	Motion Sensor, Energy-efficient

10. Warranty and Support

For warranty information, please refer to the terms and conditions provided at the time of purchase or contact your retailer. Arcchio stands for high quality and customer satisfaction.
If you require technical support or have questions not covered in this manual, please contact Arcchio customer service or the point of purchase. Please have your model number (Nora 9966006) and purchase details ready.

© 2023 Arcchio. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question