



Manuals.plus /

› Ganeed /

› Ganeed K9 Crystal Chandelier (Model GLM-DD-3G) Instruction Manual

## Ganeed GLM-DD-3G

# Ganeed K9 Crystal Chandelier (Model GLM-DD-3G) Instruction Manual

Golden, 3-Light Pendant Fixture

## 1. SAFETY INFORMATION

---

Please read these instructions carefully before installation and use. Retain this manual for future reference.

- Always turn off the main power supply at the circuit breaker before beginning installation, maintenance, or bulb replacement.
- Consult a qualified electrician if you are unsure about the installation process.
- Use only E12 base bulbs, with a maximum wattage of 25 Watts per bulb. Exceeding the maximum wattage may cause overheating and damage to the fixture.
- Ensure all connections are secure and properly insulated.
- Do not hang the fixture on a ceiling that cannot support its weight.
- This product is designed for indoor use only.

## 2. PRODUCT COMPONENTS

---

Verify that all components are present and undamaged before proceeding with assembly.

- Chandelier Frame with Lamp Holders
- K9 Crystal Elements
- Ceiling Canopy
- Adjustable Steel Sling/Chain
- Mounting Hardware (screws, wire nuts, mounting plate)
- Instruction Manual



Image: Overview of the Ganeed K9 Crystal Chandelier components before assembly.

### 3. INSTALLATION AND SETUP

#### 3.1 Assembly of the Chandelier Body

1. Carefully unpack all parts and lay them out on a clean, soft surface to prevent scratches.
2. Attach the crystal branches to the main body of the chandelier. Ensure each branch is securely fastened.
3. Connect the internal wiring from each lamp holder to the main chandelier wiring. Match white (or blue) wires from lamp holders to the main white (or blue) wire, and black (or brown) wires from lamp holders to the main black (or brown) wire. Use wire nuts to secure connections.
4. Attach the decorative crystal elements to the branches as shown in the product images.

# k9 clear crystal chandelier



Image: Detailed view of the K9 crystal elements attached to the chandelier frame.

## 3.2 Mounting to the Ceiling

1. Turn off power at the circuit breaker.
2. Install the mounting plate to the ceiling junction box using the provided screws. Ensure it is firmly secured.
3. Adjust the length of the steel sling/chain to your desired height.
4. Connect the chandelier's main wires to your household electrical wires. Connect the white (or blue) wire to the neutral wire (N), the black (or brown) wire to the live wire (L), and the ground wire to the ground wire. Use wire nuts for secure connections.
5. Carefully lift the chandelier and attach it to the mounting plate, ensuring all wires are tucked safely within the canopy. Secure the canopy with the provided screws or nuts.

Video: Detailed installation guide for the 3-Light Pendant Chandelier, demonstrating wiring and assembly steps.

Video: Comprehensive assembly and wiring instructions for the K9 Crystal Pendant Light with 3-Lights.

## 4. OPERATING INSTRUCTIONS

Once installed, the chandelier is ready for use.

- Install three E12 base bulbs (Max 25W each, not included) into the lamp holders. Compatible bulb types include Incandescent, LED, CFL, and Halogen.
- Turn on the main power supply at the circuit breaker.
- Operate the chandelier using your wall switch.
- For dimming functionality, ensure you use dimmable E12 bulbs and a compatible dimmer switch (not included).

## Different Color Temperatures Gives You Different Ambiences



Image: The chandelier illuminated with different color temperatures, demonstrating its versatility.

## 5. MAINTENANCE

Regular maintenance ensures the longevity and appearance of your chandelier.

- **Cleaning:** Turn off power before cleaning. Use a soft, dry cloth to wipe the metal frame. For crystals, a slightly damp cloth with mild glass cleaner can be used, then dry immediately. Avoid abrasive cleaners or harsh chemicals.
- **Bulb Replacement:** Ensure power is off and bulbs have cooled. Unscrew old bulbs and replace with new E12 bulbs (Max 25W).
- **Crystal Care:** Handle crystals gently. If any crystals become loose or detached, reattach them carefully using the provided spare wires or similar small hooks.

## 6. TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Light does not turn on	No power, loose wiring, faulty bulb	Check circuit breaker. Verify all wire connections. Replace bulb.
Lights flicker	Loose bulb, incompatible dimmer, unstable power supply	Tighten bulbs. Ensure dimmer is compatible with bulbs. Consult electrician for power issues.
Crystals fall off	Improper attachment, vibration	Reattach crystals securely. Use spare wires if needed.

## 7. SPECIFICATIONS

---

- **Model Name:** GLM-DD-3G
- **Dimensions:** 13 inches (Diameter) x 13.4 inches (Length)
- **Steel Sling Length:** 39 inches (Adjustable)
- **Ceiling Cap Diameter:** 5.5 inches
- **Bulb Type:** E12 x 3 (US standard, bulbs not included)
- **Max Wattage:** 25 Watts per bulb
- **Material:** K9 Crystal + Iron
- **Voltage:** 110 Volts
- **Installation Type:** Flush Mount
- **UPC:** 793029885184



Image: Diagram showing the dimensions of the Ganeed K9 Crystal Chandelier.

## 8. WARRANTY AND SUPPORT

Ganeed provides excellent customer service for your product.

- **Return/Replacement:** You may replace or return your chandelier if dissatisfied within 30 days of purchase.

- **Customer Service:** Our customer service team is available 24/7 to assist you with any questions or concerns. Please do not hesitate to contact us for support, including inquiries about replacement parts.