SHIDU SHIDU S613

SHIDU S613 Wireless Voice Amplifier User Manual

Model: SHIDU S613

Introduction

The SHIDU S613 is an 18W portable wireless voice amplifier designed to provide clear and powerful sound for various applications such as teaching, fitness instruction, yoga, and tour guiding. This device features a wireless headset microphone, Bluetooth connectivity, and support for TF card and U disk playback, making it a versatile audio solution.



Image: The SHIDU S613 wireless voice amplifier, a compact black unit with a speaker grille and a wireless headset microphone connected.

Package Contents

Please check the box for the following items:

- 1 x Voice Amplifier
- 1 x UHF Wireless Microphone
- 1 x Waistband
- 1 x Audio Cable
- 1 x USB Cable
- 1 x DC 9V Charger (for voice amplifier)
- 1 x 5V Wall Charger (for microphone)
- 1 x User Manual



Image: All components included in the SHIDU S613 package: the voice amplifier, wireless headset microphone, waistband, various cables, chargers, and the user manual.

Product Overview

Familiarize yourself with the main components and their functions.



Image: Front and side views of the SHIDU S613 amplifier, illustrating its compact dimensions (98mm x 88mm x 43mm) and showing the DC 9V, AUX, and MIC input ports on the side.



Image: Top view of the SHIDU S613 amplifier, highlighting the USB port, TF card slot, and the ON/OFF switch with integrated roller volume control. This image also shows a USB flash drive and a TF card, indicating compatibility.

Key Features:

- **Power Output:** 18W for clear and loud sound.
- **Connectivity:** Bluetooth, TF card, U disk, and Aux audio input.
- **Wireless Microphone:** UHF wireless headset for hands-free operation.
- **Rechargeable Battery:** Built-in 2200mAh battery for extended use.
- **Compact Design:** Portable and lightweight for easy transport.

Setup

Charging the Device:

Before first use, ensure both the voice amplifier and the wireless microphone are fully charged.

1. **Voice Amplifier:** Connect the DC 9V charger to the amplifier's DC 9V port. Charging time is approximately 3-5 hours.
2. **Wireless Microphone:** Connect the 5V wall charger to the microphone's charging port. Charging time is approximately 2-3 hours.



Image: An illustration showing the SHIDU S613 amplifier next to a battery icon with a clock, indicating its 18W power and 2200mAh battery capacity, and highlighting its long working hours after charging.

Initial Connection:

1. Turn on the voice amplifier using the ON/OFF switch.
2. Turn on the wireless microphone. The microphone should automatically pair with the amplifier.
3. Adjust the volume using the roller control on the amplifier.

Operating Instructions

Voice Amplification Mode:

1. Ensure the wireless microphone is charged and paired.
2. Wear the headset microphone comfortably.
3. Speak into the microphone. Adjust the volume on the amplifier to your desired level.
4. The amplifier provides clear sound coverage up to 10,000 sq.ft.



Image: The SHIDU S613 amplifier with sound waves emanating from its speaker, illustrating its excellent sound quality, loud and clear output, and low distortion even at high volume.

Music Playback Modes:

The amplifier supports various audio input methods:

1. **Bluetooth:**
    a. Turn on the amplifier and activate Bluetooth mode (if applicable, usually automatic or via a mode button).
    b. Enable Bluetooth on your device (smartphone, tablet, etc.) and search for "SHIDU S613" or similar.
    c. Pair and connect. You can now play audio from your device through the amplifier.
2. **TF Card / U Disk:**
    a. Insert a TF card or U disk (USB flash drive) with MP3 music files into the corresponding slot on the amplifier.

b. The amplifier should automatically detect and begin playing music. Use the controls on the amplifier to skip tracks or adjust volume.

3. **AUX Audio Input:**
   a. Connect one end of the audio cable to the AUX port on the amplifier.
   b. Connect the other end to the audio output (headphone jack) of your computer, laptop, iPad, or phone.
   c. The amplifier will function as an external speaker.



Image: A collage of images demonstrating various scenarios where the SHIDU S613 voice amplifier can be used, including meetings, teaching, retail environments (the mall), tourist guiding, and yoga training, highlighting its versatility.

Maintenance

- **Cleaning:** Use a soft, dry cloth to clean the surface of the amplifier and microphone. Do not use liquid cleaners or aerosols.
- **Storage:** Store the device in a cool, dry place away from direct sunlight and extreme temperatures when not in use for extended periods.

- **Battery Care:** To prolong battery life, avoid fully discharging the battery frequently. Charge the device regularly, even if not in constant use.

Troubleshooting

If you encounter issues, please refer to the following common solutions:

Problem	Possible Cause / Solution
No sound from amplifier.	Ensure the amplifier is turned on and charged. Check the volume level; increase it using the roller control. If using the microphone, ensure it is charged and properly paired. If using AUX/Bluetooth/TF/U disk, ensure the source is playing and connected correctly.
Microphone not connecting or cutting out.	Ensure the microphone is fully charged. Re-pair the microphone with the amplifier if necessary (refer to setup instructions). Avoid placing the microphone too far from the amplifier or having obstructions between them.
Distorted sound.	Reduce the volume level. Ensure the microphone is not too close to the amplifier, which can cause feedback. Check audio source quality if playing music.
Device not charging.	Ensure the correct charger (DC 9V for amplifier, 5V for mic) is used. Check if the charging cable is securely connected to both the device and the power outlet. Verify the power outlet is functional.

Important Tips:

- Do not frequently insert or plug the connector to avoid looseness of the socket or poor connection.
- Distinguish between the MIC and AUX plugs to ensure correct connection.
- Before using, turn down the volume and then adjust it according to your needs to prevent sudden loud sounds.
- Original accessories are suggested if replacements are needed.

Specifications

Feature	Detail
Power Output	18W
Battery Capacity (Amplifier)	2200mAh
Frequency Response	80Hz-18KHz

Feature	Detail
Charging Voltage (Amplifier)	DC9V, 1200mA
Charging Voltage (Microphone)	DC5V, 500mA
Working Time (Wired MIC mode)	6-8 hours
Working Time (Musical mode)	6-8 hours
Working Time (Wireless Microphone)	4 hours (dependent on volume)
Charging Time (Amplifier)	3-5 hours
Charging Time (Microphone)	2-3 hours
Sound Coverage	10,000 sq.ft
Work Temperature	-10℃ to 45℃
Product Dimensions	98mm x 88mm x 43mm (3.86 x 3.46 x 1.69 inches)
Unit Weight	183g / 0.4lb
Connectivity Technology	Bluetooth, Aux, USB
Mounting Type	Tabletop

Warranty and Support

SHIDU offers an easy return and full refund policy on your purchase within 30 days from the date of purchase. Additionally, a 1-year warranty is provided from the date of purchase.
Should you require any assistance, please do not hesitate to contact SHIDU customer support. Refer to the contact information provided in the included user manual or on the official SHIDU website.

© 2024 SHIDU. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for

conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question