

Micca RB42

Micca RB42 Reference 2-Way Passive Bookshelf Speakers User Manual

BRAND: MICCA

Model: RB42

Introduction

The Micca RB42 bookshelf speaker is designed for high-fidelity music reproduction in a compact form factor. These passive speakers deliver robust bass output and a smooth sound signature, suitable for various musical genres and applications such as desktop audio, home theater, or surround sound systems.

Key features include a stout 4-inch woofer with a long-throw design, a 0.75-inch silk dome tweeter, and a 10-element crossover network. The speakers are housed in a dark wood pattern enclosure with clean modern curves.



Image: Micca RB42 Bookshelf Speakers with grilles removed, showcasing the woofer and tweeter.

Package Contents

The Micca RB42 package includes:

- 1 pair of Micca RB42 Bookshelf Speakers

Please ensure all components are present and in good condition upon unboxing.

Setup

The Micca RB42 speakers are passive and require an external amplifier or receiver for operation. Ensure your amplifier can provide 15-100 watts per channel at 4-8 ohms impedance.

Speaker Placement

- For optimal stereo imaging, place the speakers equidistant from your listening position and spaced apart to form an equilateral triangle.
- Position speakers at ear level when seated. If this is not possible, angle them slightly upwards or downwards.
- Maintain some distance from walls to allow the rear port to function effectively and prevent excessive bass buildup. Experiment with placement to find the best sound for your room.
- These speakers are suitable for shelf mount or tabletop mount applications.

Connecting to an Amplifier

1. Turn off and unplug your amplifier or receiver before making any connections.
2. Use high-quality speaker wire (not included) to connect the speakers to your amplifier.
3. Connect the positive (+) terminal (red) on the speaker to the positive (+) terminal on the amplifier.

4. Connect the negative (-) terminal (black) on the speaker to the negative (-) terminal on the amplifier.
5. Ensure all connections are secure and there are no stray wire strands that could cause a short circuit.





Image: Rear panel of the Micca RB42 speaker, illustrating the speaker wire binding posts and the bass reflex port.

Operating Instructions

Once connected to a suitable amplifier, operating the Micca RB42 speakers is straightforward. The speakers reproduce audio signals received from your amplifier.

- **Power Handling:** The speakers are rated for 15-100 watts of power. Avoid exceeding 100 watts to prevent damage.
- **Impedance:** The nominal impedance is 4-8 ohms. Ensure your amplifier is compatible with this impedance range.
- **Volume Control:** Adjust the volume using your amplifier or source device. Start with low volume and gradually increase to a comfortable listening level.
- **Break-in Period:** Like many speakers, the RB42s may benefit from a break-in period of several hours of normal use to achieve their optimal sound performance.



Image: Micca RB42 speakers positioned in a home environment, demonstrating typical usage.

Maintenance

Proper care will ensure the longevity and performance of your Micca RB42 speakers.

- **Cleaning:** Use a soft, dry cloth to wipe the speaker cabinets. Avoid abrasive cleaners or solvents.
- **Grilles:** The speakers feature magnetic grilles. These can be removed for cleaning or for a different aesthetic. Handle them gently to avoid damage.

- **Environment:** Avoid placing speakers in direct sunlight, near heat sources, or in areas with high humidity.
- **Connections:** Periodically check speaker wire connections to ensure they remain tight and free of corrosion.

Troubleshooting

If you encounter issues with your Micca RB42 speakers, refer to the following common troubleshooting steps:

- **No Sound:**
 - Ensure your amplifier is powered on and the correct input source is selected.
 - Verify all speaker wire connections are secure at both the speaker and amplifier ends, and that polarity (+ to + and - to -) is correct.
 - Check the volume level on your amplifier and source device.
 - Test with another audio source or another pair of speakers (if available) to isolate the problem to the speakers or the amplifier/source.
- **Distorted Sound:**
 - Reduce the volume level. Distortion often occurs when the amplifier is overdriven or the speakers are receiving too much power.
 - Check speaker wire connections for any loose strands that might be touching each other or the speaker terminals.
 - Ensure your amplifier's impedance setting (if adjustable) matches the speakers' impedance.
 - Inspect speaker cones and tweeters for any visible damage.
- **Uneven Sound (one speaker louder/softer):**
 - Check the balance settings on your amplifier.
 - Verify connections for both speakers are identical and secure.
 - Swap the speakers (left to right, right to left) to determine if the issue follows the speaker or remains with the channel.

If these steps do not resolve the issue, consult your amplifier's user manual or contact customer support.

Specifications

Feature	Specification
Brand	Micca
Model Number	RB42
Speaker Type	Bookshelf, Passive
Speaker Maximum Output Power	100 watts
Impedance	8 ohm (Nominal, compatible with 4-8 ohm amplifiers)

Frequency Response	20 KHz (Upper limit, actual range depends on amplifier and room acoustics)
Audio Output Mode	Stereo
Mounting Type	Shelf Mount, Tabletop Mount
Enclosure Material	Wood
Woofer Diameter	4 inches
Tweeter Diameter	0.75 inches
Item Dimensions (D x W x H)	7.9"D x 4.9"W x 8.7"H
Item Weight	6000 g (per pair)
Color	Dark Walnut
Connectivity Protocol	Wired




Image: Detailed view of the advanced 10-element crossover network inside the Micca RB42 speaker.

Warranty Information

The Micca RB42 speakers come with a Limited Warranty. For specific details regarding the warranty period, coverage, and terms, please refer to the official Micca website or the warranty card included with your product. Keep your proof of purchase for warranty claims.

Customer Support

For further assistance, technical support, or inquiries regarding your Micca RB42 speakers, please visit the official Micca website. The website typically provides FAQs, support resources, and contact information for customer service.

Official Micca Website: www.micca.com