

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Hudson Valley Lighting](#) /
- › [Hudson Valley Lighting MDS201-PN Transitional Four-Light Semi-Flush Mount Instruction Manual](#)

Hudson Valley Lighting MDS201-PN

Hudson Valley Lighting MDS201-PN Transitional Four-Light Semi-Flush Mount Instruction Manual

Model: **MDS201-PN** | Brand: **Hudson Valley Lighting**

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Hudson Valley Lighting MDS201-PN Transitional Four-Light Semi-Flush Mount fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference. This fixture is designed for indoor use only.



Figure 1: Hudson Valley Lighting MDS201-PN Semi-Flush Mount fixture.

2. SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation, servicing, or replacing bulbs. Failure to do so may result in serious injury or death.
- **CAUTION:** Risk of fire. Use only bulbs of the specified wattage and type. Do not exceed the maximum wattage of 60 watts per bulb.
- Consult a qualified electrician if you are unsure about wiring procedures or have any electrical questions.
- Ensure all electrical connections are secure and properly insulated.
- This fixture is intended for indoor use only in dry locations.
- Do not install this fixture on a sloped ceiling.

3. PACKAGE CONTENTS

Please inspect the package contents to ensure all parts are present and undamaged. If any parts are missing or damaged, do not attempt to install the fixture. Contact customer support for assistance.

- Light Fixture Assembly (1)
- Mounting Hardware Kit (1)
- Instruction Manual (1)

4. INSTALLATION INSTRUCTIONS

It is recommended that installation be performed by a qualified electrician. Always ensure power is disconnected before beginning installation.

1. **Turn Off Power:** Locate the circuit breaker or fuse box that supplies power to the fixture location and turn off the power.
2. **Prepare Mounting:** Carefully unpack the fixture and its components. Attach the mounting bracket (included in hardware kit) to the junction box in the ceiling using the provided screws. Ensure the bracket is securely fastened.
3. **Make Electrical Connections:**
 - Connect the bare copper or green ground wire from the fixture to the ground wire from the junction box (usually bare copper or green) using a wire nut.
 - Connect the white wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
 - Connect the black wire from the fixture to the black (hot) wire from the junction box using a wire nut.
 - Ensure all connections are tight and secure. Wrap electrical tape around wire nuts for added security.
4. **Secure Fixture:** Carefully lift the fixture and align the mounting holes on the fixture canopy with the screws on the mounting bracket. Secure the fixture to the mounting bracket using the decorative nuts or screws provided.
5. **Install Bulbs:** Insert four (4) E12 base incandescent bulbs (not included) into the sockets. Do not exceed 60 watts per bulb.
6. **Install Glass Components:** Carefully attach the clear glass rods or shade components to the fixture according to the specific design. Handle glass with care to prevent breakage.
7. **Restore Power:** Once installation is complete and all components are securely in place, restore power at the circuit breaker.

5. OPERATING INSTRUCTIONS

This Hudson Valley Lighting fixture is designed for simple operation. Once properly installed and powered, the fixture is controlled by a standard wall switch (not included) connected to the electrical circuit. Flip the wall switch to the 'ON' position to illuminate the fixture and to the 'OFF' position to turn it off.

6. MAINTENANCE

- **Cleaning:** To clean the fixture, ensure power is turned off. Use a soft, dry cloth to wipe down the metal finish and glass components. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or glass.
- **Bulb Replacement:** Before replacing bulbs, turn off power at the circuit breaker and allow bulbs to cool completely. Unscrew old bulbs and replace with new E12 base incandescent bulbs, not exceeding 60 watts per bulb.

7. TROUBLESHOOTING

If your fixture is not functioning correctly, refer to the following troubleshooting guide:

- **Fixture Does Not Illuminate:**

- Ensure the power supply is turned on at the circuit breaker.
- Verify that the wall switch is in the 'ON' position.
- Check that all bulbs are correctly installed and are not burnt out. Replace any faulty bulbs.
- Confirm all electrical connections are secure as per installation instructions.

- **Flickering Lights:**

- Ensure bulbs are fully screwed into their sockets.
- Check for loose wire connections.
- Verify that the bulbs are compatible with the fixture and dimmer switch (if applicable).

If the issue persists after performing these checks, consult a qualified electrician.

8. SPECIFICATIONS

Brand	Hudson Valley Lighting
Model Number	MDS201-PN
Dimensions	19"L x 19"W x 12.75"H
Material	Metal, Crystal (Shade)
Finish	Chrome Finish, Polished Nickel
Light Source Type	Incandescent
Number of Lights	4
Bulb Base	E12
Max Wattage per Bulb	60 Watts
Voltage	120 Volts
Installation Type	Semi Flush Mount
Indoor/Outdoor Usage	Indoor
Item Weight	7 Pounds
Certification	UL Listed

9. WARRANTY AND SUPPORT

This Hudson Valley Lighting fixture is covered by a **1-year limited manufacturer's warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical assistance, or to report missing/damaged parts, please contact Hudson Valley Lighting customer service. Please have your model number (MDS201-PN) and proof of purchase available when contacting support.

For more information, you may visit the official Hudson Valley Lighting website:

www.hudsonvalleylighting.com