

[Manuals.plus](#) /

› [CHANNELLOCK](#) /

› CHANNELLOCK Rapid Fire Quick Load Power Screwdriver User Manual Model 33653

## CHANNELLOCK 33653

# CHANNELLOCK Rapid Fire Quick Load Power Screwdriver

**Model:** 33653

**Brand:** CHANNELLOCK

## 1. INTRODUCTION

The CHANNELLOCK Rapid Fire Quick Load Power Screwdriver is designed for efficient and convenient fastening tasks. This tool features an innovative quick-loading mechanism and interchangeable bit cartridges, allowing for fast and easy bit selection and replacement. It is powered by a Lithium-Ion battery, providing cordless operation for various applications.



Image 1: The CHANNELLOCK Rapid Fire Quick Load Power Screwdriver, showcasing its compact design and integrated bit cartridge.

## 2. SAFETY INFORMATION

Please read and understand all safety warnings and instructions before operating this power screwdriver. Failure to follow these instructions may result in electric shock, fire, and/or serious injury.

- **Work Area Safety:** Keep your work area clean and well-lit. Cluttered or dark areas invite accidents. Do not operate power tools in explosive atmospheres, such as in the presence of flammable liquids, gases, or dust.
- **Electrical Safety:** Do not expose power tools to rain or wet conditions. Water entering a power tool will increase the risk of electric shock.
- **Personal Safety:** Always wear eye protection. Use appropriate safety equipment such as dust masks, non-skid safety shoes, hard hats, or hearing protection when necessary. Dress properly; avoid loose clothing or jewelry. Keep hair, clothing, and gloves away from moving parts.
- **Tool Use and Care:** Do not force the power tool. Use the correct power tool for your application. Disconnect the plug from the power source and/or the battery pack from the power tool before making any adjustments, changing accessories, or storing power tools.
- **Battery Pack Use and Care:** Recharge only with the charger specified by the manufacturer. Do not use battery packs or tools that are damaged or modified.

### 3. PACKAGE CONTENTS

---

Verify that all items listed below are present in your package:

- CHANNELLOCK Rapid Fire Quick Load Power Screwdriver (Drill Driver)
- Battery Charger
- Interchangeable Bit Cartridges (pre-loadable)
- Assorted Driver Bits:
  - Phillips: PH0, PH1, PH2
  - Slotted: SL3, SL5, SL6
  - Pozi: PZ0, PZ1, PZ2
  - Square: S1, S2
  - Torx: T10, T15, T20
  - Hex: H3, H4, H6



Image 2: Product packaging illustrating the screwdriver, charger, and various bit cartridges included.

## 4. SETUP

### 4.1 Charging the Battery

1. Connect the charger to a standard electrical outlet.
2. Plug the charger into the charging port on the screwdriver.
3. Allow the battery to charge fully before first use. The charging indicator light (if present) will typically change color or turn off when charging is complete.
4. A fully charged Lithium-Ion battery can hold its charge for up to one year when stored properly.

### 4.2 Loading Bit Cartridges

The screwdriver uses interchangeable cartridges for quick bit changes.

1. Select an empty bit cartridge.
2. Insert the desired driver bits into the slots within the cartridge. Ensure bits are securely seated.
3. To insert a loaded cartridge into the screwdriver, align the cartridge with the opening at the front of the tool and push it firmly until it clicks into place.



*Image 3: The screwdriver with a bit cartridge visible, demonstrating the quick-load design.*

## 5. OPERATING INSTRUCTIONS

### 5.1 Selecting a Bit

1. Ensure a loaded bit cartridge is inserted into the screwdriver.
2. Rotate the cartridge to select the desired bit. The selected bit will extend from the front of the tool.

### 5.2 Forward/Reverse Operation

- Locate the forward/reverse switch, typically above the trigger.
- Push the switch to the left for forward (driving screws) rotation.
- Push the switch to the right for reverse (removing screws) rotation.
- Center the switch to lock the trigger and prevent accidental operation.

### 5.3 Driving/Removing Screws

1. Select the appropriate bit and rotation direction.
2. Position the bit onto the screw head.

3. Press the trigger to activate the screwdriver. Apply steady, even pressure to the tool.
4. Release the trigger when the screw is fully driven or removed.

## 5.4 On-Board LED Light

The screwdriver is equipped with an on-board LED light to illuminate the work area, especially useful in low-light conditions. This light activates automatically when the trigger is pressed.

## 6. MAINTENANCE

---

### 6.1 Cleaning

- Always disconnect the tool from any charging source before cleaning.
- Wipe the tool's exterior with a clean, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Keep ventilation openings clear of dust and debris to ensure proper motor cooling.

### 6.2 Battery Care and Storage

- Store the screwdriver and battery in a cool, dry place away from direct sunlight and extreme temperatures.
- For long-term storage, it is recommended to charge the battery to approximately 50% capacity.
- Avoid completely draining the battery frequently, as this can reduce its lifespan.

### 6.3 Bit Care

- Inspect driver bits regularly for wear or damage. Replace worn bits to prevent stripping screw heads.
- Keep bits clean and free of debris.

## 7. TROUBLESHOOTING

---

- **Tool does not turn on:** Ensure the battery is charged. Check that the forward/reverse switch is not in the center (locked) position.
- **Battery not charging:** Verify the charger is properly connected to both the outlet and the tool. Check the outlet for power. Ensure the charger is not damaged.
- **Bits slipping from screw head:** Ensure you are using the correct bit type and size for the screw. Apply firm, steady pressure to the tool. Replace worn bits.
- **Reduced power/performance:** The battery may be low. Recharge the battery fully.

## 8. SPECIFICATIONS

---

<b>Model Number</b>	33653
<b>Brand</b>	CHANNELLOCK
<b>Manufacturer</b>	Channel Lock
<b>Power Source</b>	Battery Powered
<b>Battery Type</b>	Lithium Ion
<b>Material</b>	Metal

<b>Color</b>	Black
<b>Included Components</b>	Charger, Drill Driver
<b>Package Dimensions</b>	32.28 x 25.2 x 5.79 cm
<b>Item Weight</b>	839 g
<b>UPC</b>	035794336530

## 9. WARRANTY INFORMATION

---

This CHANNELLOCK Rapid Fire Quick Load Power Screwdriver is covered by a **Limited One Year Warranty** from the date of purchase. This warranty covers defects in material and workmanship under normal use. It does not cover damage resulting from misuse, abuse, accident, alteration, or unauthorized repair. Please retain your proof of purchase for warranty claims.

## 10. CUSTOMER SUPPORT

---

For technical assistance, warranty claims, or general inquiries, please contact CHANNELLOCK Customer Support:

**Consumer Hotline:** 1-800-248-6657

Please have your model number (33653) and proof of purchase available when contacting support.