

## Hokcus TM04

# Hokcus TM04 Countdown Timer Switch User Manual

Model: TM04

---

## 1. INTRODUCTION

The Hokcus TM04 Countdown Timer Switch is designed to provide automated control over your electrical appliances, helping to save energy and enhance home security. This plug-in device allows you to set specific countdown durations after which power to the connected appliance will be automatically cut off. It features multiple timing options for convenience and ease of use.

## 2. SAFETY INFORMATION

- Read all instructions carefully before using the device.
- This device is intended for **indoor use only**. Do not expose to rain or moisture.
- Do not immerse the device in water or any other liquid.
- Ensure the total load of connected appliances does not exceed the maximum rating specified in the specifications section. Overloading can cause damage or fire.
- Keep out of reach of children.
- Do not disassemble or attempt to repair the device. Contact qualified personnel for service.
- Always ensure the timer switch is securely plugged into a wall outlet.

## 3. PRODUCT OVERVIEW

The Hokcus TM04 Countdown Timer Switch features a simple interface for easy operation.



Figure 1: Front view of the Hokcus TM04 Countdown Timer Switch with controls and outlet.

#### Components:

- **SET Button:** The central button used to select the desired countdown duration.
- **Indicator Lights (1H, 2H, 4H, 6H, 8H, 10H):** Red LEDs that illuminate to show the currently selected countdown time.
- **Power Outlet:** The socket where you plug in your appliance.
- **Power Plug:** The prongs that connect the timer switch to a wall outlet.

#### 4. SETUP

Setting up your Hokcus TM04 Countdown Timer Switch is a simple two-step process.

1. **Plug in the Timer Switch:** Insert the timer switch's plug into a standard wall electrical outlet.
2. **Connect Your Appliance:** Plug the electrical cord of the appliance you wish to control into the power outlet on the front of the timer switch.



Figure 2: Side view showing the plug of the timer switch.

## 5. OPERATING INSTRUCTIONS

To operate the countdown timer function:

1. **Select Countdown Time:** Press the central **SET** button repeatedly to cycle through the available countdown durations: 1 hour (1H), 2 hours (2H), 4 hours (4H), 6 hours (6H), 8 hours (8H), and 10 hours (10H).
2. **Confirm Selection:** As you press the button, the corresponding red LED indicator light above the

selected time will illuminate. Once the desired time is lit, release the button. The timer will begin counting down automatically.

3. **Power Off:** After the selected countdown duration expires, the power to the connected appliance will be automatically cut off.
4. **Cancel Timer:** To turn off the timer function before it expires, press the **SET** button repeatedly until all indicator lights are off. This will restore continuous power to the connected appliance.

**Anti-theft Random Function:** The timer can also be used to improve home security by giving the appearance that someone is at home. By setting a countdown, lights or other appliances can turn off automatically, simulating occupancy even when you are away.

## 6. MAINTENANCE

The Hokcus TM04 Countdown Timer Switch requires minimal maintenance.

- **Cleaning:** Disconnect the timer switch from the wall outlet before cleaning. Wipe the exterior with a soft, dry cloth. Do not use liquid cleaners, abrasive cleaners, or solvents.
- **Storage:** When not in use for extended periods, store the device in a cool, dry place away from direct sunlight and moisture.

## 7. TROUBLESHOOTING

### Common Issues and Solutions:

- **Appliance not turning on:**
  - Ensure the timer switch is securely plugged into a live wall outlet.
  - Verify that the connected appliance is properly plugged into the timer switch and is switched on.
  - Check if any indicator light on the timer switch is illuminated. If not, press the SET button to select a countdown time or to ensure it's not in an 'off' state.
  - Confirm the appliance itself is functional by plugging it directly into a wall outlet.
- **Appliance not turning off after countdown:**
  - Ensure a countdown time was correctly selected and the corresponding indicator light was illuminated.
  - Verify that the appliance's power consumption does not exceed the maximum load rating of the timer switch.
- **Indicator lights not working:**
  - Ensure the timer switch is receiving power from the wall outlet.
  - If the device is completely unresponsive, discontinue use and contact support.

## 8. SPECIFICATIONS

Technical specifications for the Hokcus TM04 Countdown Timer Switch.



Figure 3: Back view with technical specifications label.

Parameter	Value
Model	TM04
Plug Type (as per product title)	US Plug
US Plug Rating	240V 50Hz 15A 1800W
EU Plug Rating (for reference)	240V 50Hz 16A 3680W
UK Plug Rating (for reference)	240V 50Hz 13A 2900W
FR Plug Rating (for reference)	240V 50Hz 16A 3680W

Brazil Plug Rating (for reference)	240V 50Hz 16A 3680W
Installation Type	Plug-in type
Operating Temperature	-10 to 40 °C (14 to 104 °F)
Standby Power	Less than 1.5W
Timing Parameters	1, 2, 4, 6, 8, 10 hours
Product Weight	0.12 kg (0.26 lbs)
Dimensions (L x W x H)	8.50 x 6.50 x 11.50 cm (3.35 x 2.56 x 4.53 inches)
Manufacturer	Hokcus
ASIN	B07MN99Z6S
UPC	746272126238

## 9. WARRANTY AND SUPPORT

For warranty information, technical assistance, or customer support regarding your Hokcus TM04 Countdown Timer Switch, please refer to the documentation provided at the time of purchase or contact your retailer. You may also visit the official Hokcus website for further support resources.