

Manuals.plus /

› Beetel /

› Beetel M25 Corded Landline Phone User Manual

## Beetel M25

# Beetel M25 Ultra Compact Corded Landline Phone

User Instruction Manual

## INTRODUCTION

Thank you for choosing the Beetel M25 Ultra Compact Corded Landline Phone. This manual provides detailed instructions for setting up, operating, and maintaining your new phone. Please read this manual thoroughly before use to ensure proper functionality and longevity of your device.



Image: Beetel M25 Corded Landline Phone, showcasing its compact design, keypad, and LCD display.

## PACKAGE CONTENTS

Before proceeding with the setup, please verify that all items are present in the package:

- Beetel M25 Landline Phone Unit
- Handset Cord
- Line Cord
- User Manual (this document)
- 1 AAA Battery (included for display functions)

## SETUP

### 1. Connecting the Phone

1. Connect one end of the coiled handset cord to the handset and the other end to the port labeled **HANDSET** on the phone base.
2. Connect one end of the line cord to the port labeled **LINE** on the phone base and the other end to your telephone wall jack.
3. Insert the provided AAA battery into the battery compartment, typically located on the underside of the phone, ensuring correct polarity. This battery powers the LCD display and caller ID features.

### 2. Mounting Options

The Beetel M25 phone offers versatile placement options, allowing for both desk and wall mounting.

- **Desk Mounted:** Place the phone on a flat, stable surface. Ensure the cords are not tangled and allow for easy access.
- **Wall Mounted:** The phone is designed with keyhole slots on the back for wall mounting. Use appropriate screws (not included) to secure the phone to a wall. Ensure the mounting surface is sturdy.



Image: Beetel M25 phone securely mounted on a wall, demonstrating its space-saving design.

## OPERATING INSTRUCTIONS

---

### Basic Operations

- **Making a Call:** Lift the handset, wait for a dial tone, and then dial the desired number.
- **Answering a Call:** When the phone rings, lift the handset to answer.
- **Ending a Call:** Place the handset back on the cradle.
- **Redial:** Press the **RDP/P** button to redial the last dialed number. The phone supports 31 digits redial memory.
- **Mute Function:** During a call, press the **MUTE** button to temporarily silence your microphone. Press it again to unmute.

### Display and Caller ID

The Beetel M25 features a 12-digit LCD screen for clear display of incoming caller IDs and other information.



Image: Detailed view of the 12-digit LCD display, showing its clarity and numeric capabilities.

- **Caller ID:** The phone supports both FSK (Frequency Shift Keying) and DTMF (Dual Tone Multi-Frequency) caller ID systems, allowing you to see who is calling before you answer.
- **Display Contrast:** Adjust the display contrast in 3 steps for optimal visibility under different lighting conditions. Refer to the phone's settings menu (if available, typically accessed via a SET/FLASH button) for this adjustment.



Image: Illustrates the phone's compatibility with DTMF and FSK caller ID systems.

### Ringer and Notifications

- **Ringer Volume Control:** Use the dedicated switch or buttons (usually on the side or bottom of the phone) to adjust the ringer volume to your preferred level.
- **LED Indication:** The phone is equipped with an "IN USE" LED indicator that illuminates when the phone is in use or when there is an incoming call, providing a visual alert.



Image: Demonstrates the ringer volume control feature of the Beetel M25 phone.



Image: Close-up of the "IN USE" LED indicator, which provides visual notification of calls.

### Additional Features



Image: Overview of the Beetel M25's key features, including mounting options, certifications, and memory functions.

- **Date and Time Display:** The LCD screen displays the current date and time.
- **Programmable Flash:** The flash function allows for call waiting or transferring calls in compatible PABX systems.
- **TEC Certified:** The phone is certified by TEC (Telecommunication Engineering Centre), ensuring compliance with Indian telecom standards.

## MAINTENANCE

To ensure the longevity and optimal performance of your Beitel M25 phone, follow these maintenance guidelines:

- **Cleaning:** Use a soft, damp cloth to clean the phone's surface. Avoid using abrasive cleaners, solvents, or strong chemicals, as they may damage the finish.
- **Environment:** Keep the phone away from direct sunlight, excessive heat sources, and moisture. Do not expose it to extreme temperatures.
- **Cords:** Periodically check the handset and line cords for any signs of wear or damage. Replace them if necessary.
- **Battery:** If the display becomes dim or unresponsive, replace the AAA battery. Dispose of old batteries responsibly.

## TROUBLESHOOTING

If you encounter issues with your Beitel M25 phone, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
No dial tone	Line cord is disconnected or faulty.	Ensure the line cord is securely connected to both the phone and the wall jack. Try a different line cord if available.
No display or dim display	Battery is low or incorrectly inserted.	Replace the AAA battery, ensuring correct polarity. Check display contrast settings.
Cannot hear caller / Caller cannot hear me	Handset cord is loose or faulty; Mute function is active.	Ensure the handset cord is securely connected. Press the MUTE button to deactivate mute. Try a different handset cord.
Caller ID not working	Service not subscribed; Incorrect line type; Battery issue.	Contact your telephone service provider to confirm Caller ID subscription. Ensure battery is functional.
Phone not ringing	Ringer volume is set to minimum or off.	Adjust the ringer volume control to a higher setting.

## SPECIFICATIONS

Feature	Detail
Model Number	M25
Display Type	12-Digit LCD with 3-step contrast adjustment
Caller ID Compatibility	FSK/DTMF
Redial Memory	31 Digits
Mounting Options	Desk / Wall Mounted
Power Source	Line Powered (with 1 AAA battery for display)
Dimensions (LxWxH)	21.3 x 6.3 x 6.5 cm
Weight	354 g
Color	Black
Material	Plastic
Manufacturer	Beetel Teletech Limited
Country of Origin	India

## WARRANTY AND SUPPORT

Beetel products are manufactured to high-quality standards. For warranty information and technical support, please refer to the warranty card included with your product or visit the official Beetel website.

For further assistance, you may contact Beetel customer service. Please have your product model number (M25) and purchase details ready when contacting support.

