

[manuals.plus](#) /

› [TREATLIFE](#) /

› [TREATLIFE Smart Wi-Fi Light Switch Instruction Manual \(Model SS01S-2V\)](#)

## TREATLIFE SS01S-2V

# TREATLIFE Smart Wi-Fi Light Switch Instruction Manual

Model: SS01S-2V

Brand: TREATLIFE

## 1. INTRODUCTION

This manual provides detailed instructions for the installation, setup, and operation of your TREATLIFE Smart Wi-Fi Light Switch. This device allows you to control your lighting remotely via a smartphone app, voice commands through Amazon Alexa or Google Assistant, and set automated schedules for enhanced convenience and energy efficiency.

## 2. IMPORTANT SAFETY INFORMATION

### WARNING: RISK OF ELECTRIC SHOCK.

- Installation must be performed by a qualified electrician or a person with electrical knowledge.
- Disconnect power at the circuit breaker before installing or servicing the switch.
- A neutral wire is required for this device to function. If your electrical box does not have a neutral wire, this switch is not compatible.
- This switch is for single-pole applications only and is not compatible with 3-way or multi-way switch setups.
- Do not use with dimmable lights or as a dimmer switch. This is an ON-OFF switch.
- Ensure the maximum power rating of 1250W and output current of 10A are not exceeded.

# ✖ It doesn't work if:



Your house was built or remodeled **before mid-80's**. (Probably **No Neutral Wire**. Check the description below to confirm)




Use as a **dimmer switch**



Use as a **3-way switch** or **multi-way switch**.



**3-Way Switch**



**Multi-Way Switch**

**Figure 2.1: Incompatible Switch Setups.** This image illustrates scenarios where the TREATLIFE Smart Wi-Fi Light Switch cannot be used, such as in older homes lacking a neutral wire, with dimmable lights, or in 3-way/multi-way switch configurations.

## 3. PACKAGE CONTENTS

- TREATLIFE Smart Wi-Fi Light Switch (2-Pack)
- Screwless Snap-On Wall Plate
- Wire Nuts
- Mounting Screws
- User Manual



Figure 3.1: TREATLIFE Smart Wi-Fi Light Switch (2-Pack). This image displays the two smart light switches and their retail packaging, indicating a 2-pack.

## 4. PRODUCT FEATURES

- **Easy and Safe Installation:** Requires a neutral wire. Step-by-step instructions are provided. Standard size with a screwless snap-on wall plate. No hub required. Operates on 2.4G Wi-Fi only (not 5G). Max Power: 1250W. Output Current: 10A. FCC Certified.
- **Voice Control:** Compatible with Amazon Alexa and Google Assistant for hands-free operation.
- **Remote Control:** Manage lights from anywhere using the Smart Life app on your smartphone. Features include creating schedules, monitoring real-time light status, device sharing, and group control.
- **Automated Schedules:** Set timers or countdowns to automatically turn lights on and off based on routines or to simulate occupancy for security.

# Smart Light Switch

Bring long-lasting and energy efficient lighting experiences for every space



No Hub Required



Standard Size



Easy Installation



Overload Protection



**Figure 4.1: Smart Light Switch Features.** This image highlights key features of the smart light switch, including no hub requirement, standard size, ease of installation, and built-in overload protection.

## 5. INSTALLATION GUIDE


### 5.1 Pre-installation Check

Before beginning installation, ensure your electrical box meets the following requirements:

- **Neutral Wire:** A neutral wire (typically white) is essential. It may be bundled at the back of your electrical box.
- **Single-Pole Setup:** This switch is designed for single-pole configurations where one switch controls one light.
- **2.4GHz Wi-Fi:** The switch requires a 2.4GHz Wi-Fi network for connectivity.

# What Does the Neutral Wire Look Like?

Neutral wires are typically white and may be found bundled inside the switch box.



**Figure 5.1: Identifying the Neutral Wire.** This diagram shows a typical electrical box with a neutral wire (white) bundled, which is required for the smart switch installation.

## 5.2 Wiring Instructions

Follow these steps carefully. If you are unsure about any part of the process, consult a qualified electrician.

- 1. Turn Off Power:** Locate your circuit breaker and turn off the power to the switch you are replacing. Verify power is off using a voltage tester.
- 2. Identify Wires:** Carefully remove your existing switch. Identify the following wires:
  - **Line Wire:** (Live/Hot) Carries power from the circuit breaker.
  - **Load Wire:** Carries power to the light fixture.
  - **Neutral Wire:** (Typically white) Completes the circuit.
  - **Ground Wire:** (Typically green or bare copper) For safety.
- 3. Connect Wires:** Use the provided wire nuts to connect the TREATLIFE Smart Wi-Fi Light Switch wires to your house wires according to the diagram below. Match colors:
  - Red wire from switch to Line wire from wall.
  - Black wire from switch to Load wire from wall.
  - White wire from switch to Neutral wire from wall.

- Green wire from switch to Ground wire from wall.

4. **Secure Connections:** Ensure all wire connections are secure.




Figure 5.2: Wiring Guide. This diagram illustrates the correct wiring connections for the smart light switch, detailing how to connect the Load, Line, Neutral, and Ground wires.

### 5.3 Physical Installation

1. Gently push all wires back into the electrical box.
2. Mount the smart switch into the electrical box using the provided screws.
3. Attach the screwless snap-on wall plate over the switch.
4. Restore power at the circuit breaker. The indicator light on the switch should illuminate.

## 6. APP SETUP & PAIRING

To control your TREATLIFE Smart Wi-Fi Light Switch, you need to download and set up the Smart Life app.

1. **Download the App:** Search for "Smart Life" in your smartphone's app store (iOS or Android) and download it.
2. **Register/Log In:** Open the app and register for a new account or log in if you already have one.
3. **Enter Pairing Mode:** On your TREATLIFE Smart Wi-Fi Light Switch, press and hold the main button for approximately 5 seconds until the indicator light rapidly blinks. This indicates the switch is in pairing mode.
4. **Add Device in App:** In the Smart Life app, tap the "+" icon (usually in the top right corner) to add a new device. Select "Switch" from the device list.
5. **Confirm Indicator:** Confirm that the indicator light on your switch is rapidly blinking within the app.
6. **Connect to Wi-Fi:** Enter your 2.4GHz Wi-Fi network name and password when prompted. The app will then connect to the switch.
7. **Rename Device:** Once connected, you can rename your switch (e.g., "Living Room Light", "Kitchen Counter").

**Video 6.1: App Pairing Demonstration.** This video demonstrates the unboxing of the smart switch and the process of pairing it with the Smart Life mobile application.

## 7. VOICE CONTROL INTEGRATION

---

Your TREATLIFE Smart Wi-Fi Light Switch can be controlled using voice commands through Amazon Alexa or Google Assistant.

1. **Link Smart Life Account:** Open your Amazon Alexa or Google Home app. Navigate to the "Skills" or "Works with Google" section and search for "Smart Life". Enable the skill/service and link your Smart Life account using your login credentials.
2. **Discover Devices:** Once linked, ask Alexa or Google Assistant to "Discover devices" or manually initiate device discovery in their respective apps.
3. **Voice Commands:** You can now use voice commands to control your lights. Examples:
  - "Alexa, turn on [Device Name]"
  - "Hey Google, turn off [Device Name]"
  - "Alexa, set [Device Name] to 50%" (Note: This switch is ON/OFF only, percentage commands will not dim but may turn on/off depending on the smart assistant's interpretation).

**Video 7.1: Voice Control Demonstration.** This video showcases the smart light switch being controlled using voice commands via Amazon Alexa, demonstrating its hands-free operation.




Figure 7.2: Hands-free Voice Control. This image illustrates the convenience of controlling lights with voice commands, showing a person interacting with a smart assistant.

## 8. ADVANCED FEATURES

### 8.1 Automated Schedules

Create custom schedules to automate your lighting based on your daily routines or for security purposes.

- **Timer:** Set lights to turn on or off at specific times.
- **Countdown:** Set a countdown for lights to turn off after a set duration.
- **Simulate Occupancy:** Program lights to turn on and off randomly while you're away to deter potential intruders.



## Light Scheduling

Schedule your light based on your daily routines



**Figure 8.1: Light Scheduling.** This image displays the light scheduling feature, allowing users to set timers and countdowns for automated light operation.

### 8.2 Remote Control

Control your lights from anywhere in the world using the Smart Life app, as long as your smartphone has an internet connection.



## APP Remote Control

Control the light from anywhere at any time



Schedules



Device Sharing



Scenes



Away Mode

**Figure 8.2: App Remote Control.** This image shows a user controlling a light remotely via a smartphone app, highlighting features like scheduling and device sharing.

### 8.3 Group Control


Combine multiple TREATLIFE smart switches into groups within the Smart Life app to control several lights simultaneously with a single command.



**Figure 8.3: Group Control.** This image displays a smartphone interface for grouping multiple smart light switches, enabling synchronized control.

## 8.4 Device Sharing

Share control of your smart switches with family members or trusted individuals through the Smart Life app, allowing everyone in the household to manage the lighting.



**Figure 8.4: Device Sharing.** This image illustrates the device sharing feature, allowing multiple users to control the smart switch from their respective smartphones.

## 9. TROUBLESHOOTING

- **Switch Not Responding:** Ensure power is on at the circuit breaker. Check wiring connections. If the

indicator light is off, the switch may not be receiving power.

- **Cannot Connect to Wi-Fi:** Ensure your Wi-Fi network is 2.4GHz. Check your Wi-Fi password. Move the switch closer to your router if signal is weak. Reset the switch by holding the button for 5 seconds until it rapidly blinks, then try pairing again.
- **Voice Control Issues:** Verify your Smart Life account is correctly linked to Amazon Alexa or Google Assistant. Ensure device names are clear and consistent.
- **Lights Flicker/Don't Turn On:** Confirm the switch is not used with a dimmable bulb or fixture. Ensure the load does not exceed 1250W.

## 10. SPECIFICATIONS

Specification	Value
Model Number	SS01S-2V
Operation Mode	ON-OFF
Current Rating	10 Amps
Operating Voltage	120 Volts
Contact Type	Normally Closed
Connector Type	Plug In
Terminal	Spst
Item Dimensions L x W x H	4 x 5 x 6 inches
Circuit Type	1-way
Mounting Type	Wall Mount
Actuator Type	Push Button
Contact Material	Metal
International Protection Rating	IP20
Number of Positions	2
Upper Temperature Rating	45 Degrees Celsius
Controller Type	Amazon Alexa, Google Assistant, IFTTT
Control Method	App, Remote, Touch, Voice
Connectivity Protocol	Wi-Fi (2.4GHz)
Color	White
Wattage	1250 watts
Unit Count	2.0 Count
Item Weight	12 ounces

## 11. WARRANTY AND SUPPORT

The TREATLIFE Smart Wi-Fi Light Switch comes with a **2-year warranty**.

For technical support or warranty claims, please contact TREATLIFE customer service:

- **Address:** 1220 3rd St, Las Cruces, New Mexico, 88005, USA
- **Phone:** 575-555-8828
- **Email:** Support@Treatlife.Tech