

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

- › [Wildgame Innovations](#) /
- › [Wildgame Innovations Terra IR Infrared Hunting Trail Camera User Manual](#)

Wildgame Innovations Terra Extreme 12 Megapixel 2-Pack

Wildgame Innovations Terra IR Infrared Hunting Trail Camera User Manual

Model: Terra Extreme 12 Megapixel 2-Pack

INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your Wildgame Innovations Terra IR Infrared Hunting Trail Camera. Designed for reliable performance in outdoor environments, this camera captures high-quality still images and video footage of wildlife. Please read this manual thoroughly before using your camera to ensure optimal performance and longevity.

SAFETY INFORMATION

- Do not expose the camera to extreme temperatures or direct sunlight for extended periods.
- Ensure batteries are inserted with correct polarity to prevent damage.
- Keep the camera away from strong magnetic fields.
- Do not attempt to disassemble the camera; this will void the warranty.
- Dispose of batteries responsibly according to local regulations.

PACKAGE CONTENTS

Verify that all items are present in your package:

- Wildgame Innovations Terra IR Trail Camera (2 units, as per product specifications)
- Mounting Strap
- User Manual (this document)

CAMERA OVERVIEW

Familiarize yourself with the key components of your Terra IR Trail Camera:



Figure 1: Front view of two Wildgame Innovations Terra IR Trail Cameras. Each camera features a top array of 21 infrared LEDs for night vision, a central camera lens, a lower motion sensor, and an LCD screen displaying time, date, photo count, and battery status. The cameras are black with ruggedized housing.

1. **Infrared LEDs:** 21 high-intensity LEDs for illumination in low-light conditions.
2. **Camera Lens:** Captures still images and video.
3. **PIR Sensor:** Passive Infrared sensor detects motion to trigger recording.
4. **LCD Screen:** Displays camera settings, time/date, and operational status.
5. **Control Buttons:** Navigation and selection buttons (not visible in this image, typically inside the camera).
6. **Battery Compartment:** (Located on the side or back, not visible) Holds required batteries.
7. **SD Card Slot:** (Located inside, not visible) For memory card insertion.

SETUP

1. Battery Installation

The Terra IR camera requires 8 AA batteries (not included). For best performance, use high-quality alkaline or lithium batteries.

1. Open the camera housing latch.
2. Locate the battery compartment.
3. Insert 8 AA batteries, ensuring correct polarity (+/-) as indicated inside the compartment.
4. Close the battery compartment securely.

2. SD Card Installation

A Class 4 or higher SD card (up to 32GB, not included) is required to store images and videos.

1. With the camera powered off, locate the SD card slot inside the camera housing.
2. Insert the SD card with the metal contacts facing down until it clicks into place.
3. To remove, press the card in until it springs out.

3. Initial Settings (Time/Date)

Before deployment, set the correct time and date for accurate file stamping.

1. Turn the camera ON.
2. Navigate to the 'Time/Date' setting using the control buttons.
3. Adjust the year, month, day, hour, and minute.
4. Confirm settings to save.

4. Mounting the Camera

Use the included mounting strap to secure the camera to a tree or post.

1. Thread the strap through the slots on the back of the camera.
2. Wrap the strap around the desired mounting object.
3. Secure the strap tightly, ensuring the camera is stable and pointed towards the desired area.
4. Position the camera approximately 3-5 feet off the ground for optimal detection.

OPERATING THE CAMERA

Modes of Operation

The Terra IR camera supports both still image and video capture modes.

- **Still Image Mode:** Captures high-resolution photos (up to 12MP).
- **Video Mode:** Records video clips (up to 30 seconds).

Changing Modes

Use the control buttons to select your desired capture mode on the LCD screen. The screen will indicate the currently selected mode (e.g., "Still" or "Video").

Field Deployment

Once configured, close the camera housing securely. The camera will enter a monitoring state and begin capturing images or videos when motion is detected within its PIR sensor range.

MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the camera lens and PIR sensor window. Do not use abrasive cleaners.
- **Battery Replacement:** Replace batteries when the low battery indicator appears on the LCD screen to ensure continuous operation.
- **SD Card Management:** Regularly check the SD card capacity. Format the SD card periodically to maintain optimal performance and prevent data corruption.

- **Storage:** When not in use, store the camera in a cool, dry place, away from direct sunlight and extreme temperatures. Remove batteries if storing for extended periods.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Camera not powering on.	Dead or incorrectly inserted batteries.	Replace batteries with new ones, ensuring correct polarity.
No images/videos captured.	SD card full, incorrect settings, or PIR sensor obstructed.	Format or replace SD card. Check camera settings (mode, delay). Ensure clear line of sight for PIR sensor.
Poor image/video quality.	Dirty lens, low light, or object too far/close.	Clean the lens. Ensure adequate lighting or proper distance from subject.
Camera triggers too often/not enough.	PIR sensitivity setting, environmental factors (wind, heat).	Adjust PIR sensitivity. Reposition camera to avoid false triggers from moving branches or direct sunlight.

SPECIFICATIONS

- **Effective Still Resolution:** 12 MP
- **Video Capture Format:** MPEG-4
- **Infrared LEDs:** 21-piece high intensity array
- **Trigger Speed:** One-second
- **Illumination Range:** Up to 65 feet
- **Power Source:** 8 AA Batteries (not included)
- **Memory:** Supports SD card up to 32GB (not included)
- **Connectivity Protocol:** Wi-Fi
- **International Protection Rating:** IP54
- **Color:** Black
- **Material:** Plastic
- **Model Name:** Terra Extreme Trail Camera 12MP 2-Pack
- **UPC:** 616376512087

WARRANTY AND SUPPORT

Your Wildgame Innovations Terra IR Trail Camera comes with a **1 Year Warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For technical support, warranty claims, or further assistance, please visit the official Wildgame Innovations website or contact their customer service department. Keep your proof of purchase for warranty validation.

Official Brand Store: [Wildgame Innovations Store on Amazon](#)



