Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

OmniMaster PMD5

OmniMaster PatrolMaster PMD5 64GB User Guide

Model PMD5 (SMA-01); ASIN B07T8YPMRT.

Current manufacturer documentation

This corrected reference summary supersedes the older generated guide on this page. It is based on OmniMaster's English (United States) manual, edition 1.1, November 2026, for the existing 64GB and 128GB PMD5 versions. It is not a substitute for the complete manufacturer's instructions.
Official PMD5 guide, tutorials and current support · Read or download the official 16-page PMD5 manual (PDF)

Charging and battery endurance

Use the USB-C cable and a suitable DC 5V / 2A power source. A wall power adapter is not included. The supplier-rated figures are 15 hours of continuous operation and 24 hours of standby. Actual runtime depends on recording mode, infrared use, screen and other settings, battery condition and operating conditions. These figures are not an unconditional recording-duration guarantee.
The 64GB built-in storage capacity affects how many recordings can be stored, not battery capacity. Earlier battery-capacity and longer-runtime figures on this page are superseded; the current manual does not give a numerical battery-capacity value.

Setup and recording

1. Read the safety instructions, charge the camera, and hold Power for approximately three seconds to turn it on.
2. Set the date and time and choose the recording settings. Make a short test recording and check its playback before important use.
3. Briefly press the red Video button to start recording; briefly press it again to stop and save.
4. Use PTT to switch recording resolution. The startup resolution can be selected in the Video Resolution menu.

In Manual Infrared mode, hold the red Video / Night Vision button while the powered-on camera is in use to switch infrared on or off. Auto mode responds to light conditions. The current guide does not document the earlier numerical night-vision range claims shown here; do not rely on those distances.

Local storage, transfer and deletion

This version has 64GB of fixed built-in storage. The documented workflow is local recording and USB-C transfer to a Windows PC or Mac; do not infer Wi-Fi transfer, cloud evidence management, encryption or audit logging from earlier page content.

1. Stop recording and connect the camera using a USB data cable.

2. Open the camera drive in Windows File Explorer or Mac Finder and copy the files to your computer.
3. Check that the copies play correctly and keep suitable backups before deleting originals.
4. Eject the drive using the computer's normal eject control before disconnecting.

Manual file deletion is performed on a computer. Loop Recording is off by default; if enabled, it can overwrite older recordings when storage becomes insufficient. Fixed internal storage does not make recordings tamper-proof. Neither the device nor this guide guarantees that a recording will be admissible in court.

Protection and Safe Use

The supplier describes professional-grade water and dust protection but gives no numerical IP code in the current manual. Do not treat the earlier numerical ingress-protection claim as a currently documented certification or assume the camera may be immersed.
Avoid excessive heat and direct sun, keep the camera dry when stored, and do not open or modify the built-in battery. Follow the manufacturer's safety instructions and the recording rules applicable to your use.

Current Specification Reference

Item	Documented value
Version	PMD5 64GB (SMA-01)
Video modes	2304 × 1296 / 30 fps; 1920 × 1080 / 30 fps; 1280 × 720 / 60 or 30 fps; 848 × 480 / 30 fps
Video files	MOV, H.264 compression
Power	USB-C, DC 5V / 2A; wall power adapter not included
Supplier-rated endurance	15 hours continuous operation; 24 hours standby, subject to conditions
Storage and transfer	64GB fixed internal storage; USB-C to Windows or Mac
Saved video segment length	5, 10, 15, 20 or 30 minutes; not a limit on total recording time
Water/dust protection	Supplier describes professional grade; no numerical IP code stated

Support and Warranty

For current warranty terms, troubleshooting and model-specific help, use OmniMaster's official PMD5 guide or email support@omnimaster.us. Keep proof of purchase. A separate paper warranty card is not required. Earlier generic specifications and promotional illustrations have been replaced by this source-linked reference.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B07T8YPMRT

More documents and user manuals: **https://manuals.plus/**