

Crenova XPE500

Crenova Mini Projector XPE500 User Manual

Model: XPE500

Brand: Crenova

INTRODUCTION

Thank you for choosing the Crenova Mini Projector XPE500. This portable projector is designed to provide a versatile and immersive viewing experience for home entertainment, outdoor movies, and various video games. Supporting 1920x1080 resolution, 4500-lumen brightness, and a 3000:1 contrast ratio, it delivers a brilliant big-screen visual experience.

This manual provides essential information for setting up, operating, maintaining, and troubleshooting your projector to ensure optimal performance and longevity.



Image: The Crenova Mini Projector XPE500, a compact white device, is shown with its remote control. The projector lens emits a bright light, indicating its operational state.

1. SETUP GUIDE

Follow these steps to set up your Crenova Mini Projector for the first time.

1.1 Package Contents

Ensure all items are present in the box:

- 1 x LCD Projector
- 1 x HDMI Cable
- 1 x Power Cable
- 1 x AV Cable
- 1 x Remote control (battery not included)
- 1 x User Manual
- 1 x Card

1.2 Power Connection

Connect the power cable to the projector and then to a power outlet. The projector will power on or enter standby mode.

1.3 Device Connection

The projector offers multiple interfaces for connecting various devices. An extra HDMI adapter may be needed when connecting with a phone.



Image: A diagram illustrating the seven interface connections available on the Crenova projector, including VGA, SD, HDMI, AV Audio Out, and USB, showing compatibility with phones, iPads, laptops, Xbox/PS4, Firestick, and Roku.

- **HDMI:** Connect laptops, gaming consoles (Xbox ONE), TV sticks (Amazon Fire TV Stick, Roku), and other HDMI-enabled devices.
- **USB:** Connect USB drives for media playback.
- **VGA:** Connect older computers or laptops.
- **AV:** Connect devices using an AV cable.
- **TF Card:** Insert a TF card for direct media playback.

For smartphone connection, the projector supports stable wired mirroring. This allows for easy screen mirroring from iOS and Android devices, typically requiring an HDMI adapter for phones.



Image: The projector is shown connected via a wired connection to a smartphone and a tablet, demonstrating stable wired mirroring for iOS and Android devices.

To connect an Amazon Fire TV Stick, simply plug it into the HDMI port and power it via a USB port or external power source.



Fire TV Connection

Enjoy your Own Home Theater



Image: The projector is depicted with an Amazon Fire TV Stick connected, showcasing how to enjoy streaming services and create a home theater experience.

1.4 Projection Size and Distance

The mini LED projector provides a watching size from 33 inches to 200 inches with a viewing distance between 3.7 feet and 19.7 feet. For an excellent spectating experience, a viewing distance of 7 feet is strongly recommended.



Image: An illustration showing the projector casting an image onto a large screen, with indicators for projection sizes ranging from 33 inches to 200 inches and corresponding throw distances.

2. OPERATING INSTRUCTIONS

Learn how to operate your Crenova Mini Projector for the best viewing experience.

2.1 Power On/Off

Press the power button on the projector or the remote control to turn the unit on or off.

2.2 Adjusting Focus and Keystone

To achieve a clear and rectangular image, adjust the focus and keystone correction:

- **Focus:** Rotate the focus ring near the lens until the image appears sharp and clear.

- **Keystone Correction:** Use the keystone adjustment to correct trapezoidal distortion, ensuring the projected image is rectangular.



Image: A close-up view of the projector's focus adjustment mechanism, highlighting the slider used to achieve optimal image clarity.

2.3 Brightness and Color Performance

The Crenova XPE500 projector boasts authentic 4500-lumen brightness and a 3000:1 contrast ratio, providing vibrant and clear visuals. It features advanced color matching technology for up to +30% brightness uniformity, enhancing the overall picture quality.




+30% Brightness Uniformity

Advanced Color Matching Technology



Crenova 720P



Other 720P

Image: A split image comparing the brightness uniformity of Crenova 720P projectors versus other 720P projectors, demonstrating the improved color and brightness consistency of the Crenova model.

2.4 Audio Experience

The projector is equipped with an advanced built-in stereo speaker system, offering excellent loud sound quality without the need for external speakers. This provides original audio fidelity, enhancing your immersion in the movie experience.



Superior Hi-Fi Sound

Enjoy the pleasure sounds in different scenes.



Image: An overhead view of a couple enjoying a movie projected onto a wall, with sound waves emanating from the projector, illustrating the superior Hi-Fi sound experience.

For enhanced audio, you can connect external speakers via the 3.5mm audio port.

3. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your projector.

- **Lens Cleaning:** Gently clean the projector lens with a soft, lint-free cloth designed for optical surfaces. Avoid abrasive materials or harsh chemicals.
- **Dust Removal:** Regularly clean the air vents to prevent dust buildup, which can affect cooling and performance. Use a soft brush or compressed air.
- **Storage:** When not in use, store the projector in a cool, dry place, away from direct sunlight and extreme

temperatures. Use the original packaging or a protective case to prevent damage.

- **Power Off Properly:** Always power off the projector using the designated power button and allow it to cool down before unplugging or moving.

4. TROUBLESHOOTING

This section addresses common issues you might encounter with your Crenova Mini Projector.

4.1 Image Issues

- **Blurry Image:**
First, correct the keystone to ensure the image is rectangular. Second, rotate the focus button to gain the best clarity. Ensure the projector is at the recommended viewing distance.
- **Crooked or Skewed Image:**
Ensure the projector is placed on a flat, stable surface and is positioned directly in front of the projection screen. Adjust the keystone correction if the image appears trapezoidal.
- **No Picture:**
Check all cable connections (HDMI, USB, etc.) to ensure they are secure. Verify that the correct input source is selected on the projector.
- **Dim Picture:**
Ensure the room is sufficiently dark. The projector performs best in low-light conditions. Check if the lens is clean.

4.2 Audio Issues

- **No Sound or Low Volume:**
Check the volume level on both the projector and the connected device. If using external speakers, ensure they are properly connected and powered on. If connecting to a soundbar or speaker, use the 3.5mm audio port.

4.3 Other Issues

- **Overheating:**
Ensure proper ventilation around the projector. Do not block the air vents. If the projector feels excessively hot, power it off and allow it to cool down before resuming use.
- **Fan Noise:**
A certain level of fan noise is normal for projectors as they require cooling. If the noise is unusually loud, ensure vents are clear of obstructions.

For further assistance, please refer to the professional customer support channels.



Professional Customer Supports




Image: A simulated chat conversation demonstrating common customer support inquiries and solutions, such as correcting blurry images and connecting to external audio.

5. SPECIFICATIONS

Feature	Detail
Brand Name	Crenova
Model Number	XPE500
Item Weight	2.6 pounds
Product Dimensions	8.5 x 6.4 x 3.07 inches

Feature	Detail
Color	Pearl White
Display Resolution	1280 x 800 (Supports 1920x1080)
Brightness	4500 Lumens
Contrast Ratio	3000:1
Connectivity Technology	HDMI, VGA, USB, AV, TF Card, TV BOX, Firestick
Speaker Type	Built-In Stereo Speakers
Recommended Uses	Home Cinema, Gaming
Visible Screen Diagonal	200" / 508 cm (Max)
Lamp Life	50,000 hours (estimated)

6. WARRANTY AND SUPPORT

Crenova stands behind the quality of its products. The Crenova Mini HD Projector supports 50,000 hours of daily usage and is insured with a 36-month risk-free warranty and lifetime technical support.

If you encounter any issues or have questions, please do not hesitate to contact Crenova customer support. We are here to assist you.

For support, please visit the official Crenova website or contact their customer service channels.

© 2023 Crenova. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for

conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question