

Artika AMP105-RNBL

Artika Essence Wall-Mounted LED Modern Light Fixture

Model: AMP105-RNBL

1. INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Artika Essence Wall-Mounted LED Modern Light Fixture. Please read this manual thoroughly before installation and retain it for future reference.

Important Safety Information

- **Electrical Safety:** Ensure the product is properly grounded. Professional installation is recommended.
- **Environmental Protection:** Protect from exposure to water and extreme temperatures.
- Always turn off the main power supply at the circuit breaker before beginning any electrical work.
- Consult a qualified electrician if you are unsure about any part of the installation process.

2. PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Artika Essence LED Light Fixture (Model AMP105-RNBL)
- Mounting Bracket
- Mounting Hardware (screws, wire nuts)
- Instruction Manual

3. INSTALLATION INSTRUCTIONS

Follow these steps carefully to install your Artika Essence light fixture. It is suitable for both indoor and outdoor wall-mounted applications.

1. Prepare for Installation:

- Turn off the electrical power at the main circuit breaker or fuse box.

- Ensure the power is off before proceeding.

2. Attach Mounting Bracket:

- Secure the mounting bracket to the electrical junction box using the provided screws. Ensure it is firmly attached.

3. Make Electrical Connections:

- Connect the fixture's ground wire (green or bare copper) to the house supply ground wire.
- Connect the fixture's white wire to the house supply white (neutral) wire.
- Connect the fixture's black wire to the house supply black (live) wire.
- Secure all connections with the provided wire nuts and wrap with electrical tape for added safety.

4. Mount the Fixture:

- Carefully align the fixture with the mounting bracket and secure it using the provided screws.
- Ensure the fixture is flush against the wall and stable.

5. Restore Power:

- Once the fixture is securely installed and all connections are made, restore power at the circuit breaker.
- Test the light fixture to ensure proper operation.

7.2 cm
2.8 in/po



28.7 cm
11.3 in/po

15.6 cm
6.1 in/po

Figure 3.1: Product Dimensions (6.1" L x 6.1" W x 11.3" H)



Figure 3.2: Front view of the Artika Essence light fixture.



Figure 3.3: Side view of the Artika Essence light fixture, highlighting the bubble glass element.

Video 3.1: A brief overview of the Artika Essence LED Outdoor/Indoor Sconce Light, demonstrating its appearance and light output.

4. OPERATING INSTRUCTIONS

The Artika Essence light fixture features integrated LED lighting with 3-way light illumination (up/down light). It is designed for simple operation.

- **Power On/Off:** Control the light fixture using a standard wall switch connected to the electrical circuit.
- **Dimming Functionality:** This fixture is dimmable. To utilize the dimming feature, ensure it is connected to a compatible LED dimmer switch (sold separately). Follow the dimmer switch manufacturer's instructions for installation and operation.

5. MAINTENANCE

To ensure the longevity and optimal performance of your Artika Essence light fixture, follow these maintenance guidelines:

- **Cleaning:** Disconnect power before cleaning. Use a soft, dry cloth to wipe the fixture. Avoid abrasive cleaners, solvents, or polishes as they may damage the finish or electrical components.
- **LED Components:** The LED bulbs are integrated and designed for long-term use (up to 25,000 hours). They are not user-replaceable.
- **Inspection:** Periodically inspect the fixture for any signs of damage or loose connections. If any issues are found, disconnect power and consult a qualified electrician.

6. TROUBLESHOOTING

If you encounter issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power supply.	Check the circuit breaker or fuse. Ensure the wall switch is in the 'ON' position.
	Loose wiring connection.	Turn off power at the circuit breaker. Recheck all wire connections.
Light flickers or dims unexpectedly.	Incompatible dimmer switch.	Ensure you are using an LED-compatible dimmer switch.
	Loose wiring.	Turn off power at the circuit breaker. Recheck all wire connections.

If the problem persists after attempting these solutions, contact customer support or a qualified electrician.

7. SPECIFICATIONS

Feature	Detail
Brand	Artika
Model Name	AMP105-RNBL
Product Dimensions	6.1" L x 6.1" W x 11.3" H (15.6 cm L x 15.6 cm W x 28.7 cm H)
Color	Black
Material	Metal, Glass
Style	Modern
Power Source	Hardwire
Light Source Type	Integrated LED
Voltage	120 Volts
Wattage	24 watts
Brightness	600 Lumens
Color Temperature	3000 Kelvin

Feature	Detail
Special Feature	3-way light illumination, Dimmable
Shade Material	Premium Bubble Glass
Mounting Type	Wall Mount
Estimated LED Lifespan	25,000 hours
Item Weight	6.9 Pounds
UPC	846979020959

8. WARRANTY INFORMATION

This product is covered by a manufacturer's warranty. For specific details regarding warranty coverage, terms, and conditions, please refer to the documentation included with your purchase or visit the official Artika website.

9. CUSTOMER SUPPORT

For technical assistance, missing parts, or any questions regarding your Artika Essence light fixture, please contact Artika customer support. Contact information can typically be found on the manufacturer's website or on the product packaging.

Related Documents - AMP105-RNBL

	<p>Artika Essence Glow Box LED Wall Light GB390L-HDBL Installation Manual</p> <p>Official instruction manual for the Artika Essence Glow Box LED Wall Light (Model GB390L-HDBL). Includes installation steps, parts list, warranty information, and safety precautions.</p>
	<p>Artika Ratio 4 Wall-Mounted Light Fixture Instruction Manual</p> <p>This manual provides step-by-step instructions for the installation and use of the Artika Ratio 4 wall-mounted light fixture. It includes details on included hardware, necessary tools, installation steps, warranty information, and safety precautions.</p>
	<p>Artika Essence 4 LED Pendant Light - Instruction Manual and Installation Guide</p> <p>Detailed instruction manual for the Artika Essence 4-light LED pendant light (Model OME59B-HD2D). Includes parts list, step-by-step installation, height adjustment, troubleshooting, replacement parts, warranty, and FCC compliance information.</p>

