

Hercules DJSPEAKER 32 SMART

Hercules DJSPEAKER 32 SMART Active Bluetooth Monitor Speakers User Manual

Brand: Hercules | Model: DJSPEAKER 32 SMART

1. INTRODUCTION

The Hercules DJSPEAKER 32 SMART speakers are compact, high-quality active monitor speakers designed for mixing, producing, and listening to music. They offer wireless connectivity via Bluetooth and can also be connected using cables. Developed by audio professionals, these speakers provide clear sound reproduction suitable for various audio tasks.

Key Features:

- Multifunctional Bluetooth Active DJ speakers for mixing, producing, and wireless music listening.
- Bluetooth Multi-pairing technology allows simultaneous connection to up to two devices.
- Delivers 30 watts RMS (60 watts Peak power) with a 7.6-cm/3-inch woofer.
- Features a shifted tweeter for clearer sound rendering and enhanced spatial stereo effect.
- Optimized acoustic waveguide ensures lifelike audio reproduction.

2. WHAT'S IN THE BOX

- Hercules DJSPEAKER 32 SMART Speakers (2 units)
- Speaker Connection Cable
- Instruction Book

3. PRODUCT OVERVIEW



Figure 1: Front view of the Hercules DJSPeaker 32 SMART speakers. Both speakers feature a 3-inch woofer and a tweeter. The active speaker includes front-facing controls.



Figure 2: Close-up of the active speaker's front panel, showing the volume knob, power/volume LED indicator, auxiliary input (AUX), and headphone jack.



Figure 3: Rear view of the active (left) and passive (right) speakers. The active speaker features RCA and balanced inputs, an output to the passive speaker, and a power switch. The passive speaker has a single input from the active speaker.

Official Product Video:

Video 1: Official product overview of the Hercules DJSPKAKER 32 SMART, demonstrating its features and connectivity options. This video is provided by Hercules.

Product Overview Video:

Video 2: A brief product overview video showcasing the Hercules DJSPKAKER 32 SMART. This video is provided by Amazon Product Imaging.

4. SETUP INSTRUCTIONS

4.1. Speaker Placement

Position the active speaker (with controls) and the passive speaker on a flat, stable surface. Ensure adequate space around each speaker for optimal sound dispersion. The active speaker can be placed on either the right or left side; adjust the 'Active Speaker Position' switch on the rear panel accordingly.

4.2. Power Connection

1. Connect the power cable to the 'Power In' port on the rear of the active speaker.
2. Plug the other end of the power cable into a suitable wall outlet (100-240V, 50/60Hz).

4.3. Connecting Speakers

1. Use the provided speaker connection cable.
2. Connect one end of the cable to the 'Output to L-SPK' port on the active speaker.
3. Connect the other end to the 'Input from Active Speaker' port on the passive speaker.

4.4. Audio Source Connection

Choose one of the following methods to connect your audio source:

- **Bluetooth:** Ensure Bluetooth is enabled on your device. The speakers will automatically enter pairing mode when powered on. Select 'Hercules DJSPEAKER 32 SMART' from your device's Bluetooth list to connect.
- **RCA Input:** Use an RCA cable (not included) to connect your audio source (e.g., DJ controller, audio interface) to the 'Input R/L' RCA ports on the rear of the active speaker.
- **Balanced Input:** Use 1/4-inch TRS cables (not included) to connect your audio source to the 'Balanced R/L' input jacks on the rear of the active speaker.
- **Auxiliary Input (Front):** Use a 3.5mm audio cable to connect your device to the 'AUX' input jack on the front of the active speaker.

5. OPERATING INSTRUCTIONS

5.1. Powering On/Off

Flip the 'On/Off' switch on the rear panel of the active speaker to the 'On' position. The power/volume LED on the front will illuminate.

5.2. Adjusting Volume

Rotate the 'Volume' knob on the front of the active speaker clockwise to increase volume and counter-clockwise to decrease it.

5.3. Headphone Use

Plug your headphones into the 3.5mm headphone jack on the front of the active speaker. The speaker output will mute automatically.

6. MAINTENANCE

To ensure the longevity and optimal performance of your Hercules DJSPEAKER 32 SMART speakers, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the speaker surfaces. Avoid abrasive cleaners or solvents.
- **Environment:** Keep speakers away from direct sunlight, heat sources, and excessive moisture.
- **Handling:** Handle speakers with care to avoid damage to the drivers. Avoid poking the tweeter or woofer cones.
- **Storage:** When not in use for extended periods, store speakers in a cool, dry place.

7. TROUBLESHOOTING

If you encounter issues with your speakers, refer to the following common troubleshooting steps:

- **No Power:** Ensure the power cable is securely connected to both the speaker and the wall outlet. Check if the power switch on the rear is in the 'On' position.
- **No Sound:** Verify that the volume knob is turned up. Check all audio cable connections. If using Bluetooth, ensure the device is properly paired and the volume on the source device is also turned up.
- **Distorted Sound:** Reduce the volume on both the speakers and the audio source. Check for damaged audio cables.
- **Bluetooth Pairing Issues:** Ensure the speakers are in pairing mode (LED blinking). Turn off and on Bluetooth on your source device, then try pairing again.


8. SPECIFICATIONS





Feature	Specification
Output Power	30 Watts RMS (60 Watts Peak)
Speaker Type	Active Monitor Speakers
Woofer Diameter	3 Inches (7.6 cm)
Tweeter Diameter	1 Inch
Connectivity	Bluetooth, RCA, Balanced (TRS), 3.5mm AUX
Bluetooth Range	10 Meters
Audio Output Mode	Stereo
Item Weight	7.46 Pounds
Product Dimensions	9.33 x 15.94 x 7.28 inches
Manufacturer	Hercules

9. WARRANTY AND SUPPORT

The Hercules DJSPEAKER 32 SMART comes with a Limited Warranty. For detailed warranty terms, conditions, and support, please refer to the official Hercules website or the warranty information provided in your product packaging. For technical assistance or customer service, contact Hercules support directly.

Related Documents - DJSPEAKER 32 SMART

	<p>Comment vérifier l'installation d'un périphérique Hercules WiFi</p> <p>Guide pour vérifier l'installation correcte de votre périphérique WiFi Hercules sur Windows en utilisant le Gestionnaire de périphériques. Inclut des étapes pour identifier les problèmes d'installation et de configuration.</p>
	<p>XPS SOUND BAR USB - دليل المستخدم والمواصفات</p> <p>يتضمن محتويات العلبة، تعليمات التوصيل، دليل شامل لنظام الصوت Hercules من XPS SOUND BAR USB، معلومات الضمان، وحقوق الطبع والنشر والاستخدام، احتياطات السلامة.</p>

	<p>Manuale d'uso Hercules USB WiFi Transmitter</p> <p>Guida completa all'installazione e all'utilizzo del trasmettitore USB WiFi Hercules, con istruzioni dettagliate per la condivisione della connessione internet e la gestione degli accessi alla rete.</p>
	<p>Hercules DJControl Inpulse 300 Mk2 Quick Start Guide - Setup and Installation</p> <p>Comprehensive quick start guide for the Hercules DJControl Inpulse 300 Mk2 DJ controller. Learn how to connect, install software (Serato DJ Lite, DJUCED), and set up your equipment for music production and DJing.</p>
	<p>Hercules USB WiFi Transmitter User Manual</p> <p>This user manual provides detailed information for setting up and using the Hercules USB WiFi Transmitter. It covers installation, driver setup, connecting to WiFi networks, and managing network access for PCs and gaming consoles.</p>
	<p>HERCULES Pedelec Operating Instructions with BAFANG DP E160.CAN System</p> <p>Comprehensive operating manual for HERCULES pedelecs featuring the BAFANG DP E160.CAN system. Covers safety, assembly, operation, maintenance, and troubleshooting for various Urbanico models.</p>