

## JALL DC801

# JALL Digital Calendar Alarm Day Clock User Manual

Model: DC801

Brand: JALL

## 1. INTRODUCTION

Thank you for purchasing the JALL Digital Calendar Alarm Day Clock. This device is designed to provide clear and easy-to-read time, date, and day information, making it ideal for individuals with impaired vision, seniors, and those with dementia. Its large 8-inch screen and multiple alarm settings help users stay oriented and manage daily routines effectively. This manual provides detailed instructions for setup, operation, maintenance, and troubleshooting to ensure optimal performance of your clock.

## 2. IMPORTANT SAFETY INFORMATION

Please read and understand all safety instructions before using this product. Keep this manual for future reference.

- **WARNING:** To reduce the risk of fire or electric shock, do not expose this appliance to rain or moisture.
- To prevent fire or shock hazard, do not install this product in a confined space such as a bookcase or similar unit.
- **CAUTION:** To reduce the risk of electric shock, do not remove the cover (or back). There are no user-serviceable parts inside. Refer servicing to qualified personnel.
- The clock is not battery operated; it requires a corded electric power source.
- Avoid applying excessive pressure to the high-quality non-reflective LED screen.

## 3. PACKAGE CONTENTS

Please check the package contents carefully. If any items are missing or damaged, contact customer support.

- JALL Digital Calendar Alarm Day Clock (Model: DC801)
- Power Adapter
- User Manual
- Remote Control (for models with remote functionality)

## 4. PRODUCT OVERVIEW

The JALL Digital Calendar Alarm Day Clock features a large, clear display and intuitive controls for ease of use.



**Figure 4.1: Front View of the Clock.** This image shows the main display of the JALL Digital Calendar Alarm Day Clock, clearly indicating the day of the week, time with AM/PM, and full date. The large, high-contrast text is designed for easy readability from a distance.

# 8 - in Large Screen

- Easy to Watch Time for the Aged



**\* Not Battery Operated !**

**Figure 4.2: Clock Dimensions.** This diagram illustrates the physical dimensions of the clock, measuring approximately 8.5 inches in width and 6.75 inches in height, with an 8-inch diagonal screen. It also notes that the clock is not battery operated.



**Figure 4.3: Rear Panel and Controls.** The back of the clock features the DC power port, a USB port for upgrading (USB Upgrading ONLY), and control buttons (On/Off, Up, Down, OK, Menu) for setting the clock. A slot for wall hanging is also visible.

### Key Features:

- **Large Screen Display:** 8-inch high-resolution digital display clearly spells out the time, date, and month.
- **Multiple Alarm Settings:** Supports 2 to 5 alarm settings, useful for medication reminders.
- **Auto-Dimming Option:** Automatically dims at 7:00 PM (Mid/Low Brightness) and brightens at 7:00 AM (High Brightness). This feature can also be turned off.
- **User-Friendly Interface:** Simple controls, often with a remote, for easy setup and adjustments.
- **Display Modes:** Options for 12-hour or 24-hour time format, and various date display modes (e.g., Month-Day-Year).
- **Mounting Options:** Can be placed on a desk using the built-in stand or wall-mounted.

## 5. SETUP

Follow these steps to set up your JALL Digital Calendar Alarm Day Clock:

1. **Unpack the Clock:** Carefully remove the clock and all accessories from the packaging.
2. **Remove Screen Protector:** The clock is packaged with a thin anti-scratch screen protector. Gently peel it off using the pull-up tab. Ensure not to apply pressure directly to the screen during this process.
3. **Connect Power:** Insert the power adapter cable into the DC IN port on the back of the clock. Plug the power adapter into a standard electrical outlet. The clock has an auto switch-on facility when connected to the power supply.
4. **Initial Power On:** If the clock does not automatically turn on, press the On/Off button located on the back panel.
5. **Placement:**
  - **Desk Placement:** Extend the built-in stand on the back of the clock to place it securely on a flat surface.
  - **Wall Mounting:** Use the wall hanging slot on the back of the clock to mount it on a wall using an appropriate screw (not included). Ensure the power cord can reach an outlet safely.



**Figure 5.1: Clock with Power Cord.** This image demonstrates the clock connected to a power outlet, emphasizing that it is corded electric and not battery operated. Proper placement ensures clear visibility and access to power.

## 6. OPERATING INSTRUCTIONS

The clock's settings can be adjusted using the buttons on the back panel or, if included, the remote control.

### 6.1. Setting Time and Date

1. Press the **MENU** button on the back of the clock or on the remote control to enter the settings menu.
2. Use the **UP** and **DOWN** arrows to navigate through the menu options (e.g., Set Date, Time Mode, Date Mode, Language).
3. Press **OK** to select an option.
4. Use **UP** and **DOWN** to adjust values (e.g., hour, minute, year, month, day).
5. Press **OK** to confirm each setting.



6. Once all settings are adjusted, exit the menu by pressing **MENU** again or waiting for the menu to time out.



**Figure 6.1: Adjusting Settings with Remote Control.** This image shows the user interface for adjusting settings such as date, time mode (24-hour), date mode (Month-Day-Year), language, auto dimming, and color mode. The remote control simplifies interaction, especially when the clock is wall-mounted.

## 6.2. Alarm Settings

The clock supports 2 to 5 alarm settings, which can be configured for daily reminders, such as medication times.

1. From the main menu, navigate to the "Alarm Settings" option (exact name may vary).
2. Select an alarm slot (e.g., Alarm 1, Alarm 2).
3. Set the desired alarm time using the **UP** and **DOWN** buttons and confirm with **OK**.
4. Choose the alarm frequency (e.g., daily, weekdays, weekends, specific days).
5. Enable or disable the alarm.
6. Repeat for additional alarms as needed.

**Do the seniors in your family have such sleeping problem?  
Their life is getting chaotic due to unclear time, day and date.**



**Figure 6.2: Medication Reminder Alarm.** This image illustrates how the clock displays a clear message like "TAKE YOUR MEDICINE" when an alarm is triggered, along with instructions to stop the alarm. This feature is particularly beneficial for managing medication schedules.

### **6.3. Auto-Dimming Function**

The clock features an auto-dimming function to adjust screen brightness based on the time of day, enhancing comfort and readability.

- By default, the clock auto dims during the night at 7:00 PM (to Mid Brightness or Low Brightness options).
- It brightens up during the day at 7:00 AM (to High Brightness).
- To turn off the auto-dimming function, navigate to the "Auto Dimming" option in the settings menu and select "Off". This is useful for users who prefer consistent high brightness.



**Figure 6.3: Auto-Dimming in Action.** This image depicts the clock in a room with lower ambient light, showcasing how the auto-dimming feature adjusts the screen brightness for comfortable viewing during evening or night hours.

6.4. Display Modes and Language

- You can switch between 12-hour (AM/PM) and 24-hour time formats in the "Time Mode" setting.
- Adjust the date display format (e.g., Month-Day-Year, Day-Month-Year) in the "Date Mode" setting.
- Select your preferred language from the "Language" option in the settings menu.

7. MAINTENANCE

Proper care and maintenance will ensure the longevity of your JALL Digital Calendar Alarm Day Clock.

- **Cleaning:** Use a soft, dry, lint-free cloth to clean the screen and exterior of the clock. Do not use abrasive cleaners, waxes, or solvents. Avoid spraying liquids directly onto the screen or into any openings.
- **Power Cord:** Regularly inspect the power cord for any signs of damage. If the cord is damaged, discontinue use and contact customer support.
- **Placement:** Ensure the clock is placed in a stable location, away from direct sunlight, excessive heat, moisture, or strong magnetic fields.
- **Storage:** If storing the clock for an extended period, unplug it from the power outlet and store it in a cool, dry place.

8. TROUBLESHOOTING

If you encounter any issues with your clock, please refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Clock does not turn on.	No power, loose connection, power adapter issue.	Ensure the power adapter is securely plugged into both the clock and a working electrical outlet. Try a different outlet. Press the On/Off button.



Problem	Possible Cause	Solution
Display is too dim or too bright.	Auto-dimming feature is enabled, or brightness settings need adjustment.	Check the "Auto Dimming" setting in the menu. Adjust brightness levels manually if auto-dimming is off.
Alarm does not sound.	Alarm is disabled, volume is too low, or incorrect alarm time/frequency.	Verify alarm settings in the menu, ensure the alarm is enabled, and check the volume level.
Time/Date is incorrect.	Time/Date not set correctly or power interruption.	Re-enter the correct time and date through the settings menu.
Remote control not working.	Dead battery, obstruction, or not pointed correctly.	Replace the remote control battery (CR2032, if applicable). Ensure no obstructions between the remote and the clock's sensor. Point the remote directly at the clock.

If the problem persists after trying these solutions, please contact JALL customer support for further assistance.

9. SPECIFICATIONS





Feature	Detail
Brand	JALL
Model Number	DC801
Display Type	Digital
Screen Size	8 inches
Color	Black
Product Dimensions	8"W x 7"H
Power Source	Corded Electric
Material	Plastic (Frame: Acrylonitrile Butadiene Styrene)
Mounting Type	Desk, Wall Mount
Item Weight	1.2 Pounds
Batteries Required	1 CR2032 (for remote, if included)
Special Features	Multiple alarms, Auto-dimming, AM/PM or 24-hour display, Full date display

10. WARRANTY AND SUPPORT

JALL is committed to providing high-quality products and customer satisfaction.

- **Warranty:** We offer a 365-Day warranty on all products sold on Amazon. Please shop with confidence.
- **Customer Support:** For any questions, technical assistance, or warranty claims, please visit the official JALL Store on Amazon or contact their customer service directly through the Amazon platform.

Related Documents

	<p><a href="#">JALL PH-10 8 in 1 Colors Digital Wall Clock User Manual</a></p> <p>User manual for the JALL PH-10 Digital Wall Clock, detailing installation, setup, features like time and alarm setting, temperature display, night light, screen brightness, countdown functions, and warranty information.</p>
	<p><a href="#">JALL RGB Digital Alarm Clock User Manual</a></p> <p>User manual for the JALL RGB Digital Alarm Clock, detailing setup, time setting, alarm functions, display options, USB output, and FAQs. Includes warranty information and customer support contact.</p>
	<p><a href="#">JALL Digital Wall Clock User Manual</a></p> <p>User manual for the JALL Digital Wall Clock, providing instructions on installation, setup, features like time and alarm setting, temperature display, screen brightness, night light, countdown timer, volume control, and troubleshooting.</p>
	<p><a href="#">PH01-T Digital Wall Clock User Manual</a></p> <p>User manual for the JALL PH01-T Digital Wall Clock, covering installation, first use, device overview, time setting, alarm setting, temperature unit, screen brightness, font colors, night light, countdown, volume, daylight saving time, and FAQ.</p>

Documents - JALL – DC801

no relevant documents