

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [TREATLIFE](#) /

› [TREATLIFE 3 Way Smart Switch 4 Pack Instruction Manual](#)

**TREATLIFE 0756171583643**

# TREATLIFE 3 Way Smart Switch Instruction Manual

**Brand:** TREATLIFE | **Model:** 0756171583643

## 1. INTRODUCTION

Thank you for choosing the TREATLIFE 3 Way Smart Switch. This device allows you to effortlessly control your lighting from anywhere using the TREATLIFE App, voice commands with Alexa or Google Assistant, and traditional wall switch operation. It supports both single-pole and 3-way wiring configurations, offering versatile control for your home lighting.

## 2. WHAT'S IN THE Box

- 4 x 3-Way Smart Light Switch
- 4 x Wallplate
- 4 x 5 Wire Nuts
- 4 x 2 Screws
- 1 x User Manual

## 3. SPECIFICATIONS

Feature	Detail
Product Dimensions	3.3 x 4.84 x 1.57 inches
Item Model Number	0756171583643
Max Power	1250W
Output Current	10 Amps
Operating Voltage	120 Volts

Wireless Frequency	2.4GHz Wi-Fi (NOT 5GHz)
Circuit Type	3-way
Certifications	FCC Certified

## 4. IMPORTANT SAFETY INFORMATION

- **Neutral Wire Required:** Installation requires a neutral wire. Please ensure your house wiring includes a neutral wire before attempting installation.
- **No Dimming Support:** This 3-way smart light switch does not support dimming functions.
- **2.4GHz Wi-Fi Only:** Compatible only with 2.4GHz Wi-Fi networks. 5GHz networks are not supported.
- **Electrical Safety:** FCC certified with flame-retardant material and built-in overheat protection for added safety. Always turn off power at the circuit breaker before wiring.
- Consult a qualified electrician if you are unsure about any wiring procedures.

## 5. INSTALLATION

Follow these steps for a safe and successful installation:

1. **Turn off Power:** Locate your circuit breaker and turn off the power to the light switch you are replacing. Verify power is off using a voltage tester.
2. **Identify Wires:** Carefully remove the old switch. Label the Line/Load, Neutral, Ground, and Traveler wires using the provided wire labels.
3. **Wiring Diagram:** Refer to the wiring diagram below for connecting the TREATLIFE Smart Switch.



## Voice-activated Lighting

Control the lights in your house with just your voice



Figure 1: Wiring diagram for single-pole and 3-way configurations. Ensure neutral wire is connected.



## Remote Control

Control and access your home lighting from anywhere in the world



Device Sharing



Group Control



Schedules



Figure 2: Physical dimensions of the smart switch. Note that smart switches are generally larger than traditional switches.

For detailed wiring instructions, please refer to the [User Manual \(PDF\)](#).

## 6. SETUP

### 6.1 App Setup (TREATLIFE App)

1. Download the "TREATLIFE" App from your smartphone's app store.
2. Register or log in to your TREATLIFE account.
3. Add your smart switch by following the in-app instructions. Ensure your device is connected to a 2.4GHz Wi-Fi network.

### 6.2 Voice Assistant Integration (Alexa/Google Home)

Integrate your TREATLIFE Smart Switch with voice assistants for hands-free control.

Video: How to link your TreatLife APP to Amazon Alexa. This video demonstrates the steps to connect your TreatLife account

with Amazon Alexa for voice control.

For detailed steps on linking with Alexa or Google Assistant, refer to the TREATLIFE App's help section or the provided User Manual.

## 7. OPERATING THE SMART SWITCH

### 7.1 Manual Control

Press the switch button to turn lights ON or OFF, just like a traditional switch.

### 7.2 App Control

Use the TREATLIFE App on your smartphone to control lights from anywhere. Features include:

- **Remote ON/OFF:** Turn lights on or off remotely.
- **Scheduling:** Set schedules or countdowns for automated lighting based on daily routines.
- **Group Control:** Group multiple Treatlife switches to control all lights in your home simultaneously.
- **Device Sharing:** Share control of your smart switches with family members.
- **Away Mode:** Simulate occupancy while you are away to enhance home security.

### 7.3 Voice Control

Enjoy hands-free control using voice commands with Amazon Alexa or Google Assistant. Examples:

- "Alexa, turn on the living room light."
- "Hey Google, turn off the kitchen light."

## 8. MAINTENANCE

To ensure optimal performance and longevity of your smart switch:

- Keep the switch clean by wiping it with a soft, dry cloth. Avoid using harsh chemicals or abrasive cleaners.
- Regularly check for any loose connections or signs of wear.
- Ensure the switch is not exposed to excessive moisture or extreme temperatures.

## 9. TROUBLESHOOTING

### 9.1 Connectivity Issues

- Ensure your Wi-Fi network is 2.4GHz.
- Check if the Wi-Fi signal strength is strong enough at the switch's location.
- Restart your Wi-Fi router and the smart switch.

- If the indicator light is not blinking rapidly during setup, try resetting the switch (refer to the user manual for reset procedures).

## 9.2 Light Not Responding

- Verify that the circuit breaker is ON.
- Check all wire connections to ensure they are secure.
- Ensure the light bulb is functioning correctly.
- Confirm that the switch is properly paired with the TREATLIFE App and your voice assistant.

## 10. WARRANTY AND SUPPORT

TREATLIFE products are FCC certified and built with quality materials for reliability and security. For any questions, technical assistance, or warranty claims, please contact TREATLIFE customer support. Refer to the original product packaging or the official TREATLIFE website for specific warranty terms and contact information.

Shop confidently with TREATLIFE's friendly customer support.