

[Manuals.plus](#) /

› [MICTUNING](#) /

› MICTUNING Nema 14-50P Male Plug Connector Instruction Manual

MICTUNING 14-50P

MICTUNING Nema 14-50P Male Plug Connector Instruction Manual

Model: 14-50P

1. PRODUCT OVERVIEW

The MICTUNING Nema 14-50P Male Plug Connector is a robust 4-prong, 50 Amp, 125/250 Volt straight blade plug designed for heavy-duty applications. It serves as a replacement or new installation plug for various electrical equipment, including RVs, generators, and electric dryers. Constructed from flame-retardant ABS material and featuring solid brass blades, this connector ensures durability and optimal electrical conductivity.



Image 1.1: The MICTUNING Nema 14-50P Male Plug Connector, highlighting its ABS material, heavy-duty construction, pressure-proof design, and 125/250V rating.

2. SAFETY INFORMATION

WARNING: Electrical work can be hazardous. Improper installation or use can result in serious injury, death, or property damage. Always follow these safety guidelines:

- **Disconnect Power:** Before attempting any installation or wiring, ensure that the power source is completely disconnected and locked out to prevent accidental energization.
- **Qualified Personnel:** Installation should be performed by a qualified electrician or a knowledgeable individual with experience in electrical wiring.
- **Proper Wire Gauge:** Use appropriate wire gauges for 50 Amp applications as specified by local electrical codes. Using undersized wire can lead to overheating and fire hazards.
- **Local Codes:** Adhere to all national and local electrical codes and regulations.
- **Inspect Components:** Before installation, inspect the plug for any signs of damage. Do not use if damaged.
- **Secure Connections:** Ensure all wire connections are tight and secure to prevent arcing and overheating.

3. PACKAGE CONTENTS

- 1 x MICTUNING Nema 14-50P Male Plug Connector

4. INSTALLATION INSTRUCTIONS

Follow these steps to correctly wire the Nema 14-50P Male Plug Connector:

1. **Prepare the Cable:** Strip the outer jacket of your 4-conductor electrical cable (typically 6 AWG for 50A applications) to expose the individual insulated wires (Black, Red, White, Green/Bare). Strip approximately 3/4 inch of insulation from the end of each individual wire.
2. **Disassemble the Plug:** Unscrew the housing of the Nema 14-50P plug to separate the front and back sections, exposing the internal terminals.
3. **Identify Terminals:** Refer to the internal wiring diagram (Image 4.1) to identify the correct terminal for each wire. The terminals are typically marked or color-coded.
 - **Green Wire:** Connect to the ground terminal (typically marked 'G' or green screw).
 - **White Wire:** Connect to the neutral terminal (typically marked 'W' or silver screw).
 - **Black Wire:** Connect to one hot terminal (typically marked 'X' or brass screw).
 - **Red Wire:** Connect to the other hot terminal (typically marked 'Y' or brass screw).
4. **Connect Wires:** Insert each stripped wire end into its corresponding terminal and tighten the screw securely. Ensure no stray wire strands are present and that the insulation is close to the terminal without being pinched under the screw.
5. **Secure the Cable:** Route the cable through the strain relief mechanism at the back of the plug. Tighten the strain relief to secure the cable and prevent tension on the wire connections.
6. **Reassemble the Plug:** Carefully align the front and back sections of the plug housing and secure them with the screws. Ensure no wires are pinched during reassembly.



Image 4.1: Internal view of the Nema 14-50P plug, indicating the connection points for the Green (Ground), Black (Hot), Red (Hot), and White (Neutral) wires.

Maximum Conductivity



Solid brass blades ensure optimum conductivity

Image 4.2: Detail of the solid brass blades, designed for maximum conductivity and minimal electrical loss.

5. OPERATION

Once the Nema 14-50P plug is correctly wired and assembled, it is ready for use.

- **Connecting:** Align the prongs of the plug with the corresponding slots in a Nema 14-50R receptacle. Insert the plug firmly until it is fully seated.
- **Disconnecting:** Grasp the body of the plug and pull it straight out from the receptacle. Avoid pulling on the cable itself, as this can damage the wiring or the plug.

6. MAINTENANCE

Regular inspection and basic maintenance can extend the life of your plug connector:

- **Visual Inspection:** Periodically check the plug for any signs of physical damage, such as cracks in the housing, bent prongs, or discoloration from overheating.
- **Wire Connections:** If you suspect an issue, carefully open the plug (after disconnecting power) and check that all wire connections remain tight. Loose connections can cause resistance and heat buildup.

- **Cleaning:** Keep the plug clean and free from dirt, dust, and moisture. Use a dry cloth for cleaning. Do not use liquid cleaners on electrical components.
- **Storage:** When not in use, store the plug in a clean, dry environment away from extreme temperatures.

7. TROUBLESHOOTING

If you encounter issues with your Nema 14-50P plug, consider the following:

- **No Power:**
 - Verify the power source is active.
 - Check circuit breakers or fuses.
 - Inspect internal wiring for loose connections (refer to Section 4).
- **Overheating:**
 - Ensure the wire gauge is appropriate for 50 Amps.
 - Check for loose or corroded wire connections within the plug.
 - Confirm the connected appliance is not drawing more than 50 Amps.
- **Difficulty Fitting Wires:** Some heavy-gauge wires can be stiff. Ensure wires are properly stripped and twisted before inserting into terminals. If necessary, trim a small amount of insulation to allow for full insertion into the terminal without excess bare wire.
- **Bent Prongs:** If a prong becomes bent, carefully attempt to straighten it. If the prong shows signs of fatigue or cracking, replace the plug immediately to prevent poor connection and potential hazards.

8. SPECIFICATIONS

Feature	Specification
Brand	MICTUNING
Model	Nema 14-50P
Amperage	50 Amps
Voltage	125/250 Volts
Connector Type	4-Prong Male Plug
Number of Wires	4
Material	Acrylonitrile Butadiene Styrene (ABS)
Blades Material	Solid Brass
Specification Met	NEMA



Image 8.1: Dimensional drawing of the Nema 14-50P plug, indicating key measurements for fitment.

Fairly Solid

Made of reinforced flame retardant ABS material, durable to use



Image 8.2: Bottom view of the plug, displaying its NEMA rating and voltage/amperage specifications, emphasizing its solid construction.

9. WARRANTY AND SUPPORT

For warranty information, technical support, or any inquiries regarding your MICTUNING Nema 14-50P Male Plug Connector, please refer to the official MICTUNING website or contact their customer service directly. Keep your purchase receipt for warranty claims.

MICTUNING Official Website: [Visit MICTUNING Store on Amazon](#)