

[manuals.plus](#) /

› [ARENTI](#) /

› [ARENTI GO1 Wireless Outdoor Security Camera Instruction Manual](#)

ARENTI GO1

ARENTI GO1 Wireless Outdoor Security Camera Instruction Manual

Model: GO1

1. INTRODUCTION

The ARENTI GO1 is a 100% wireless, battery-powered outdoor security camera designed to provide reliable surveillance for your home. Featuring 1080P Full HD video, night vision, two-way audio, and IP65 weather resistance, this camera offers comprehensive monitoring capabilities. Its AI motion detection ensures you receive relevant alerts, keeping you informed about activity around your property.

2. WHAT'S IN THE Box

Carefully unpack the box and ensure all items are present. If any items are missing or damaged, please contact customer support.



GET IT ON
Google Play



Android



Camera 1X



Power adapter 1X




USB cable 1X



Screws 3X



Bracket (A) 1X



Bracket (B) 1X



Reset key 1X



Quick guide 1X

Image: Contents of the ARENTI GO1 package, including the camera, mounting options, charging cable, power adapter, and quick start guide.

- ARENTI GO1 Camera (1X)
- USB Cable (1X)
- Power Adapter (1X)
- Mounting Bracket (A) (1X)
- Mounting Bracket (B) (1X)
- Screws (3X)
- Reset Key (1X)
- Quick Guide (1X)

Video: An unboxing of the ARENTI GO1 camera, showing all included components and accessories.

3. PRODUCT OVERVIEW

The ARENTI GO1 camera is designed for ease of use and robust performance. It features a compact, wireless design with dual mounting options for flexible placement.

Let's make it easy

Upgraded Dual Mounting Options



Outdoor stand

Magnet stand

Image: The ARENTI GO1 camera shown with both the traditional outdoor stand and a magnetic stand for versatile installation.

Key Features:

- 1080P Full HD Video:** Provides clear and detailed video recordings.
- 145° Wide-Angle View:** Captures a broad area for comprehensive surveillance.
- Night Vision:** Equipped with infrared sensors for clear monitoring in low-light conditions.
- Two-Way Audio:** Allows for real-time communication with visitors or intruders.
- AI Motion Detection:** Intelligently detects human motion to reduce false alarms.
- IP65 Weather Resistance:** Durable design suitable for outdoor use in various weather conditions.
- 6700mAh Rechargeable Battery:** Offers long-lasting operation (30-180 days depending on usage).
- Local & Cloud Storage:** Supports SD card storage and optional cloud service.

Video: An introductory video highlighting the key features and benefits of the ARENTI GO1 camera.

4. SETUP

4.1. Charging the Camera

Before initial use, fully charge the ARENTI GO1 camera using the provided USB cable and power adapter. The battery is rechargeable and designed for long-term use.

Rechargeable Battery Powered

100% Wire-Free

Arenti **6700mAh**

Others **5000mAh**



Image: An internal view of the ARENTI GO1 camera, highlighting its 6700mAh rechargeable battery.

4.2. App Installation

Download the 'Arenti' app from your device's app store (Google Play Store for Android or Apple App Store for iOS). Ensure your smartphone is connected to a 2.4GHz Wi-Fi network, as the camera does not support 5GHz Wi-Fi.

4.3. Device Pairing

Follow these steps to pair your ARENTI GO1 camera with the app:

1. Open the Arenti app and sign up or log in to your account.
2. Tap the '+' icon to add a new device.
3. Select 'Battery Camera' from the device list.
4. Hold the device power button to start the device.
5. Press the [battery camera] button to wake the device if it is asleep.
6. Hold the RESET button on your device for 4-5 seconds (refer to the user manual for more details).
Wait for a flashing RED indicator light.
7. Select your 2.4GHz Wi-Fi network and enter the password.
8. Remove any protective film from the camera lens.

9. Tap 'Next' to show a QR code on your phone.
10. Hold your phone 5-8 inches (15-25cm) from the camera lens, allowing the camera to scan the QR code. A tone will be heard upon successful scan.
11. The app will then connect and register the device.

Video: A step-by-step guide on how to connect the ARENTI GO1 camera to the Arenti app.

4.4. Mounting Options

The ARENTI GO1 offers dual mounting options for versatile placement:

- **Outdoor Stand:** Use the metal bracket and screws for secure, permanent installation on walls or ceilings.
- **Magnetic Stand:** For temporary or easily adjustable placement, use the magnetic bracket. This allows for quick removal for charging.

5. OPERATING THE CAMERA

5.1. Live View & Recording

Once connected, access the live feed from your camera through the Arenti app. You can view real-time video and manually initiate recordings. The camera supports both event recording and 24-hour continuous recording to an SD card or cloud storage.



Image: The ARENTI GO1 camera illustrating its support for both cloud storage and local SD card storage.

5.2. Two-Way Audio

The camera features a built-in microphone and speaker, enabling two-way communication. Use the app to speak through the camera and hear responses from the other end.

Hear, and speak to visitors

Only support 2.4G Wi-Fi



Image: A user communicating with a delivery person via the ARENTI GO1 camera's two-way audio feature.

5.3. Motion Detection & Alerts

The ARENTI GO1 utilizes AI motion detection to identify human activity. When motion is detected, you will receive instant push notifications on your smartphone, allowing you to monitor suspicious activity promptly.

Video: Demonstrates the night vision capabilities of the ARENTI GO1 camera, showing clear footage in low-light conditions.

5.4. Night Vision

The camera automatically switches to night vision mode in low-light conditions, providing clear black-and-white footage up to 32 feet.

5.5. Smart Home Integration

The ARENTI GO1 camera is compatible with Amazon Alexa and Google Assistant. You can use voice commands to view the camera feed on compatible smart displays.

Video: Instructions on how to connect and use the ARENTI GO1 camera with Amazon Alexa.

5.6. Device Sharing

You can share access to your camera's live feed with family members through the Arenti app, allowing multiple users to monitor the property simultaneously.

Unlimited sharing

All family members can watch



Image: Illustration of multiple family members sharing and viewing the camera feed on various mobile devices.

6. MAINTENANCE

6.1. Battery Management

The 6700mAh rechargeable battery provides 30-180 days of operation depending on environmental factors and the number of wake-ups. Recharge the camera when the battery level is low. The app will notify you when charging is required.

6.2. Weather Resistance

The ARENTI GO1 camera has an IP65 rating, making it resistant to dust and water. It is designed to withstand various weather conditions, ensuring year-round security.

IP65 Weather Resistance

Operating temperature: $-4^{\circ}\text{F} \sim 122^{\circ}\text{F}$



Image: The ARENTI GO1 camera installed on an exterior wall, shown enduring rainfall, highlighting its IP65 weather resistance.

7. TROUBLESHOOTING

- Camera not connecting to Wi-Fi:** Ensure your Wi-Fi network is 2.4GHz. Move the camera closer to the router for a stronger signal. Reset the camera using the reset key and try pairing again.
- Poor night vision:** Ensure the camera lens is clean. Check for any obstructions that might reflect infrared light back into the lens.
- Short battery life:** Reduce motion detection sensitivity or frequency of alerts. Ensure the camera is not placed in an area with constant motion (e.g., tree branches moving in the wind).
- No alerts received:** Check app notification settings on your smartphone and within the Arenti app. Ensure the camera is connected to Wi-Fi.

8. SPECIFICATIONS

Feature	Detail
Model Name	GO1
Video Resolution	1080P Full HD
Viewing Angle	145 Degrees

Night Vision Range	32 Feet
Battery Capacity	6700 mAh Lithium Ion
Weather Resistance	IP65
Connectivity	2.4GHz Wi-Fi (not 5GHz)
Storage Options	SD Card (up to 128GB), Cloud Storage
Audio	2-Way Audio
Motion Detection	AI Motion Detection
Smart Home Compatibility	Amazon Alexa, Google Assistant
Dimensions	2.05 x 1.97 x 3.74 inches
Weight	6.7 ounces

9. WARRANTY & SUPPORT

The ARENTI GO1 camera comes with a manufacturer's warranty. Please refer to the warranty card included in your package for specific terms and conditions. For technical support, troubleshooting, or any inquiries, please visit the official ARENTI website or contact their customer service directly.