



[Manuals.plus](#) /

› [FEZIBO](#) /

› FEZIBO Electric Standing Desk Instruction Manual (Model SDE)

FEZIBO SDE

FEZIBO Electric Standing Desk Instruction Manual (Model SDE)

Brand: FEZIBO

INTRODUCTION

This manual provides detailed instructions for the assembly, operation, maintenance, and troubleshooting of your FEZIBO Electric Standing Desk, Model SDE. This height-adjustable desk is designed to enhance your workspace by allowing seamless transitions between sitting and standing positions.



Image: The FEZIBO Electric Standing Desk in black, set up in a modern home office with a laptop and headphones.

IMPORTANT SAFETY INFORMATION

Please read all safety instructions before use. Failure to follow these instructions may result in injury or damage to the product.

- The desk has a maximum weight capacity of 176 lbs (70 kg). Do not exceed this limit.
- Ensure the desk is stable and properly anchored to prevent tipping, especially when adjusting height or when heavy items are placed on it.
- The anti-collision technology is designed to prevent damage or injury by moving the desk 2cm in the opposite direction if it encounters obstacles while lifting or lowering. However, always be aware of your surroundings during operation.
- Keep children and pets away from the desk during operation.
- Do not sit or stand on the desk.
- Ensure all cables are properly managed to avoid entanglement or damage during height adjustments.

- Wipe with a damp or dry cloth for cleaning. Avoid harsh chemicals.

PARTS LIST

Before assembly, verify that all components are present and undamaged. Refer to the assembly video for visual identification of parts.



Image: An exploded view showing all individual components of the FEZIBO Electric Standing Desk, including the desktop halves, legs, frame, control panel, and hardware.

- Desktop (2 pieces)
- Desk Legs (2)
- Crossbar/Frame
- Control Panel
- Motor(s)
- Power Adapter

- Detachable Lockable Casters (Optional/Included)
- Assembly Tools (Hex key, Screwdriver - check package contents)
- Screws and Fasteners (Various sizes, labeled in instructions)
- Cable Management Tray/Hooks

SETUP AND ASSEMBLY

A detailed installation video is available to guide you through the assembly process. Please watch the entire video before beginning installation.

Your browser does not support the video tag.

Video: FEZIBO Standing Desk Installation Guide. This video provides a step-by-step visual guide for assembling your desk, including attaching the legs, crossbar, and desktop components.

Assembly Steps:

1. **Unpack and Identify Parts:** Carefully unpack all components and compare them against the parts list. Ensure all screws and tools are present.
2. **Assemble the Frame:** Attach the desk legs to the crossbar using the provided screws (e.g., M6*10). Ensure all connections are secure.
3. **Install the Drive Rod:** Insert the drive rod into the designated slots, connecting the two leg mechanisms.
4. **Attach the Desktop:** Place the desktop (two pieces) onto the assembled frame. Align the pre-drilled holes and secure the desktop using the appropriate screws (e.g., st4.8*13).
5. **Install Control Panel and Cable Management:** Mount the control panel and cable management tray/hooks to the underside of the desktop. Connect all motor and power cables as instructed.
6. **Connect Power:** Plug the power adapter into the desk and then into a wall outlet.

Note: The desktop comes in two pieces. Ensure they are correctly aligned before securing.

OPERATING INSTRUCTIONS

Your FEZIBO Electric Standing Desk features an intuitive control panel for easy height adjustment and memory settings.



Image: Close-up of the Smart Keypad control panel, showing Up/Down arrows and four memory buttons (1, 2, 3, 4).

Adjusting Height:

- **Manual Adjustment:** Use the **Up (^)** and **Down (v)** arrow buttons to manually raise or lower the desk to your desired height. The current height will be displayed on the control panel.
- The desk supports height adjustment between 27.3"-45.5" (30.3"-48.5" with detachable lockable casters included).

Setting Memory Heights:

The desk has 3 programmable memory height buttons (1, 2, 3) to save your preferred sitting and standing positions.

1. Adjust the desk to your desired height using the Up (^) or Down (v) buttons.
2. Press the **"S"** button. The display will show "S-".
3. Within 3 seconds, press one of the memory buttons (**1, 2, or 3**). The current height will be saved to that button.
4. To recall a saved height, simply press the corresponding memory button (1, 2, or 3). The desk will automatically move to the saved position.

Your browser does not support the video tag.

Video: FAQ: Reset, set memory height, adjust the desk legs - FEZIBO. This video demonstrates how to reset the desk, set memory heights, and adjust the desk legs.

MAINTENANCE

- **Cleaning:** Wipe the desk surfaces with a damp or dry cloth. Avoid using abrasive cleaners or harsh chemicals that could damage the finish.

- **Regular Checks:** Periodically check all screws and fasteners to ensure they are tight. Retighten if necessary.
- **Cable Management:** Ensure cables remain organized and free from entanglement to prevent damage during height adjustments.

TROUBLESHOOTING

If you encounter any issues with your FEZIBO Electric Standing Desk, refer to the solutions below or consult the troubleshooting video.

Your browser does not support the video tag.

Video: FEZIBO Troubleshooting and Solutions. This video covers common error codes and provides solutions for issues like the desk not moving, being tilted, or displaying error messages.

Common Issues and Solutions:

Issue: Desk Does Not Lift or Lower (E-1 Displayed)

This often indicates that a reset is required or the height of the legs is inconsistent after operation.

Solution: Reset the Desk Control Panel

1. Press and hold both the **"Up (^)"** and **"Down (v)"** buttons simultaneously for 5 seconds.
2. The desk will move to its lowest position and then slightly back up. Release the buttons once the movement stops.
3. Verify that the desk can now lift and lower smoothly.

Issue: Desktop Is Tilted

This can occur if the desk legs are not at the same height.

Solution: Adjust the Desk Legs

1. Manually press the adjustable leg down until it reaches its lowest position.
2. Confirm that both desk legs are now at the same height. Use a level if necessary.
3. Perform a reset as described in the "Desk Does Not Lift or Lower" section.

Issue: "ovr" Displayed (Overload)

This indicates that the load on the desktop exceeds the maximum weight capacity (176 lbs).

Solution: Remove items from the desktop until the total weight is less than 176 lbs. The desk should then resume normal operation.

Issue: "E-2" Displayed (Anti-Collision Triggered)

The anti-collision function has been triggered due to an obstacle.

Solution 1: Remove the obstacle. The desk should then resume normal operation.

Solution 2: Lower Sensitivity of Anti-Collision System

1. Keep pressing the "**S**" key for 10 seconds until the display shows "**A--**".
2. Pressing "**S**" again saves the setting.
3. Press the "**Up (^)**" key to adjust the number to "**15**" (lower sensitivity).
4. Press the "**Down (v)**" key until the display shows "**P--**".

Issue: "dut" Displayed (Duty Cycle Exceeded)

The desk has been operated continuously for too long, exceeding its duty cycle.

Solution: Allow the desk to rest for approximately 15 minutes before further operation. This allows the motor to cool down.

Issue: "E-3" Displayed (Motor Connection Failure)

This indicates that one or more motors are not properly connected to the control unit.

Solution:

1. Check whether any motors fail connected with control unit.
2. Please connect the main cable again, wait at least 5 seconds.
3. Connect all the plugs.
4. Perform a reset as described in the "Desk Does Not Lift or Lower" section.

Issue: "hot" Displayed (Motor Overheating)

The motor temperature protection has been triggered due to overheating.

Solution: Allow the desk to rest for approximately 15 minutes for the motor to cool down before further operation.

SPECIFICATIONS

Feature	Detail
Brand	FEZIBO
Model Number	SDE
Product Dimensions	24"D x 40"W x 27.16"H
Height Adjustment Range	27.3"-45.5" (30.3"-48.5" with casters)
Color	Black
Material	Alloy Steel, Wood (Laminated finish)

Weight Capacity	176 lbs (70 kg)
Lifting Mechanism	Electric
Special Features	Adjustable height, Ergonomic, Sturdy, Anti-Collision Technology, 3 Programmable Memory Heights
Noise Level	Under 50 dB during operation
Assembly Required	Yes
Recommended for Assembly	2 people

WARRANTY AND SUPPORT

Your FEZIBO Electric Standing Desk comes with a limited warranty and a money-back guarantee.

- **Warranty Type:** Limited
- **Manufacturer Warranty:** Money Back Guarantee
- **Customer Support:** For any questions, warranty concerns, or technical support during assembly and use, please do not hesitate to contact FEZIBO customer service.