

EMEET Luna Black

EMEET Luna Conference Speaker and Microphone User Manual

Model: Luna Black

Brand: EMEET

INTRODUCTION

The EMEET Luna Conference Speaker and Microphone is a versatile audio solution designed to enhance your communication experience in various settings, from personal home offices to larger conference rooms. Featuring advanced voice pickup and noise reduction technologies, it ensures clear and effective meetings for all participants.



Figure 1: EMEET Luna Conference Speaker and Microphone, showcasing its compact, circular design with intuitive control buttons and LED indicators on the top surface. A USB dongle is also visible.

WHAT'S IN THE BOX

Please verify that all components are present upon unboxing:

- EMEET Luna Conference Speaker
- USB Dongle (A200)
- USB Cable
- User Manual
- Carrying Case (implied by product images)

PRODUCT FEATURES

VoiceIA Noise Reduction Technology

The EMEET Luna incorporates exclusive upgraded VoiceIA technology, designed to effectively eliminate distracting background noises such as air conditioning hum, keyboard clicks, and general ambient sounds. This ensures your voice is clear and prominent during calls.



Figure 2: Visual representation of VoiceIA Noise Reduction, demonstrating how the technology isolates and reduces environmental noise while preserving the clarity of human speech.

Ultra-clear Sound & Speech Enhancement

Equipped with an auto-vocal-increase function, the EMEET Luna intelligently identifies the distance of the sound source and automatically adjusts the volume to achieve balanced audio output. This feature provides a smooth call experience and can reduce the need for prolonged headphone use. The speaker's maximum volume is 85 dB, suitable for larger conference rooms.

Ultra-clear Sound



Get Rid of Headaches Caused
by Using Headphones



Figure 3: Illustration highlighting the comfort and clarity of using the EMEET Luna speakerphone, offering an alternative to traditional headphones for extended calls.

Multi-Microphone Array & 360° Voice Pickup

The EMEET Luna features a 3-microphone array that provides 360° omnidirectional voice pickup, ensuring that all voices around the device are captured clearly. This full-duplex capability allows for natural, simultaneous conversation without interruptions.

360° Voice Pick-up

CNET

“ One of the
Best Speakerphones
in 2023 for Working from Home ”



Figure 4: The EMEET Luna speakerphone, emphasizing its 360° voice pickup capability, recognized by CNET as a top speakerphone for remote work.

Daisy Chain Functionality

For larger meetings, two EMEET Luna conference speakers can be connected via a special daisy-chain cable (sold separately, ASIN: [B087G5MFN1](#)). This expands the coverage area, supporting up to 16 attendees, and provides a more stable wired connection compared to wireless alternatives. The device also features an automatic shut-off after one hour of inactivity to conserve battery life.

Daisy Chain

Hook up 2 Luna to cover up to **16** People



Figure 5: Depiction of the daisy chain feature, showing how two Luna units can be linked to expand audio coverage for larger meeting spaces.

Multiple Connectivity Options & Portable Design

The EMEET Luna offers flexible connectivity via USB, Bluetooth, AUX, and a dedicated USB dongle. It is a plug-and-play device, requiring no driver installation, and is compatible with leading communication platforms such as Zoom, Skype for Business, and WebEx. Its full-metal, matte-colored casing, achieved through an advanced sandblasting process, provides a durable and professional aesthetic. The integrated dongle slot and portable design make it easy to carry and use anywhere.

Plug & Play



Figure 6: Overview of the EMEET Luna's diverse connectivity options, including USB, dongle, AUX, and Bluetooth, highlighting its plug-and-play convenience.

Simpler Youthful Design

Sandblasted Body is Designed
for Business People



Figure 7: The compact and portable design of the EMEET Luna, making it convenient for transport and use in various locations.

SETUP

Initial Setup

- Charging:** Before first use, fully charge the EMEET Luna using the provided USB cable. Connect the USB cable to the speakerphone and a power source (e.g., computer USB port, USB wall adapter). The LED indicators will show charging status.
- Power On:** Press and hold the power button () for a few seconds until the LED indicators light up.

Connecting to Devices

The EMEET Luna offers multiple ways to connect to your devices:

- **USB Connection (Plug & Play):**

- a. Connect the EMEET Luna to your computer using the supplied USB cable.
- b. The device will be automatically recognized by your operating system. No drivers are required.
- c. Select "EMEET Luna" as your audio input (microphone) and output (speaker) device in your computer's sound settings or conferencing software.

- **Bluetooth Connection:**

- a. Press the Bluetooth button () on the EMEET Luna until the LED indicators flash blue, indicating pairing mode.
- b. On your device (smartphone, tablet, computer), enable Bluetooth and search for "EMEET Luna" in the list of available devices.
- c. Select "EMEET Luna" to pair. Once connected, the blue LEDs will become solid.

- **USB Dongle Connection:**

- a. Insert the USB dongle (A200) into an available USB port on your computer.
- b. The EMEET Luna will automatically connect to the dongle. The LED indicators will show a solid blue light when connected.
- c. Select "EMEET Luna" as your audio input and output device in your computer's sound settings or conferencing software.

- **AUX Connection:**

- a. Connect an AUX cable (not included) from the AUX port on the EMEET Luna to the audio output port of your device.
- b. This connection is for audio output only; the microphone will not function via AUX.

The EMEET Luna is compatible with various leading conferencing platforms, including Zoom, Skype for Business, WebEx, Microsoft Teams, GoTo Meeting, FaceTime, and Google Meet.

OPERATING INSTRUCTIONS

Control Buttons Overview

Button Icon	Function	Description
	Power On/Off	Press and hold to power the device on or off.
	Bluetooth	Press to enter Bluetooth pairing mode.
←	Answer/End Call	Press to answer an incoming call or end an active call.
-	Volume Down	Decrease the speaker volume.
	Mute Microphone	Toggle microphone mute on/off. The LED indicator will change color when muted.
+	Volume Up	Increase the speaker volume.

Advanced Functions

- **VoicelA Noise Reduction:** This feature is typically active by default. If you experience excessive background noise, ensure the VoicelA function is enabled through the EMEETLink software (if available for your model) or by checking the device's current mode.
- **Directional Audio Indicators:** The LED lights on the device indicate the direction from which audio is being picked

up, allowing you to visually confirm the active microphone array.

- **Daisy Chain Mode:** To connect two EMEET Luna units for expanded coverage (up to 16 attendees), use the dedicated daisy-chain cable (sold separately). Connect one end of the cable to the "Daisy Chain In" port on the first unit and the other end to the "Daisy Chain Out" port on the second unit. Ensure both units are powered on.

MAINTENANCE

To ensure the longevity and optimal performance of your EMEET Luna speakerphone, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the device. Do not use liquid cleaners or aerosols directly on the speakerphone.
- **Storage:** When not in use, store the device in its provided carrying case to protect it from dust and physical damage.
- **Environment:** Avoid exposing the device to extreme temperatures, direct sunlight, high humidity, or corrosive substances. The device is not waterproof.
- **Battery Care:** For optimal battery life, avoid fully discharging the battery frequently. Charge the device regularly, even if not in constant use.

TROUBLESHOOTING

If you encounter issues with your EMEET Luna, please refer to the following common problems and solutions:

Problem	Possible Cause & Solution
No Sound / Microphone Not Working	<ul style="list-style-type: none">◦ Check Connection: Ensure the USB cable is securely connected, or Bluetooth is properly paired. If using the dongle, ensure it's inserted correctly.◦ Device Selection: Verify that "EMEET Luna" is selected as the default audio input and output device in your computer's sound settings and within your conferencing software (e.g., Zoom, Teams).◦ Volume Levels: Check both the device's volume buttons and your computer's system volume.◦ Mute Status: Ensure the microphone is not muted on the device or within the conferencing software.
Mute Button Not Syncing with Microsoft Teams	<ul style="list-style-type: none">◦ This is a known compatibility issue with some versions of Microsoft Teams. While the physical mute button on the device will mute the microphone, the visual indicator within the Teams application may not always synchronize. Always confirm your mute status directly within the Teams application.
Echo or Robotic Sound (when far from device)	<ul style="list-style-type: none">◦ Proximity: The optimal voice pickup range is typically within 3 feet. Moving closer to the device can improve clarity and reduce echo.◦ Room Acoustics: Hard surfaces can cause echoes. Consider using the device in a room with softer furnishings or acoustic treatments.◦ Daisy Chain Placement: If using daisy chain, ensure units are spread appropriately and not too close, which can cause feedback.

Problem	Possible Cause & Solution
Bluetooth Disconnection	<ul style="list-style-type: none"> Distance: Ensure the device is within the Bluetooth range (approx. 10 meters / 33 feet) of the connected device. Interference: Avoid strong electromagnetic interference from other electronic devices. Re-pair: Try unpairing and re-pairing the device.

SPECIFICATIONS

Feature	Detail
Model Name	Luna Black
Brand	EMEET
Material	Metal
Speaker Type	Computer
Special Features	USB Port, Built-In Microphone, Portable
Recommended Uses	Video Conference
Compatible Devices	Desktop (and other devices with USB/Bluetooth/AUX)
Controller Type	Button, Voice Control
Surround Sound Channel Configuration	2.0
Color	Luna Black
Product Dimensions	4.72"D x 4.72"W x 1.53"H
Item Weight	0.66 Pounds (10.6 ounces)
Waterproof	FALSE
Control Method	Voice
Wireless Communication Technology	Bluetooth
Speaker Size	4.7 Inches
Power Source	USB (or built-in rechargeable battery charged via USB)
Signal-to-Noise Ratio	80 dB
Number of Batteries	1 A batteries required (included)
Audio Driver Type	Dynamic Driver
Bluetooth Range	10 Meters (33 Feet)
Number of Microphones	3
Connectivity Protocol	Bluetooth, USB

Feature	Detail
Includes MP3 player?	No
Indoor/Outdoor Usage	Indoor
Manufacturer	Shenzhen eMeet technology Co.,Ltd.
Speaker Maximum Output Power	3 Watts
Mounting Type	Tabletop Mount
UPC	191893139370

WARRANTY AND SUPPORT

EMEET is committed to providing high-quality products and excellent customer service.

- **Manufacturer:** Shenzhen eMeet technology Co.,Ltd.
- **Warranty:** The EMEET Luna comes with a 2-year exclusive warranty. Please refer to the product packaging or EMEET's official website for detailed warranty terms and conditions.
- **Technical Support:** EMEET offers lifetime professional technical team support. For any inquiries or assistance, you can expect a quick reply within 24 hours.
- **Online Resources:** Visit the official EMEET website for updated drivers, firmware, FAQs, and additional support resources.

© 2025 EMEET. All rights reserved.

This manual is for informational purposes only. Specifications are subject to change without notice.

Documents - EMEET – Luna Black

no relevant documents